

4.

Instruction tables

Lists of instruction latencies, throughputs and micro-operation breakdowns for Intel, AMD and VIA CPUs

By Agner Fog. Copenhagen University College of Engineering.
Copyright © 1996 - 2010. Last updated 2010-09-25.

Contents

1	Introduction	3
1.1	Definition of terms	4
1.2	Microprocessor versions tested	5
2	List of instruction timings for P1 and PMMX	7
2.1	Integer instructions (P1 and PMMX)	7
2.2	Floating point instructions (P1 and PMMX)	9
2.3	MMX instructions (PMMX)	11
3	List of instruction timings and μ op breakdown for PPro, P2 and P3	12
3.1	Integer instructions (PPro, P2 and P3)	12
3.2	Floating point x87 instructions (PPro, P2 and P3)	15
3.3	Integer MMX instructions (P2 and P3)	16
3.4	Floating point XMM instructions (P3)	17
4	List of instruction timings and μ op breakdown for PM	19
4.1	Integer instructions	19
4.2	Floating point x87 instructions	23
4.3	Integer MMX and XMM instructions	24
4.4	Floating point XMM instructions	27
5	List of instruction timings and μ op breakdown for Core 2 (65nm)	30
5.1	Integer instructions	31
5.2	Floating point x87 instructions	35
5.3	Integer MMX and XMM instructions	37
5.4	Floating point XMM instructions	40
6	List of instruction timings and μ op breakdown for Core 2 (45nm)	44
6.1	Integer instructions	45
6.2	Floating point x87 instructions	49
6.3	Integer MMX and XMM instructions	51
6.4	Floating point XMM instructions	55
7	List of instruction timings and μ op breakdown for Core i7	58
7.1	Integer instructions	59
7.2	Floating point x87 instructions	64
7.3	Integer MMX and XMM instructions	66
7.4	Floating point XMM instructions	70
8	List of instruction timings and μ op breakdown for P4	73
8.1	integer instructions	74
8.2	Floating point x87 instructions	78
8.3	Integer MMX and XMM instructions	79
8.4	Floating point XMM instructions	81
9	List of instruction timings and μ op breakdown for P4E	83
9.1	Integer instructions	84
9.2	Floating point x87 instructions	88
9.3	Integer MMX and XMM instructions	90
9.4	Floating point XMM instructions	92
10	List of instruction timings and μ op breakdown for Atom	94
10.1	Integer instructions	94
10.2	Floating point x87 instructions	99

10.3 Integer MMX and XMM instructions	101
10.4 Floating point XMM instructions	103
11 List of instruction timings and μ op breakdown for VIA Nano 2000 series	105
11.1 Integer instructions.....	105
11.2 Floating point x87 instructions.....	109
11.3 Integer MMX and XMM instructions	111
11.4 Floating point XMM instructions	113
11.5 VIA-specific instructions	115
12 List of instruction timings and μ op breakdown for VIA Nano 3000 series	116
12.1 Integer instructions.....	116
12.2 Floating point x87 instructions.....	120
12.3 Integer MMX and XMM instructions	122
12.4 Floating point XMM instructions	124
12.5 VIA-specific instructions	126
13 Instruction timings and macro-operation breakdown for AMD K7	127
13.1 Integer instructions.....	127
13.2 Floating point x87 instructions.....	131
13.3 Integer MMX instructions	133
13.4 Floating point XMM instructions	134
13.5 3DNow instructions	135
14 Instruction timings and macro-operation breakdown for AMD K8	136
14.1 Integer instructions.....	136
14.2 Floating point x87 instructions.....	140
14.3 Integer MMX and XMM instructions	142
14.4 Floating point XMM instructions	144
14.5 3DNow instructions	145
15 Instruction timings and macro-operation breakdown for AMD K10	147
15.1 Integer instructions.....	147
15.2 Floating point x87 instructions.....	151
15.3 Integer MMX and XMM instructions	153
15.4 Floating point XMM instructions	155
15.5 3DNow instructions	156
Instruction set compatibility table	158
15.6 Explanation of instruction sets	159
16 Comparison of the different microprocessors	163
17 Literature	164
18 Copyright notice	164

1 Introduction

This is the fourth in a series of five manuals:

1. Optimizing software in C++: An optimization guide for Windows, Linux and Mac platforms.
2. Optimizing subroutines in assembly language: An optimization guide for x86 platforms.
3. The microarchitecture of Intel, AMD and VIA CPUs: An optimization guide for assembly programmers and compiler makers.
4. Instruction tables: Lists of instruction latencies, throughputs and micro-operation breakdowns for Intel, AMD and VIA CPUs.
5. Calling conventions for different C++ compilers and operating systems.

The latest versions of these manuals are always available from www.agner.org/optimize. Copyright conditions are listed on page 164 below.

The present manual contains tables of instruction latencies, throughputs and micro-operation breakdown and other tables Intel, AMD and VIA CPUs as an appendix to the preceding manuals.

The figures in the instruction tables represent the results of my measurements rather than the official values published by microprocessor vendors. Some values in my tables are higher or lower than the values published elsewhere. The discrepancies can be explained by the following factors:

- My figures are experimental values while figures published by microprocessor vendors may be based on theory or simulations.
- My figures are obtained with a particular test method under particular conditions. It is possible that different values can be obtained under other conditions.
- Some latencies are difficult or impossible to measure accurately, especially for memory access and type conversions that cannot be chained.
- Latencies for moving data from one execution unit to another are listed explicitly in some of my tables while they are included in the general latencies in some tables published by Intel.

Most values are the same in all microprocessor modes (real, virtual, protected, 16-bit, 32-bit, 64-bit). Values for far calls and interrupts may be different in different modes. Call gates have not been tested.

Instructions with a **LOCK** prefix have a long latency that depends on cache organization and possibly RAM speed. If there are multiple processors or cores or direct memory access (DMA) devices then all locked instructions will lock a cache line for exclusive access, which may involve RAM access. A **LOCK** prefix typically costs more than a hundred clock cycles, even on single-processor systems. This also applies to the **XCHG** instruction with a memory operand.

1.1 Definition of terms

Microarchitecture abbreviations

The tables in this manual are organized around the different kernel microarchitectures, not the commercial names of the microprocessors. Certain brand names are covering more than one microarchitecture, and some microarchitectures are sold under several different brand names. See manual 3: "The microarchitecture of Intel, AMD and VIA CPUs" for details.

Microprocessor name	Abbreviation
AMD Athlon	AMD Athlon
AMD Athlon 64, Opteron, etc., 64-bit	AMD K8
AMD Family 10h, Phenom, third generation Opteron	AMD K10
Intel Pentium (without name suffix)	P1
Intel Pentium MMX	PMMX
Intel Pentium Pro	PPro
Intel Pentium II	P2
Intel Pentium III	P3
Intel Pentium 4 (NetBurst)	P4
Intel Pentium 4 with EM64T, Pentium D, etc.	P4E
Intel Pentium M, Core Solo, Core Duo	PM
Intel Core 2	Core2
Intel Atom	Atom
VIA Nano	Nano

Operands

i = immediate constant, r = any general purpose register, r32 = 32-bit register, etc., mm = 64 bit mmx register, xmm = 128 bit xmm register, sr = segment register, m = any memory operand including indirect operands, m64 means 64-bit memory operand, etc.

Latency

The latency of an instruction is the delay that the instruction generates in a dependence chain. The measurement unit is clock cycles. The numbers listed are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably. Floating point operands are presumed to be normal numbers. Denormal numbers, NAN's and infinity may increase the latencies by possibly more than 100 clock cycles except in move, shuffle and Boolean instructions. Floating point overflow, underflow, denormal or NAN results give a similar delay. A missing value in the table means that the value has not been measured or that it cannot be measured in a meaningful way.

Reciprocal throughput

The throughput is the maximum number of instructions of the same kind that can be executed per clock cycle when the operands of each instruction are independent of the preceding instructions. The values listed are the reciprocals of the throughputs, i.e. the average number of clock cycles per instruction when the instructions are not part of dependence chains. For example, a reciprocal throughput of 2 for FMUL means that a new FMUL instruction can start executing 2 clock cycles after a previous FMUL. A reciprocal throughput of 0.25 for ADD means that the execution units can handle 4 integer additions per clock cycle.

The reason for listing the reciprocal values is that this makes comparisons between latency and throughput easier. The reciprocal throughput is also called issue latency.

The values listed are for a single thread or a single core. A missing value in the table means that the value has not been measured.

μops

Uop or μop is an abbreviation for micro-operation. Processors with out-of-order cores are capable of splitting complex instructions into μops. For example, a read-modify instruction may be split into a read-μop and a modify-μop. The number of μops that an instruction generates is important when certain bottlenecks in the pipeline limit the number of μops per clock cycle.

Execution unit

The execution core of a microprocessor has several execution units. Each execution unit can handle a particular category of μops, for example floating point additions. The information about which execution unit a particular μop goes to can be useful for two purposes. Firstly, two μops cannot execute simultaneously if they need the same execution unit. And secondly, some processors have a latency of an extra clock cycle when the result of a μop executing in one execution unit is needed as input for a μop in another execution unit.

Execution port

The execution units are clustered around a few execution ports on most Intel processors. Each μop passes through an execution port to get to the right execution unit. An execution port can be a bottleneck because it can only handle one μop at a time. Two μops cannot execute simultaneously if they need the same execution port, even if they are going to different execution units.

Backwards compatibility

This indicates which instruction set an instruction belongs to. The instruction is only available in processors that support this instruction set. The different instruction sets are listed in chapter 0 page 146. Availability in processors prior to 80386 does not apply for 32-bit and 64-bit operands. Availability in the MMX instruction set does not apply to 128-bit packed integer instructions, which require SSE2. Availability in the SSE instruction set does not apply to double precision floating point instructions, which require SSE2.

32-bit instructions are available in 80386 and later. 64-bit instructions in general purpose registers are available only under 64-bit operating systems. Instructions that use XMM registers (SSE and later) are only available under operating systems that support this register set. It is necessary to test which microprocessor the code is running on, and possibly also which operating system, before using an instruction that is not available on all processors or all operating systems.

1.2 Microprocessor versions tested

The tables in this manual are based on testing of the following microprocessors:

Processor name	Family number (hex)	Model number (hex)	Comment
AMD K7 Athlon	6	6	Step. 2, rev. A5
AMD K8 Opteron	F	5	Stepping A
AMD K10 Opteron	10	2	2350, step. 1
Intel Pentium	5	2	
Intel Pentium MMX	5	4	Stepping 4
Intel Pentium II	6	6	
Intel Pentium III	6	7	
Intel Pentium 4	F	2	Stepping 4, rev. B0

Intel Pentium 4 EM64T	F	4	Xeon. Stepping 1
Intel Pentium M	6	D	Stepping 6, rev. B1
Intel Core Duo	6	E	Not fully tested
Intel Core 2 (65 nm)	6	F	T5500, Step. 6, rev. B2
Intel Core 2 (45 nm)	6	17	E8400, Step. 6
Intel Core i7	6	1A	i7-920, Step. 5, rev. D0
Intel Atom 330	6	1C	Step. 2
VIA Nano L2200	6	F	Step. 2
VIA Nano L3050	6	F	Step. 8 (prerelease sample)

2 List of instruction timings for P1 and PMMX

2.1 Integer instructions (P1 and PMMX)

Explanation of column headings:

Operands: r = register, accum = al, ax or eax, m = memory, i = immediate data, sr = segment register, m32 = 32 bit memory operand, etc.

Clock cycles: The numbers are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably.

Pairability: u = pairable in u-pipe, v = pairable in v-pipe, uv = pairable in either pipe, np = not pairable.

Instruction	Operands	Clock cycles	Pairability
NOP		1	uv
MOV	r/m, r/m/i	1	uv
MOV	r/m, sr	1	np
MOV	sr, r/m	>= 2 b)	np
MOV	m, accum	1	uv h)
XCHG	(E)AX, r	2	np
XCHG	r, r	3	np
XCHG	r, m	>15	np
XLAT		4	np
PUSH	r/i	1	uv
POP	r	1	uv
PUSH	m	2	np
POP	m	3	np
PUSH	sr	1 b)	np
POP	sr	>= 3 b)	np
PUSHF		3-5	np
POPF		4-6	np
PUSHA POPA		5-9 i)	np
PUSHAD POPAD		5	np
LAHF SAHF		2	np
MOVSX MOVZX	r, r/m	3 a)	np
LEA	r, m	1	uv
LDS LES LFS LGS LSS	m	4 c)	np
ADD SUB AND OR XOR	r, r/i	1	uv
ADD SUB AND OR XOR	r, m	2	uv
ADD SUB AND OR XOR	m, r/i	3	uv
ADC SBB	r, r/i	1	u
ADC SBB	r, m	2	u
ADC SBB	m, r/i	3	u
CMP	r, r/i	1	uv
CMP	m, r/i	2	uv
TEST	r, r	1	uv
TEST	m, r	2	uv
TEST	r, i	1	f)

TEST	m, i	2	np
INC DEC	r	1	uv
INC DEC	m	3	uv
NEG NOT	r/m	1/3	np
MUL IMUL	r8/r16/m8/m16	11	np
MUL IMUL	all other versions	9 d)	np
DIV	r8/m8	17	np
DIV	r16/m16	25	np
DIV	r32/m32	41	np
IDIV	r8/m8	22	np
IDIV	r16/m16	30	np
IDIV	r32/m32	46	np
CBW CWDE		3	np
CWD CDQ		2	np
SHR SHL SAR SAL	r, i	1	u
SHR SHL SAR SAL	m, i	3	u
SHR SHL SAR SAL	r/m, CL	4/5	np
ROR ROL RCR RCL	r/m, 1	1/3	u
ROR ROL	r/m, i(><1)	1/3	np
ROR ROL	r/m, CL	4/5	np
RCR RCL	r/m, i(><1)	8/10	np
RCR RCL	r/m, CL	7/9	np
SHLD SHRD	r, i/CL	4 a)	np
SHLD SHRD	m, i/CL	5 a)	np
BT	r, r/i	4 a)	np
BT	m, i	4 a)	np
BT	m, i	9 a)	np
BTR BTS BTC	r, r/i	7 a)	np
BTR BTS BTC	m, i	8 a)	np
BTR BTS BTC	m, r	14 a)	np
BSF BSR	r, r/m	7-73 a)	np
SETcc	r/m	1/2 a)	np
JMP CALL	short/near	1 e)	v
JMP CALL	far	>= 3 e)	np
conditional jump	short/near	1/4/5/6 e)	v
CALL JMP	r/m	2/5 e	np
RETN		2/5 e	np
RETN	i	3/6 e)	np
RETF		4/7 e)	np
RETF	i	5/8 e)	np
J(E)CXZ	short	4-11 e)	np
LOOP	short	5-10 e)	np
BOUND	r, m	8	np
CLC STC CMC CLD STD		2	np
CLI STI		6-9	np
LODS		2	np
REP LODS		7+3*n g)	np
STOS		3	np
REP STOS		10+n g)	np
MOVS		4	np
REP MOVS		12+n g)	np

SCAS		4	np
REP(N)E SCAS		9+4*n g)	np
CMPS		5	np
REP(N)E CMPS		8+4*n g)	np
BSWAP	r	1 a)	np
CPUID		13-16 a)	np
RDTSC		6-13 a) j)	np

Notes:

- This instruction has a **0FH** prefix which takes one clock cycle extra to decode on a P1 unless preceded by a multi-cycle instruction.
- versions with **FS** and **GS** have a **0FH** prefix. see note a.
- versions with **SS**, **FS**, and **GS** have a **0FH** prefix. see note a.
- versions with two operands and no immediate have a **0FH** prefix, see note a.
- high values are for mispredicted jumps/branches.
- only pairable if register is **AL**, **AX** or **EAX**.
- add one clock cycle for decoding the repeat prefix unless preceded by a multi-cycle instruction (such as **CLD**).
- pairs as if it were writing to the accumulator.
- 9 if **SP** divisible by 4 (imperfect pairing).
- on P1: 6 in privileged or real mode; 11 in non-privileged; error in virtual mode.
On PMMX: 8 and 13 clocks respectively.

2.2 Floating point instructions (P1 and PMMX)

Explanation of column headings:

Operands: r = register, m = memory, m32 = 32-bit memory operand, etc.

Clock cycles: The numbers are minimum values. Cache misses, misalignment, denormal operands, and exceptions may increase the clock counts considerably.

Pairability: + = pairable with **FXCH**, np = not pairable with **FXCH**.

i-ov: Overlap with integer instructions. i-ov = 4 means that the last four clock cycles can overlap with subsequent integer instructions.

fp-ov: Overlap with floating point instructions. fp-ov = 2 means that the last two clock cycles can overlap with subsequent floating point instructions. (**WAIT** is considered a floating point instruction here)

Instruction	Operand	Clock cycles	Pairability	i-ov	fp-ov
FLD	r/m32/m64	1	+	0	0
FLD	m80	3	np	0	0
FBLD	m80	48-58	np	0	0
FST(P)	r	1	np	0	0
FST(P)	m32/m64	2 m)	np	0	0
FST(P)	m80	3 m)	np	0	0
FBSTP	m80	148-154	np	0	0
FILD	m	3	np	2	2
FIST(P)	m	6	np	0	0
FLDZ FLD1		2	np	0	0

FLDPI FLDL2E etc.		5 s)	np	2	2
FNSTSW	AX/m16	6 q)	np	0	0
FLDCW	m16	8	np	0	0
FNSTCW	m16	2	np	0	0
FADD(P)	r/m	3	+	2	2
FSUB(R)(P)	r/m	3	+	2	2
FMUL(P)	r/m	3	+	2	2 n)
FDIV(R)(P)	r/m	19/33/39 p)	+	38 o)	2
FCHS FABS		1	+	0	0
FCOM(P)(P) FUCOM	r/m	1	+	0	0
FIADD FISUB(R)	m	6	np	2	2
FIMUL	m	6	np	2	2
FIDIV(R)	m	22/36/42 p)	np	38 o)	2
FICOM	m	4	np	0	0
FTST		1	np	0	0
FXAM		17-21	np	4	0
FPREM		16-64	np	2	2
FPREM1		20-70	np	2	2
FRNDINT		9-20	np	0	0
FSCALE		20-32	np	5	0
EXTRACT		12-66	np	0	0
FSQRT		70	np	69 o)	2
FSIN FCOS		65-100 r)	np	2	2
FSINCOS		89-112 r)	np	2	2
F2XM1		53-59 r)	np	2	2
FYL2X		103 r)	np	2	2
FYL2XP1		105 r)	np	2	2
FPTAN		120-147 r)	np	36 o)	0
FPATAN		112-134 r)	np	2	2
FNOP		1	np	0	0
FXCH	r	1	np	0	0
FINCSTP FDECSTP		2	np	0	0
FFREE	r	2	np	0	0
FNCLEX		6-9	np	0	0
FNINIT		12-22	np	0	0
FNSAVE	m	124-300	np	0	0
FRSTOR	m	70-95	np	0	0
WAIT		1	np	0	0

Notes:

- m) The value to store is needed one clock cycle in advance.
- n) 1 if the overlapping instruction is also an **FMUL**.
- o) Cannot overlap integer multiplication instructions.
- p) **FDIV** takes 19, 33, or 39 clock cycles for 24, 53, and 64 bit precision respectively.
FIDIV takes 3 clocks more. The precision is defined by bit 8-9 of the floating point control word.
- q) The first 4 clock cycles can overlap with preceding integer instructions.
- r) Clock counts are typical. Trivial cases may be faster, extreme cases may be slower.
- s) May be up to 3 clocks more when output needed for **FST**, **FCHS**, or **FABS**.

2.3 MMX instructions (PMMX)

A list of MMX instruction timings is not needed because they all take one clock cycle, except the MMX multiply instructions which take 3. MMX multiply instructions can be pipelined to yield a throughput of one multiplication per clock cycle.

The [EMMS](#) instruction takes only one clock cycle, but the first floating point instruction after an [EMMS](#) takes approximately 58 clocks extra, and the first MMX instruction after a floating point instruction takes approximately 38 clocks extra. There is no penalty for an MMX instruction after [EMMS](#) on the PMMX.

There is no penalty for using a memory operand in an MMX instruction because the MMX arithmetic unit is one step later in the pipeline than the load unit. But the penalty comes when you store data from an MMX register to memory or to a 32-bit register: The data have to be ready one clock cycle in advance. This is analogous to the floating point store instructions.

All MMX instructions except [EMMS](#) are pairable in either pipe. Pairing rules for MMX instructions are described in manual 3: "The microarchitecture of Intel, AMD and VIA CPUs".

3 List of instruction timings and μ ops breakdown for PPro, P2 and P3

Explanation of column headings:

Operands: i = immediate data, r = register, mm = 64 bit mmx register, xmm = 128 bit xmm register, sr = segment register, m = memory, m32 = 32-bit memory operand, etc.

μ ops: The number of μ ops that the instruction generates for each execution port.

p0: Port 0: ALU, etc.

p1: Port 1: ALU, jumps

p01: Instructions that can go to either port 0 or 1, whichever is vacant first.

p2: Port 2: load data, etc.

p3: Port 3: address generation for store

p4: Port 4: store data

Latency: This is the delay that the instruction generates in a dependence chain. (This is not the same as the time spent in the execution unit. Values may be inaccurate in situations where they cannot be measured exactly, especially with memory operands). The numbers are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably. Floating point operands are presumed to be normal numbers. Denormal numbers, NAN's and infinity increase the delays by 50-150 clocks, except in XMM move, shuffle and Boolean instructions. Floating point overflow, underflow, denormal or NAN results give a similar delay.

Reciprocal throughput: The average number of clock cycles per instruction for a series of independent instructions of the same kind.

3.1 Integer instructions (PPro, P2 and P3)

Instruction	Operands	μ ops						Latency	Reciprocal throughput
		p0	p1	p01	p2	p3	p4		
MOV	r,r/i			1					
MOV	r,m				1				
MOV	m,r/i					1	1		
MOV	r,sr			1					
MOV	m,sr			1		1	1		
MOV	sr,r	8						5	
MOV	sr,m	7			1			8	
MOVSX MOVZX	r,r			1					
MOVSX MOVZX	r,m				1				
CMOVcc	r,r	1		1					
CMOVcc	r,m	1		1	1				
XCHG	r,r			3					
XCHG	r,m			4	1	1	1	high b)	
XLAT				1	1				
PUSH	r/i			1		1	1		

POP	r			1	1				
POP	(E)SP			2	1				
PUSH	m			1	1	1	1		
POP	m			5	1	1	1		
PUSH	sr			2		1	1		
POP	sr			8	1				
PUSHF(D)		3		11		1	1		
POPF(D)		10		6	1				
PUSHA(D)				2		8	8		
POPA(D)				2	8				
LAHF SAHF				1					
LEA	r,m	1						1 c)	
LDS LES LFS LGS									
LSS	m			8	3				
ADD SUB AND OR XOR	r,r/i			1					
ADD SUB AND OR XOR	r,m			1	1				
ADD SUB AND OR XOR	m,r/i			1	1	1	1		
ADC SBB	r,r/i			2					
ADC SBB	r,m			2	1				
ADC SBB	m,r/i			3	1	1	1		
CMP TEST	r,r/i			1					
CMP TEST	m,r/i			1	1				
INC DEC NEG NOT	r			1					
INC DEC NEG NOT	m			1	1	1	1		
AAA AAS DAA DAS			1						
AAD		1		2				4	
AAM		1	1	2				15	
IMUL	r,(r),(i)	1						4	1
IMUL	(r),m	1			1			4	1
DIV IDIV	r8	2		1				19	12
DIV IDIV	r16	3		1				23	21
DIV IDIV	r32	3		1				39	37
DIV IDIV	m8	2		1	1			19	12
DIV IDIV	m16	2		1	1			23	21
DIV IDIV	m32	2		1	1			39	37
CBW CWDE				1					
CWD CDQ		1							
SHR SHL SAR ROR									
ROL	r,i/CL	1							
SHR SHL SAR ROR									
ROL	m,i/CL	1			1	1	1		
RCR RCL	r,l	1		1					
RCR RCL	r8,i/CL	4		4					
RCR RCL	r16/32,i/CL	3		3					
RCR RCL	m,l	1		2	1	1	1		
RCR RCL	m8,i/CL	4		3	1	1	1		
RCR RCL	m16/32,i/CL	4		2	1	1	1		
SHLD SHRD	r,r,i/CL	2							
SHLD SHRD	m,r,i/CL	2		1	1	1	1		
BT	r,r/i			1					
BT	m,r/i	1		6	1				

BTR BTS BTC	r,r/i			1					
BTR BTS BTC	m,r/i	1		6	1	1	1		
BSF BSR	r,r		1	1					
BSF BSR	r,m		1	1	1				
SETcc	r			1					
SETcc	m			1		1	1		
JMP	short/near		1						2
JMP	far	21			1				
JMP	r		1						2
JMP	m(near)		1		1				2
JMP	m(far)	21			2				
conditional_jump	short/near		1						2
CALL	near		1	1		1	1		2
CALL	far	28			1	2	2		
CALL	r		1	2		1	1		2
CALL	m(near)		1	4	1	1	1		2
CALL	m(far)	28			2	2	2		
RETN			1	2	1				2
RETN	i		1	3	1				2
RETF		23			3				
RETF	i	23			3				
J(E)CXZ	short		1	1					
LOOP	short	2	1	8					
LOOP(N)E	short	2	1	8					
ENTER	i,0			12		1	1		
ENTER	a,b	ca.	18	+4b		b-1	2b		
LEAVE				2	1				
BOUND	r,m	7		6	2				
CLC STC CMC				1					
CLD STD				4					
CLI		9							
STI		17							
INTO				5					
LODS					2				
REP LODS				10+6n					
STOS					1	1	1		
REP STOS				ca. 5n	a)				
MOVS				1	3	1	1		
REP MOVS				ca. 6n	a)				
SCAS				1	2				
REP(N)E SCAS				12+7n					
CMPS				4	2				
REP(N)E CMPS				12+9n					
BSWAP	r	1		1					
NOP (90)				1					0.5
Long NOP (0F-1F-mod00rm)				1					1
CPUID		23-48							
RDTSC		31							
IN		18						>300	
OUT		18						>300	
PREFETCHNTA d)	m				1				

PREFETCHT0/1/2 d)	m				1				
SFENCE d)						1	1		6

Notes:

- a) Faster under certain conditions: see manual 3: "The microarchitecture of Intel, AMD and VIA CPUs".
- b) Has an implicit LOCK prefix.
- c) 3 if constant without base or index register
- d) P3 only.

3.2 Floating point x87 instructions (PPro, P2 and P3)

Instruction	Operands	μ ops						Latency	Reciprocal throughput
		p0	p1	p01	p2	p3	p4		
FLD	r	1							
FLD	m32/64				1			1	
FLD	m80	2			2				
FBLD	m80	38			2				
FST(P)	r	1							
FST(P)	m32/m64					1	1	1	
FSTP	m80	2				2	2		
FBSTP	m80	165				2	2		
FXCH	r							0	$\frac{1}{3}$ f)
FILD	m	3			1			5	
FIST(P)	m	2				1	1	5	
FLDZ		1							
FLD1 FLDPI FLDL2E etc.		2							
FCMOVcc	r	2						2	
FNSTSW	AX	3						7	
FNSTSW	m16	1				1	1		
FLDCW	m16	1		1	1			10	
FNSTCW	m16	1				1	1		
FADD(P) FSUB(R)(P)	r	1						3	1
FADD(P) FSUB(R)(P)	m	1			1			3-4	1
FMUL(P)	r	1						5	2 g)
FMUL(P)	m	1			1			5-6	2 g)
FDIV(R)(P)	r	1						38 h)	37
FDIV(R)(P)	m	1			1			38 h)	37
FABS		1							
FCHS		3						2	
FCOM(P) FUCOM	r	1						1	
FCOM(P) FUCOM	m	1			1			1	
FCOMPP FUCOMPP		1		1				1	
FCOMI(P) FUCOMI(P)	r	1						1	
FCOMI(P) FUCOMI(P)	m	1			1			1	
FIADD FISUB(R)	m	6			1				
FIMUL	m	6			1				
FIDIV(R)	m	6			1				
FICOM(P)	m	6			1				
FTST		1						1	
FXAM		1						2	
FPREM		23							

FPREM1		33							
FRNDINT		30							
FSCALE		56							
FXTRACT		15							
FSQRT		1						69	e,i)
FSIN FCOS		17-97						27-103	e)
FSINCOS		18-110						29-130	e)
F2XM1		17-48						66	e)
FYL2X		36-54						103	e)
FYL2XP1		31-53						98-107	e)
FPTAN		21-102						13-143	e)
FPATAN		25-86						44-143	e)
FNOP		1							
FINCSTP FDECSTP		1							
FFREE	r	1							
FFREEP	r	2							
FNCLEX				3					
FNINIT		13							
FNSAVE		141							
FRSTOR		72							
WAIT				2					

Notes:

- e) Not pipelined
- f) **FXCH** generates 1 μ op that is resolved by register renaming without going to any port.
- g) **FMUL** uses the same circuitry as integer multiplication. Therefore, the combined throughput of mixed floating point and integer multiplications is 1 **FMUL** + 1 **IMUL** per 3 clock cycles.
- h) **FDIV** latency depends on precision specified in control word: 64 bits precision gives latency 38, 53 bits precision gives latency 32, 24 bits precision gives latency 18. Division by a power of 2 takes 9 clocks. Reciprocal throughput is 1/(latency-1).
- i) Faster for lower precision.

3.3 Integer MMX instructions (P2 and P3)

Instruction	Operands	μ ops						Latency	Reciprocal throughput
		p0	p1	p01	p2	p3	p4		
MOVD MOVQ	r,r			1				1	0.5
MOVD MOVQ	mm,m32/64				1				1
MOVD MOVQ	m32/64,mm					1	1		1
PADD PSUB PCMP	mm,mm			1				1	0.5
PADD PSUB PCMP	mm,m64			1	1				1
PMUL PMADD	mm,mm	1						3	1
PMUL PMADD	mm,m64	1			1			3	1
PAND(N) POR PXOR	mm,mm			1				1	0.5
PAND(N) POR PXOR	mm,m64			1	1				1
PSRA PSRL PSLL	mm,mm/i		1					1	1
PSRA PSRL PSLL	mm,m64		1		1				1
PACK PUNPCK	mm,mm		1					1	1
PACK PUNPCK	mm,m64		1		1				1
EMMS		11						6 k)	
MASKMOVQ d)	mm,mm			1		1	1	2-8	2 - 30

PMOVMSKB d)	r32,mm		1					1	1
MOVNTQ d)	m64,mm					1	1		1 - 30
PSHUFW d)	mm,mm,i		1					1	1
PSHUFW d)	mm,m64,i		1		1			2	1
PEXTRW d)	r32,mm,i		1	1				2	1
PINSRW d)	mm,r32,i		1					1	1
PINSRW d)	mm,m16,i		1		1			2	1
PAVGB PAVGW d)	mm,mm			1				1	0.5
PAVGB PAVGW d)	mm,m64			1	1			2	1
PMIN/MAXUB/SW d)	mm,mm			1				1	0.5
PMIN/MAXUB/SW d)	mm,m64			1	1			2	1
PMULHUW d)	mm,mm	1						3	1
PMULHUW d)	mm,m64	1			1			4	1
PSADBW d)	mm,mm	2		1				5	2
PSADBW d)	mm,m64	2		1	1			6	2

Notes:

d) P3 only.

k) The delay can be hidden by inserting other instructions between [EMMS](#) and any subsequent floating point instruction.

3.4 Floating point XMM instructions (P3)

Instruction	Operands	μops						Latency	Reciprocal throughput
		p0	p1	p01	p2	p3	p4		
MOVAPS	xmm,xmm			2				1	1
MOVAPS	xmm,m128				2			2	2
MOVAPS	m128,xmm					2	2	3	2
MOVUPS	xmm,m128				4			2	4
MOVUPS	m128,xmm		1			4	4	3	4
MOVSS	xmm,xmm			1				1	1
MOVSS	xmm,m32			1	1			1	1
MOVSS	m32,xmm					1	1	1	1
MOVHPS MOVLPs	xmm,m64			1				1	1
MOVHPS MOVLPs	m64,xmm					1	1	1	1
MOVLHPS MOVHLPS	xmm,xmm			1				1	1
MOVMSKPS	r32,xmm	1						1	1
MOVNTPS	m128,xmm					2	2		2 - 15
CVTPI2PS	xmm,mm		2					3	1
CVTPI2PS	xmm,m64		2		1			4	2
CVT(T)PS2PI	mm,xmm		2					3	1
CVTPS2PI	mm,m128		1		2			4	1
CVTSI2SS	xmm,r32		2		1			4	2
CVTSI2SS	xmm,m32		2		2			5	2
CVT(T)SS2SI	r32,xmm		1		1			3	1
CVTSS2SI	r32,m128		1		2			4	2
ADDPS SUBPS	xmm,xmm		2					3	2
ADDPS SUBPS	xmm,m128		2		2			3	2
ADDSS SUBSS	xmm,xmm		1					3	1
ADDSS SUBSS	xmm,m32		1		1			3	1
MULPS	xmm,xmm	2						4	2

MULPS	xmm,m128	2			2			4	2
MULSS	xmm,xmm	1						4	1
MULSS	xmm,m32	1			1			4	1
DIVPS	xmm,xmm	2						48	34
DIVPS	xmm,m128	2			2			48	34
DIVSS	xmm,xmm	1						18	17
DIVSS	xmm,m32	1			1			18	17
AND(N)PS ORPS XORPS	xmm,xmm		2					2	2
AND(N)PS ORPS XORPS	xmm,m128		2		2			2	2
MAXPS MINPS	xmm,xmm		2					3	2
MAXPS MINPS	xmm,m128		2		2			3	2
MAXSS MINSS	xmm,xmm		1					3	1
MAXSS MINSS	xmm,m32		1		1			3	1
CMPccPS	xmm,xmm		2					3	2
CMPccPS	xmm,m128		2		2			3	2
CMPccSS	xmm,xmm		1					3	1
CMPccSS	xmm,m32		1		1			3	1
COMISS UCOMISS	xmm,xmm		1					1	1
COMISS UCOMISS	xmm,m32		1		1			1	1
SQRTPS	xmm,xmm	2						56	56
SQRTPS	xmm,m128	2			2			57	56
SQRTSS	xmm,xmm	2						30	28
SQRTSS	xmm,m32	2			1			31	28
RSQRTPS	xmm,xmm	2						2	2
RSQRTPS	xmm,m128	2			2			3	2
RSQRTSS	xmm,xmm	1						1	1
RSQRTSS	xmm,m32	1			1			2	1
RCPPS	xmm,xmm	2						2	2
RCPPS	xmm,m128	2			2			3	2
RCPSS	xmm,xmm	1						1	1
RCPSS	xmm,m32	1			1			2	1
SHUFPS	xmm,xmm,i		2	1				2	2
SHUFPS	xmm,m128,i		2		2			2	2
UNPCKHPS UNPCKLPS	xmm,xmm		2	2				3	2
UNPCKHPS UNPCKLPS	xmm,m128		2		2			3	2
LDMXCSR	m32	11						15	15
STMXCSR	m32	6						7	9
FXSAVE	m4096	116						62	
FXRSTOR	m4096	89						68	

4 List of instruction timings and μ ops breakdown for PM

Explanation of column headings:

Operands: i = immediate data, r = register, mm = 64 bit mmx register, xmm = 128 bit xmm register, sr = segment register, m = memory, m32 = 32-bit memory operand, etc.

μ ops fused domain: The number of μ ops at the decode, rename, allocate and retirement stages in the pipeline. Fused μ ops count as one.

μ ops unfused domain: The number of μ ops for each execution port. Fused μ ops count as two.

p0: Port 0: ALU, etc.

p1: Port 1: ALU, jumps

p01: Can go to either port 0 or port 1, whichever is vacant first

p2: Port 2: load data, etc.

p3: Port 3: address generation for store

p4: Port 4: store data

Latency: This is the delay that the instruction generates in a dependence chain. (This is not the same as the time spent in the execution unit. Values may be inaccurate in situations where they cannot be measured exactly, especially with memory operands). The numbers are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably. Floating point operands are presumed to be normal numbers. Denormal numbers, NAN's and infinity increase the delays by 50-150 clocks, except in XMM move, shuffle and Boolean instructions. Floating point overflow, underflow, denormal or NAN results give a similar delay.

Reciprocal throughput: The average number of clock cycles per instruction for a series of independent instructions of the same kind in one thread.

4.1 Integer instructions

Instruction	Operands	μ ops fused domain	μ ops unfused domain						Latency	Reciprocal throughput
			p0	p1	p01	p2	p3	p4		
Move instructions										
MOV	r,r/i	1			1					0.5
MOV	r,m	1				1				1
MOV	m,r	1					1	1		1
MOV	m,i	2					1	1		1
MOV	r,sr	1			1					
MOV	m,sr	2			1		1	1		
MOV	sr,r	8	8						5	
MOV	sr,m	8	7			1			8	

MOVNTI	m,r32	2					1	1		2
MOVSX MOVZX	r,r	1			1				1	0.5
MOVSX MOVZX	r,m	1				1				1
CMOVcc	r,r	2	1		1				2	1.5
CMOVcc	r,m	2	1		1	1				
XCHG	r,r	3			3				2	1.5
XCHG	r,m	7			4	1	1	1	high b)	
XLAT		2			1	1				1
PUSH	r	1					1	1	1	1
PUSH	i	2					1	1	1	1
PUSH	m	2				1	1	1	2	1
PUSH	sr	2			1		1	1		
PUSHF(D)		16	3		11		1	1		6
PUSHA(D)		18			2		8	8	8	8
POP	r	1				1				
POP	(E)SP	3			2	1				
POP	m	2				1	1	1	2	1
POP	sr	10			9	1				
POPF(D)		17	10		6	1				16
POPA(D)		10			2	8			7	7
LAHF SAHF		1			1				1	1
SALC		2	1	1						1
LEA	r,m	1	1						1	1
BSWAP	r	2	1		1					
LDS LES LFS LGS LSS	m	11			8	3				
PREFETCHNTA	m	1				1				1
PREFETCHT0/1/2	m	1				1				1
SFENCE/LFENCE/MFENCE		2					1	1		6
IN			18						>300	
OUT			18						>300	
Arithmetic instructions										
ADD SUB	r,r/i	1			1				1	0.5
ADD SUB	r,m	1			1	1			2	1
ADD SUB	m,r/i	3			1	1	1	1		1
ADC SBB	r,r/i	2		1	1				2	2
ADC SBB	r,m	2		1	1	1				
ADC SBB	m,r/i	7			4	1	1	1		
CMP	r,r/i	1			1				1	0.5
CMP	m,r	1			1	1			1	1
CMP	m,i	2			1	1				1
INC DEC NEG NOT	r	1			1				1	0.5
INC DEC NEG NOT	m	3			1	1	1	1		
AAA AAS DAA DAS		1		1						
AAD		3	1		2				2	
AAM		4	1	1	2				15	
MUL IMUL	r8	1	1						4	1
MUL IMUL	r16/r32	3	3						5	1
IMUL	r,r	1	1						4	1
IMUL	r,r,i	1	1						4	1
MUL IMUL	m8	1	1			1			4	1

MUL IMUL	m16/m32	3	3			1			5	1
IMUL	r,m	1	1			1			4	1
IMUL	r,m,i	2	1			1			4	1
DIV IDIV	r8	5	4		1				15-16 c)	12
DIV IDIV	r16	4	3		1				15-24 c)	12-20 c)
DIV IDIV	r32	4	3		1				15-39 c)	12-20 c)
DIV IDIV	m8	6	4		1	1			15-16 c)	12
DIV IDIV	m16	5	3		1	1			15-24 c)	12-20 c)
DIV IDIV	m32	5	3		1	1			15-39 c)	12-20 c)
CBW CWDE		1		1					1	1
CWD CDQ		1		1					1	1
Logic instructions										
AND OR XOR	r,r/i	1			1				1	0.5
AND OR XOR	r,m	1			1	1			2	1
AND OR XOR	m,r/i	3			1	1	1	1		1
TEST	r,r/i	1			1				1	0.5
TEST	m,r	1			1	1			1	1
TEST	m,i	2			1	1				1
SHR SHL SAR ROR ROL	r,i/CL	1	1						1	1
SHR SHL SAR ROR ROL	m,i/CL	3	1			1	1	1		
RCR RCL	r,l	2	1		1				2	2
RCR	r8,i/CL	9	5		4				11	
RCL	r8,i/CL	8	4		4				10	
RCR RCL	r16/32,i/CL	6	3		3				9	9
RCR RCL	m,l	7	2		2	1	1	1		
RCR	m8,i/CL	12	6		3	1	1	1		
RCL	m8,i/CL	11	5		3	1	1	1		
RCR RCL	m16/32,i/CL	10	5		2	1	1	1		
SHLD SHRD	r,r,i/CL	2	2						2	2
SHLD SHRD	m,r,i/CL	4	1		1	1	1	1		
BT	r,r/i	1		1					1	1
BT	m,r	8			7	1				
BT	m,i	2		1		1				
BTR BTS BTC	r,r/i	1		1						
BTR BTS BTC	m,r	10			7	1	1	1	6	
BTR BTS BTC	m,i	3		1		1	1	1		
BSF BSR	r,r	2		1	1					
BSF BSR	r,m	2		1	1	1				
SETcc	r	1		1						
SETcc	m	2		1			1	1		
CLC STC CMC		1		1						1
CLD STD		4			4					7
Control transfer instructions										
JMP	short/near	1		1						1
JMP	far	22	21			1				28
JMP	r	1		1						1
JMP	m(near)	2		1		1				2
JMP	m(far)	25	23			2				31
conditional jump	short/near	1		1						1

J(E)CXZ	short	2		1	1					1
LOOP	short	11	2	1	8					6
LOOP(N)E	short	11	2	1	8					6
CALL	near	4		1	1		1	1		2
CALL	far	32	27			1	2	2		27
CALL	r	4		1	2		1	1		9
CALL	m(near)	4		1		1	1	1		2
CALL	m(far)	35	29			2	2	2		30
RETN		2		1	2	1				2
RETN	i	3		1	1	1				2
RETF		27	24			3				30
RETF	i	27	24			3				30
BOUND	r,m	15	7		6	2				8
INTO		5			5					4
String instructions										
LODS		2				2				4
REP LODS		6n			10+6n					0.5
STOS		3				1	1	1		1
REP STOS		5n			ca. 5n	a)				0.7
MOVS		6			1	3	1	1		0.7
REP MOVS		6n			ca. 6n	a)				0.5
SCAS		3			1	2				1.3
REP(N)E SCAS		7n			12+7n					0.6
CMPS		6			4	2				0.7
REP(N)E CMPS		9n			12+9n					0.5
Other										
NOP (90)		1			1					0.5
NOP (0F 1F mod000rm)		1			1					1
PAUSE		2			2					
CLI			9							
STI			17							
ENTER	i,0	12			10		1	1		
ENTER	a,b		ca.	18	+4b		b-1	2b		
LEAVE		3			2	1				
CPUID		38-59	38-59						ca. 130	
RDTSC		13	13							42

Notes:

- a) Faster under certain conditions: see manual 3: "The microarchitecture of Intel, AMD and VIA CPUs".
- b) Has an implicit LOCK prefix.
- c) High values are typical, low values are for round divisors. Core Solo/Duo is more efficient than Pentium M in cases with round values that allow an early-out algorithm.

4.2 Floating point x87 instructions

Instruction	Operands	jops fused domain	jops unfused domain						Latency	Reciprocal throughput
Move instructions			p0	p1	p01	p2	p3	p4		
FLD	r	1	1						1	
FLD	m32/64	1				1			1	
FLD	m80	4	2			2				
FBLD	m80	40	38			2				
FST(P)	r	1	1							
FST(P)	m32/m64	1					1	1	1	
FSTP	m80	6	2				2	2		3
FBSTP	m80	169	165				2	2		167
FXCH	r	1							0	0.33 f)
FILD	m	4	3			1			5	2
FIST(P)	m	4	2				1	1	5	2
FISTTP g)	m	4	2				1	1	5	2
FLDZ		1	1							
FLD1 FLDPI FLDL2E etc.		2	2							
FCMOVcc	r	2	2						2	
FNSTSW	AX	3	3						7	3
FNSTSW	m16	2	1				1	1		
FLDCW	m16	3	1		1	1				19
FNSTCW	m16	3	1				1	1		3
FINCSTP FDECSTP		1	1						1	
FFREE	r	1	1							1
FFREEP	r	2	2							2
FNSAVE		142	142							131
FRSTOR		72	72							91
Arithmetic instructions										
FADD(P) FSUB(R)(P)	r	1			1				3	1
FADD(P) FSUB(R)(P)	m	1			1	1			3	1
FMUL(P)	r	1	1						5	2
FMUL(P)	m	1	1			1			5	2
FDIV(R)(P)	r	1	1						9-38 c)	8-37 c)
FDIV(R)(P)	m	1	1			1			9-38 c)	8-37 c)
FABS		1	1						1	1
FCHS		1	1						1	1
FCOM(P) FUCOM	r	1		1					1	1
FCOM(P) FUCOM	m	1		1		1			1	1
FCOMPP FUCOMPP		2		1	1				1	1
FCOMI(P) FUCOMI(P)	r	1		1					1	1
FIADD FISUB(R)	m	6	3	1	1	1			3	3
FIMUL	m	6	5			1			5	3
FIDIV(R)	m	6	5			1			9-38 c)	8-37 c)
FICOM(P)	m	6	3	2		1				4
FTST		1		1						1

FXAM		1		1					1
FPREM FPREM1		26	26					37	
FRNDINT		15	15					19	
Math									
FSCALE		28	28					43	
FXTRACT		15			15			9	
FSQRT		1	1					9 h)	8
FSIN FCOS		80-100	80-100					80-110	
FSINCOS		90-110	90-110					100-130	
F2XM1		ca. 20	ca. 20					ca. 45	
FYL2X		ca. 40	ca. 40					ca. 60	
FYL2XP1		ca. 55	ca. 55					ca. 65	
FPTAN		ca. 100	ca. 100					ca. 140	
FPATAN		ca. 85	ca. 85					ca. 140	
Other									
FNOP		1	1						1
WAIT		2		1	1				1
FNCLEX		3	3						13
FNINIT		14	14						27

Notes:

- c) High values are typical, low values are for low precision or round divisors.
- f) **FXCH** generates 1 μ op that is resolved by register renaming without going to any port.
- g) SSE3 instruction only available on Core Solo and Core Duo.

4.3 Integer MMX and XMM instructions

Instruction	Operands	μops fused domain	μops unfused domain						Latency	Reciprocal throughput
			p0	p1	p01	p2	p3	p4		
Move instructions										
MOVD	r32,mm	1			1				1	0.5
MOVD	mm,r32	1			1				1	0.5
MOVD	mm,m32	1				1				1
MOVD	m32,mm	1					1	1		1
MOVD	r32,xmm	1		1					1	1
MOVD	xmm,r32	2			2					1
MOVD	xmm,m32	2			1	1				1
MOVD	m32, xmm	1					1	1		1
MOVQ	mm,mm	1			1					0.5
MOVQ	mm,m64	1				1				1
MOVQ	m64,mm	1					1	1		1
MOVQ	xmm,xmm	2			2				1	1
MOVQ	xmm,m64	2			1	1				1
MOVQ	m64, xmm	1					1	1		1
MOVDQA	xmm, xmm	2			2				1	1

MOVDQA	xmm, m128	2				2				2
MOVDQA	m128, xmm	2					2	2		2
MOVDQU	xmm, m128	4			2	2				2-10
MOVDQU	m128, xmm	8			5-6		2-3	2-3		4-20
LDDQU g)	xmm, m128	4								2
MOVDQ2Q	mm, xmm	1		1					1	1
MOVQ2DQ	xmm,mm	2		1	1				1	1
MOVNTQ	m64,mm	1					1	1		2
MOVNTDQ	m128,xmm	4					2	2		3
PACKSSWB/DW PACKUSWB	mm,mm	1	1						1	1
PACKSSWB/DW PACKUSWB	mm,m64	1	1			1			1	1
PACKSSWB/DW PACKUSWB	xmm,xmm	3	2	1					2	2
PACKSSWB/DW PACKUSWB	xmm,m128	4	1	1		2			2	2
PUNPCKH/LBW/WD/DQ	mm,mm	1	1						1	1
PUNPCKH/LBW/WD/DQ	mm,m64	1	1			1				1
PUNPCKH/LBW/WD/DQ	xmm,xmm	2	2						2	2
PUNPCKH/LBW/WD/DQ	xmm,m128	3	1			2				2
PUNPCKHQDQ	xmm,xmm	2		1	1				1	1
PUNPCKHQDQ	xmm, m128	3		1		2				1
PUNPCKLQDQ	xmm,xmm	1		1					1	1
PUNPCKLQDQ	xmm, m128	1				1				1
PSHUFW	mm,mm,i	1	1						1	1
PSHUFW	mm,m64,i	2	1			1				1
PSHUFD	xmm,xmm,i	3	2	1					2	2
PSHUFD	xmm,m128,i	4	1	1		2				2
PSHUFL/HW	xmm,xmm,i	2	1	1						1
PSHUFL/HW	xmm, m128,i	3		1		2				1
MASKMOVQ	mm,mm	3			1		1	1		
MASKMOVDQU	xmm,xmm	8		1			2	2		
PMOVMskb	r32,mm	1	1						1	1
PMOVMskb	r32,xmm	1	1	j)					1	1
PEXTRW	r32,mm,i	2	1	1					2	1
PEXTRW	r32,xmm,i	4	2	2					3	2
PINSRW	mm,r32,i	1	1						1	1
PINSRW	xmm,r32,i	2	2						1	2
Arithmetic instructions										
PADD/SUB(U)(S)B/W/D	mm,mm	1			1				1	0.5
PADD/SUB(U)(S)B/W/D	mm,m64	1			1	1				1
PADD/SUB(U)(S)B/W/D	xmm,xmm	2			2				1	1
PADD/SUB(U)(S)B/W/D	xmm,m128	4			2	2				2
PADDQ PSUBQ	mm,mm	2			2				2	1
PADDQ PSUBQ	mm,m64	2			2	1				1
PADDQ PSUBQ	xmm,xmm	4			4				2	2
PADDQ PSUBQ	xmm,m128	6			4	2				2
PCMPEQ/GTB/W/D	mm,mm	1			1				1	0.5
PCMPEQ/GTB/W/D	mm,m64	1			1	1				1
PCMPEQ/GTB/W/D	xmm,xmm	2			2				1	1
PCMPEQ/GTB/W/D	xmm,m128	2			2	2				2
PMULL/HW PMULHUW	mm,mm	1			1				3	1
PMULL/HW PMULHUW	mm,m64	1			1	1			3	1

PMULL/HW PMULHUW	xmm,xmm	2			2			3	2
PMULL/HW PMULHUW	xmm,m128	4			2	2		3	2
PMULUDQ	mm,mm	1	1					4	1
PMULUDQ	mm,m64	1	1			1		4	1
PMULUDQ	xmm,xmm	2	2					4	2
PMULUDQ	xmm,m128	4	2			2		4	2
PMADDWD	mm,mm	1			1			3	1
PMADDWD	mm,m64	1			1	1		3	1
PMADDWD	xmm,xmm	2			2			3	2
PMADDWD	xmm,m128	4			2	2		3	2
PAVGB/W	mm,mm	1			1			1	0.5
PAVGB/W	mm,m64	1			1	1			1
PAVGB/W	xmm,xmm	2			2			1	1
PAVGB/W	xmm,m128	4			2	2			2
PMIN/MAXUB/SW	mm,mm	1			1			1	0.5
PMIN/MAXUB/SW	mm,m64	1			1	1			1
PMIN/MAXUB/SW	xmm,xmm	2			2			1	1
PMIN/MAXUB/SW	xmm,m128	4			2	2			2
PSADBW	mm,mm	2			2			4	1
PSADBW	mm,m64	2			2	1		4	1
PSADBW	xmm,xmm	4			4			4	2
PSADBW	xmm,m128	6			4	2		4	2
Logic instructions									
PAND(N) POR PXOR	mm,mm	1			1			1	0.5
PAND(N) POR PXOR	mm,m64	1			1	1			1
PAND(N) POR PXOR	xmm,xmm	2			2			1	1
PAND(N) POR PXOR	xmm,m128	4			2	2			2
PSLL/RL/RAW/D/Q	mm,mm/i	1	1					1	1
PSLL/RL/RAW/D/Q	mm,m64	1	1			1			1
PSLL/RL/RAW/D/Q	xmm,i	2	2					2	2
PSLL/RL/RAW/D/Q	xmm,xmm	3	2	1				2	2
PSLL/RL/RAW/D/Q	xmm,m128	3		1		2			2
PSLL/RLDQ	xmm,i	4	3	1				3	3
Other									
EMMS		11			11			6 k)	6

Notes:

- g) SSE3 instruction only available on Core Solo and Core Duo.
- j) Also uses some execution units under port 1.
- k) You may hide the delay by inserting other instructions between [EMMS](#) and any subsequent floating point instruction.

4.4 Floating point XMM instructions

Instruction	Operands	jops fused domain	jops unfused domain						Latency	Reciprocal throughput
Move instructions			p0	p1	p01	p2	p3	p4		
MOVAPS/D	xmm,xmm	2			2				1	1
MOVAPS/D	xmm,m128	2				2			2	2
MOVAPS/D	m128,xmm	2					2	2	3	2
MOVUPS/D	xmm,m128	4				4			2	2
MOVUPS/D	m128,xmm	8			4		2	2	3	4
MOVSS/D	xmm,xmm	1		1					1	1
MOVSS/D	xmm,m32/64	2		1		1			1	1
MOVSS/D	m32/64,xmm	1					1	1	1	1
MOVHPS/D MOVLPS/D	xmm,m64	1		1		1			1	1
MOVHPS/D MOVLPS/D	m64,xmm	1					1	1	1	1
MOVLHPS MOVHLPS	xmm,xmm	1		1					1	1
MOVMSKPS/D	r32,xmm	1	1	j)					2	1
MOVNTPS/D	m128,xmm	2					2	2		3
SHUFPS/D	xmm,xmm,i	3	2	1					2	2
SHUFPS/D	xmm,m128,i	4	1	1		2				2
MOVDDUP g)	xmm,xmm	2							1	1
MOVSH/LDUP g)	xmm,xmm	2							2	2
MOVSH/LDUP g)	xmm,m128	4								
UNPCKH/LPS	xmm,xmm	4	2	2					3-4	5
UNPCKH/LPS	xmm,m128	4		2		2				5
UNPCKH/LPD	xmm,xmm	2		1	1				1	1
UNPCKH/LPD	xmm,m128	3		1	1	1				1
Conversion										
CVTTPS2PD	xmm,xmm	4	2	2					3	3
CVTTPS2PD	xmm,m64	4	1	2		1				3
CVTPD2PS	xmm,xmm	4	3	1					4	3
CVTPD2PS	xmm,m128	6	3	1		2				3
CVTSD2SS	xmm,xmm	2			2				4	2
CVTSD2SS	xmm,m64	3			2	1				2
CVTSS2SD	xmm,xmm	2	2						2	2
CVTSS2SD	xmm,m64	3	2			1				2
CVTDQ2PS	xmm,xmm	2			2				3	2
CVTDQ2PS	xmm,m128	4			2	2				2
CVT(T) PS2DQ	xmm,xmm	2			2				3	2
CVT(T) PS2DQ	xmm,m128	4			2	2				2
CVTDQ2PD	xmm,xmm	4			4				4	2
CVTDQ2PD	xmm,m64	5			4	1				2
CVT(T)PD2DQ	xmm,xmm	4			4				4	3
CVT(T)PD2DQ	xmm,m128	6			4	2				3
CVTP12PS	xmm,mm	1		1					3	1
CVTP12PS	xmm,m64	2		1		1				1
CVT(T)PS2PI	mm,xmm	1		1					3	1

CVT(T)PS2PI	mm,m128	2		1		1				1
CVTP12PD	xmm,mm	4	2	2					5	2
CVTP12PD	xmm,m64	5	2	2		1				2
CVT(T) PD2PI	mm,xmm	3			3				4	2
CVT(T) PD2PI	mm,m128	5			3	2				2
CVTSI2SS	xmm,r32	2	1	1					4	1
CVT(T)SS2SI	r32,xmm	2		1	1				4	1
CVT(T)SS2SI	r32,m32	3		1	1	1				1
CVTSI2SD	xmm,r32	2	1	1					4	1
CVTSI2SD	xmm,m32	3	1	1		1				1
CVT(T)SD2SI	r32,xmm	2		1	1				4	1
CVT(T)SD2SI	r32,m64	3		1	1	1				1
Arithmetic										
ADDSS/D SUBSS/D	xmm,xmm	1			1				3	1
ADDSS/D SUBSS/D	xmm,m32/64	2			1	1			3	1
ADDPS/D SUBPS/D	xmm,xmm	2			2				3	2
ADDPS/D SUBPS/D	xmm,m128	4			2	2			3	2
ADDSUBPS/D g)	xmm,xmm	2			2				3	2
HADDPS HSUBPS g)	xmm,xmm	6?			?				7	4
HADDPD HSUBPD g)	xmm,xmm	3			3				4	2
MULSS	xmm,xmm	1	1						4	1
MULSD	xmm,xmm	1	1						5	2
MULSS	xmm,m32	2	1			1			4	1
MULSD	xmm,m64	2	1			1			5	2
MULPS	xmm,xmm	2	2						4	2
MULPD	xmm,xmm	2	2						5	4
MULPS	xmm,m128	4	2			2			4	2
MULPD	xmm,m128	4	2			2			5	4
DIVSS	xmm,xmm	1	1						9-18 c)	8-17 c)
DIVSD	xmm,xmm	1	1						9-32 c)	8-31 c)
DIVSS	xmm,m32	2	1			1			9-18 c)	8-17 c)
DIVSD	xmm,m64	2	1			1			9-32 c)	8-31 c)
DIVPS	xmm,xmm	2	2						16-34 c)	16-34 c)
DIVPD	xmm,xmm	2	2						16-62 c)	16-62 c)
DIVPS	xmm,m128	4	2			2			16-34 c)	16-34 c)
DIVPD	xmm,m128	4	2			2			16-62 c)	16-62 c)
CMPccSS/D	xmm,xmm	1			1				3	1
CMPccSS/D	xmm,m32/64	2			1	1				1
CMPccPS/D	xmm,xmm	2			2				3	2
CMPccPS/D	xmm,m128	4			2	2				2
COMISS/D UCOMISS/D	xmm,xmm	1		1						1
COMISS/D UCOMISS/D	xmm,m32/64	2		1		1				1
MAXSS/D MINSS/D	xmm,xmm	1			1				3	1
MAXSS/D MINSS/D	xmm,m32/64	2			1	1			3	1
MAXPS/D MINPS/D	xmm,xmm	2			2				3	2
MAXPS/D MINPS/D	xmm,m128	4			2	2			3	2
RCPS	xmm,xmm	1		1					3	1
RCPS	xmm,m32	2		1		1				1
RCPPS	xmm,xmm	2		2					3	2
RCPPS	xmm,m128	4		2		2				2

Math										
SQRTSS	xmm,xmm	2	2						6-30	4-28
SQRTSS	xmm,m32	3	2			1				4-28
SQRTSD	xmm,xmm	1	1						5-58	4-57
SQRTSD	xmm,m64	2	1			1				4-57
SQRTPS	xmm,xmm	2	2						8-56	16-55
SQRTPD	xmm,xmm	2	2						16-114	16-114
SQRTPS	xmm,m128	4	2			2				16-55
SQRTPD	xmm,m128	4	2			2				16-114
RSQRTSS	xmm,xmm	1		1					3	1
RSQRTSS	xmm,m32	2		1		1				1
RSQRTPS	xmm,xmm	2		3					3	2
RSQRTPS	xmm,m128	4		2		2				2
Logic										
AND/ANDN/OR/XORPS/D	xmm,xmm	2			2				1	1
AND/ANDN/OR/XORPS/D	xmm,m128	4			2	2				1
Other										
LDMXCSR	m32	9	9							20
STMXCSR	m32	6	6							12
FXSAVE	m4096	118	32				43	43		63
FXRSTOR	m4096	87	43			44				72

Notes:

- c) High values are typical, low values are for round divisors.
- g) SSE3 instruction only available on Core Solo and Core Duo.
- j) Also uses some execution units under port 1.

5 List of instruction timings and μ op breakdown for Core 2 (65nm)

Explanation of column headings:

Operands: i = immediate data, r = register, mm = 64 bit mmx register, xmm = 128 bit xmm register, (x)mm = mmx or xmm register, sr = segment register, m = memory, m32 = 32-bit memory operand, etc.

μ ops fused domain: The number of μ ops at the decode, rename, allocate and retirement stages in the pipeline. Fused μ ops count as one.

μ ops unfused domain: The number of μ ops for each execution port. Fused μ ops count as two. Fused macro-ops count as one. The instruction has μ op fusion if the sum of the numbers listed under p015 + p2 + p3 + p4 exceeds the number listed under μ ops fused domain. An x under p0, p1 or p5 means that at least one of the μ ops listed under p015 can optionally go to this port. For example, a 1 under p015 and an x under p0 and p5 means one μ op which can go to either port 0 or port 5, whichever is vacant first. A value listed under p015 but nothing under p0, p1 and p5 means that it is not known which of the three ports these μ ops go to.

p015: The total number of μ ops going to port 0, 1 and 5.

p0: The number of μ ops going to port 0 (execution units).

p1: The number of μ ops going to port 1 (execution units).

p5: The number of μ ops going to port 5 (execution units).

p2: The number of μ ops going to port 2 (memory read).

p3: The number of μ ops going to port 3 (memory write address).

p4: The number of μ ops going to port 4 (memory write data).

Unit: Tells which execution unit cluster is used. An additional delay of 1 clock cycle is generated if a register written by a μ op in the integer unit (int) is read by a μ op in the floating point unit (float) or vice versa. flt→int means that an instruction with multiple μ ops receive the input in the float unit and delivers the output in the int unit. Delays for moving data between different units are included under latency when they are unavoidable. For example, `movd eax, xmm0` has an extra 1 clock delay for moving from the XMM-integer unit to the general purpose integer unit. This is included under latency because it occurs regardless of which instruction comes next. Nothing listed under unit means that additional delays are either unlikely to occur or unavoidable and therefore included in the latency figure.

Latency: This is the delay that the instruction generates in a dependence chain. The numbers are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably. Floating point operands are presumed to be normal numbers. Denormal numbers, NAN's and infinity increase the delays very much, except in XMM move, shuffle and Boolean instructions. Floating point overflow, underflow, denormal or NAN results give a similar delay. The time unit used is core clock cycles, not the reference clock cycles given by the time stamp counter.

Reciprocal throughput: The average number of core clock cycles per instruction for a series of independent instructions of the same kind in the same thread.

5.1 Integer instructions

Instruction	Operands	jops fused domain	jops unfused domain							Latency	Reciprocal throughput
Move instructions			p015	p0	p1	p5	p2	p3	p4		
MOV	r,r/i	1	1	x	x	x				1	0.33
MOV a)	r,m	1					1			2	1
MOV a)	m,r	1						1	1	3	1
MOV	m,i	1						1	1	3	1
MOV	r,sr	1					1				1
MOV	m,sr	2					1	1	1		1
MOV	sr,r	8	4	x	x	x	4				16
MOV	sr,m	8	3	x		x	5				16
MOVNTI	m,r	2						1	1		2
MOVSX MOVZX MOVXSD	r,r	1	1	x	x	x				1	0.33
MOVSX MOVZX	r,m	1					1				1
CMOVcc	r,r	2	2	x	x	x				2	1
CMOVcc	r,m	2	2	x	x	x	1				
XCHG	r,r	3	3	x	x	x				2	2
XCHG	r,m	7					1	1	1	high b)	
XLAT		2	1				1			4	1
PUSH	r	1						1	1	3	1
PUSH	i	1						1	1		1
PUSH	m	2					1	1	1		1
PUSH	sr	2	1					1	1		1
PUSHF(D/Q)		17	15	x	x	x		1	1		7
PUSHA(D) i)		18	9					1	8		8
POP	r	1					1			2	1
POP	(E/R)SP	4	3				1				
POP	m	2					1	1	1		1.5
POP	sr	10	9				1				17
POPF(D/Q)		24	23	x	x	x	1			20	
POPA(D) i)		10	2				8				7
LAHF SAHF		1	1	x	x	x				1	0.33
SALC i)		2	2	x	x	x				4	1
LEA a)	r,m	1	1	1						1	1
BSWAP	r	2	2	1		1				4	1
LDS LES LFS LGS LSS	m	11	11				1				17
PREFETCHNTA	m	1					1				1
PREFETCHT0/1/2	m	1					1				1
LFENCE		2						1	1		8
MFENCE		2						1	1		9
SFENCE		2						1	1		9
CLFLUSH	m8	4	2	x	x	x		1	1	240	117
IN											
OUT											

Arithmetic instructions											
ADD SUB	r,r/i	1	1	x	x	x				1	0.33
ADD SUB	r,m	1	1	x	x	x	1				1
ADD SUB	m,r/i	2	1	x	x	x	1	1	1	6	1
ADC SBB	r,r/i	2	2	x	x	x				2	2
ADC SBB	r,m	2	2	x	x	x	1			2	2
ADC SBB	m,r/i	4	3	x	x	x	1	1	1	7	
CMP	r,r/i	1	1	x	x	x				1	0.33
CMP	m,r/i	1	1	x	x	x	1			1	1
INC DEC NEG NOT	r	1	1	x	x	x				1	0.33
INC DEC NEG NOT	m	3	1	x	x	x	1	1	1	6	1
AAA AAS DAA DAS i)		1	1		1						1
AAD i)		3	3	x	x	x					1
AAM i)		4	4							17	
MUL IMUL	r8	1	1		1					3	1
MUL IMUL	r16	3	3	x	x	x				5	1.5
MUL IMUL	r32	3	3	x	x	x				5	1.5
MUL IMUL	r64	3	3	x	x	x				7	4
IMUL	r16,r16	1	1		1					3	1
IMUL	r32,r32	1	1		1					3	1
IMUL	r64,r64	1	1	1						5	2
IMUL	r16,r16,i	1	1		1					3	1
IMUL	r32,r32,i	1	1		1					3	1
IMUL	r64,r64,i	1	1	1						5	2
MUL IMUL	m8	1	1		1		1			3	1
MUL IMUL	m16	3	3	x	x	x	1			5	1.5
MUL IMUL	m32	3	3	x	x	x	1			5	1.5
MUL IMUL	m64	3	2	2			1			7	4
IMUL	r16,m16	1	1		1		1			3	1
IMUL	r32,m32	1	1		1		1			3	1
IMUL	r64,m64	1	1	1			1			5	2
IMUL	r16,m16,i	1	1		1		1				2
IMUL	r32,m32,i	1	1		1		1				1
IMUL	r64,m64,i	1	1	1			1				2
DIV IDIV	r8	3	3							18	12
DIV IDIV	r16	5	5							18-26 c)	12-20 c)
DIV IDIV	r32	4	4							18-42 c)	12-36 c)
DIV	r64	32	32							29-61 c)	18-37 c)
IDIV	r64	56	56							39-72 c)	28-40 c)
DIV IDIV	m8	4	3				1			18	12
DIV IDIV	m16	6	5				1			18-26 c)	12-20 c)
DIV IDIV	m32	5	4				1			18-42 c)	12-36 c)
DIV	m64	32	31				1			29-61 c)	18-37 c)
IDIV	m64	56	55				1			39-72 c)	28-40 c)
CBW CWDE CDQE		1	1	x	x	x				1	
CWD CDQ CQO		1	1	x		x				1	
Logic instructions											
AND OR XOR	r,r/i	1	1	x	x	x				1	0.33
AND OR XOR	r,m	1	1	x	x	x	1				1
AND OR XOR	m,r/i	2	1	x	x	x	1	1	1	6	1

TEST	r,r/i	1	1	x	x	x				1	0.33
TEST	m,r/i	1	1	x	x	x	1				1
SHR SHL SAR	r,i/cl	1	1	x		x				1	0.5
SHR SHL SAR	m,i/cl	3	2	x		x	1	1	1	6	1
ROR ROL	r,i/cl	1	1	x		x				1	1
ROR ROL	m,i/cl	3	2	x		x	1	1	1	6	1
RCR RCL	r,l	2	2	x	x	x				2	2
RCR	r8,i/cl	9	9	x	x	x				12	
RCL	r8,i/cl	8	8	x	x	x				11	
RCR RCL	r16/32/64,i/cl	6	6	x	x	x				11	
RCR RCL	m,l	4	3	x	x	x	1	1	1	7	
RCR	m8,i/cl	12	9	x	x	x	1	1	1	14	
RCL	m8,i/cl	11	8	x	x	x	1	1	1	13	
RCR RCL	m16/32/64,i/cl	10	7	x	x	x	1	1	1	13	
SHLD SHRD	r,r,i/cl	2	2	x	x	x				2	1
SHLD SHRD	m,r,i/cl	3	2	x	x	x	1	1	1	7	
BT	r,r/i	1	1	x	x	x				1	1
BT	m,r	10	9	x	x	x	1				5
BT	m,i	2	1	x	x	x	1				1
BTR BTS BTC	r,r/i	1	1	x	x	x				1	
BTR BTS BTC	m,r	11	8	x	x	x	1	1	1	5	
BTR BTS BTC	m,i	3	1	x	x	x	1	1	1	6	
BSF BSR	r,r	2	2	x	1	x				2	1
BSF BSR	r,m	2	2	x	1	x	1				2
SETcc	r	1	1	x	x	x				1	1
SETcc	m	2	1	x	x	x		1	1		1
CLC STC CMC		1	1	x	x	x				1	0.33
CLD		7	7	x	x	x					4
STD		6	6	x	x	x					14
Control transfer instructions											
JMP	short/near	1	1			1				0	1-2
JMP i)	far	30	30								76
JMP	r	1	1			1				0	1-2
JMP	m(near)	1	1			1	1			0	1-2
JMP	m(far)	31	29				2				68
Conditional jump	short/near	1	1			1				0	1
Fused compare and branch e,i)		1	1			1				0	1
Fused test and branch e,i)		1	1			1				0	1
J(E/R)CXZ	short	2	2	x	x	1					1-2
LOOP	short	11	11	x	x	x					5
LOOP(N)E	short	11	11	x	x	x					5
CALL	near	3	2	x	x	x		1	1		2
CALL i)	far	43	43								75
CALL	r	3	2					1	1		2
CALL	m(near)	4	3				1	1	1		2
CALL	m(far)	44	42				2				75
RETN		1				1	1				2
RETN	i	3	1			1	1				2
RETF		32	30				2				78
RETF	i	32	30				2				78

BOUND i)	r,m	15	13				2				8
INTO i)		5	5								3
String instructions											
LODS		3	2				1				1
REP LODS		4+7n - 14+6n								1+5n - 21+3n	
STOS		4	2					1	1		1
REP STOS		8+5n - 20+1.2n								7+2n - 0.55n	
MOVS		8	5				1	1	1		5
REP MOVS		7+7n - 13+n								1+3n - 0.63n	
SCAS		4	3				1				1
REP(N)E SCAS		7+8n - 17+7n								3+8n - 23+6n	
CMPS		7	5				2				3
REP(N)E CMPS		7+10n - 7+9n								2+7n - 22+5n	
Other											
NOP (90)		1	1	x	x	x					0.33
NOP (0F 1F mod000rm)		1	1	x	x	x					1
PAUSE		3	3	x	x	x					8
ENTER	i,0	12	10					1	1		8
ENTER	a,b										
LEAVE		3	2				1				
CPUID		46- 100									180-215
RDTSC		29									64
RDPMSR		23									54

Notes:

- a) Applies to all addressing modes
- b) Has an implicit LOCK prefix.
- c) Low values are for small results, high values for high results.
- e) See manual 3: "The microarchitecture of Intel, AMD and VIA CPUs" for restrictions on macro-op fusion.
- i) Not available in 64 bit mode.

5.2 Floating point x87 instructions

Instruction	Operands	jops fused domain	jops unfused domain							Unit	Latency	Reciprocal throughput
Move instructions			p015	p0	p1	p5	p2	p3	p4			
FLD	r	1	1	1						float	1	1
FLD	m32/64	1	1				1			float	3	1
FLD	m80	4	2	2			2			float	4	3
FBLD	m80	40	38				2			float	45	20
FST(P)	r	1	1	1						float	1	1
FST(P)	m32/m64	1						1	1	float	3	1
FSTP	m80	7	3	x	x	x		2	2	float	4	5
FBSTP	m80	170	166	x	x	x		2	2	float	164	166
FXCH	r	1	0 f)							float	0	1
FILD	m	1	1	1			1			float	6	1
FIST	m	2	1		1			1	1	float	6	1
FISTP	m	3	1		1			1	1	float	6	1
FISTTP g)	m	3	1		1			1	1	float	6	1
FLDZ		1	1	1						float		1
FLD1		2	2	1	1					float		2
FLDPI FLDL2E etc.		2	2		2					float		2
FCMOVcc	r	2	2	2						float	2	2
FNSTSW	AX	1	1	1						float		1
FNSTSW	m16	2	1	1				1	1	float		2
FLDCW	m16	2	1				1			float		10
FNSTCW	m16	3	1					1	1	float		8
FINCSTP FDECSTP		1	1	1						float	1	1
FFREE(P)	r	2	2	2						float		2
FNSAVE	m	142								float	184	192
FRSTOR	m	78								float	169	177
Arithmetic instructions												
FADD(P) FSUB(R)(P)	r	1	1		1					float	3	1
FADD(P) FSUB(R)(P)	m	1	1		1		1			float		1
FMUL(P)	r	1	1	1						float	5	2
FMUL(P)	m	1	1	1			1			float		2
FDIV(R)(P)	r	1	1	1						float	6-38 d)	5-37 d)
FDIV(R)(P)	m	1	1	1			1			float		5-37 d)
FABS		1	1	1						float	1	1
FCHS		1	1	1						float	1	1
FCOM(P) FUCOM	r	1	1		1					float		1
FCOM(P) FUCOM	m	1	1		1		1			float		1
FCOMPP FUCOMPP		2	2	1	1					float		
FCOMI(P) FUCOMI(P)	r	1	1		1					float		1
FIADD FISUB(R)	m	2	2	1	1		1			float		2
FIMUL	m	2	2	2			1			float		2
FIDIV(R)	m	2	2	2			1			float		5-37 d)

FICOM(P)	m	2	2	1	1		1			float		2
FTST		1	1		1					float		1
FXAM		1	1		1					float		1
FPREM FPREM1		21-27	21-27							float	16-56	
FRNDINT		7-15	7-15							float	22-29	
Math												
FSCALE		27	27							float	41	
EXTRACT		82	82							float	170	
FSQRT		1	1							float	6-69	
FSIN FCOS		~96	~96							float	~96	
FSINCOS		~100	~100							float	~115	
F2XM1		~19	~19							float	~45	
FYL2X FYL2XP1		~53	~53							float	~96	
FPTAN		~98	~98							float	~136	
FPATAN		~70	~70							float	~119	
Other												
FNOP		1	1	1						float		1
WAIT		2	2							float		1
FNCLEX		4	4							float		15
FNINIT		15	15							float		63

Notes:

- d) Round divisors or low precision give low values.
- f) Resolved by register renaming. Generates no μ ops in the unfused domain.
- g) SSE3 instruction set.

5.3 Integer MMX and XMM instructions

Instruction	Operands	jops fused domain	jops unfused domain							Unit	Latency	Reciprocal throughput
Move instructions			p015	p0	p1	p5	p2	p3	p4			
MOVD k)	r32/64,(x)mm	1	1	x	x	x				int	2	0.33
MOVD k)	m32/64,(x)mm	1						1	1		3	1
MOVD k)	(x)mm,r32/64	1	1	x		x				int	2	0.5
MOVD k)	(x)mm,m32/64	1					1			int	2	1
MOVQ	(x)mm, (x)mm	1	1	x	x	x				int	1	0.33
MOVQ	(x)mm,m64	1					1			int	2	1
MOVQ	m64, (x)mm	1						1	1		3	1
MOVDQA	xmm, xmm	1	1	x	x	x				int	1	0.33
MOVDQA	xmm, m128	1					1			int	2	1
MOVDQA	m128, xmm	1						1	1		3	1
MOVDQU	m128, xmm	9	4	x	x	x	1	2	2		3-8	4
MOVDQU	xmm, m128	4	2	x		x	2			int	2-8	2
LDDQU g)	xmm, m128	4	2	x		x	2			int	2-8	2
MOVDQ2Q	mm, xmm	1	1	x	x	x				int	1	0.33
MOVQ2DQ	xmm,mm	1	1	x	x	x				int	1	0.33
MOVNTQ	m64,mm	1						1	1			2
MOVNTDQ	m128,xmm	1						1	1			2
PACKSSWB/DW PACKUSWB	mm,mm	1	1	1						int	1	1
PACKSSWB/DW PACKUSWB	mm,m64	1	1	1			1			int		1
PACKSSWB/DW PACKUSWB	xmm,xmm	3	3							flt→int	3	2
PACKSSWB/DW PACKUSWB	xmm,m128	4	3				1			int		2
PUNPCKH/LBW/WD/DQ	mm,mm	1	1	1						int	1	1
PUNPCKH/LBW/WD/DQ	mm,m64	1	1	1			1			int		1
PUNPCKH/LBW/WD/DQ	xmm,xmm	3	3							flt→int	3	2
PUNPCKH/LBW/WD/DQ	xmm,m128	4	3				1			int		2
PUNPCKH/LQDQ	xmm,xmm	1	1							int	1	1
PUNPCKH/LQDQ	xmm, m128	2	1				1			int		1
PSHUFB h)	mm,mm	1	1			1				int	1	1
PSHUFB h)	mm,m64	2	1			1	1			int		1
PSHUFB h)	xmm,xmm	4	4							int	3	2
PSHUFB h)	xmm,m128	5	4				1			int		2
PSHUFW	mm,mm,i	1	1			1				int	1	1
PSHUFW	mm,m64,i	2	1			1	1			int		1
PSHUFD	xmm,xmm,i	2	2	x	x	1				flt→int	3	1
PSHUFD	xmm,m128,i	3	2	x	x	1	1			int		1
PSHUFL/HW	xmm,xmm,i	1	1			1				int	1	1
PSHUFL/HW	xmm, m128,i	2	1			1	1			int		1
PALIGNR h)	mm,mm,i	2	2	x	x	x				int	2	1
PALIGNR h)	mm,m64,i	2	2	x	x	x	1			int		1
PALIGNR h)	xmm,xmm,i	2	2	x	x	x				int	2	1
PALIGNR h)	xmm,m128,i	2	2	x	x	x	1			int		1
MASKMOVQ	mm,mm	4								int		2-5

MASKMOVDQU	xmm,xmm	10								int		6-10
PMOVBMSKB	r32,(x)mm	1	1	1						int	2	1
PEXTRW	r32,mm,i	2	2							int	3	1
PEXTRW	r32,xmm,i	3	3							int	5	1
PINSRW	mm,r32,i	1	1			1				int	2	1
PINSRW	mm,m16,i	2	1			1	1			int		1
PINSRW	xmm,r32,i	3	3	x	x	x				int	6	1.5
PINSRW	xmm,m16,i	4	3	x	x	x	1			int		1.5
Arithmetic instructions												
PADD/SUB(U)(S)B/W/D	(x)mm, (x)mm	1	1	x		x				int	1	0.5
PADD/SUB(U)(S)B/W/D	(x)mm,m	1	1	x		x	1			int		1
PADDQ PSUBQ	(x)mm, (x)mm	2	2	x		x				int	2	1
PADDQ PSUBQ	(x)mm,m	2	2	x		x	1			int		1
PHADD(S)W PHSUB(S)W h)	mm,mm	5	5							int	5	4
PHADD(S)W PHSUB(S)W h)	mm,m64	6	5				1			int		4
PHADD(S)W PHSUB(S)W h)	xmm,xmm	7	7							int	6	4
PHADD(S)W PHSUB(S)W h)	xmm,m128	8	7				1			int		4
PHADDD PHSUBD h)	mm,mm	3	3							int	3	2
PHADDD PHSUBD h)	mm,m64	4	3				1			int		2
PHADDD PHSUBD h)	xmm,xmm	5	5							int	5	3
PHADDD PHSUBD h)	xmm,m128	6	5				1			int		3
PCMPEQ/GTB/W/D	(x)mm,(x)mm	1	1	x		x				int	1	0.5
PCMPEQ/GTB/W/D	(x)mm,m	1	1	x		x	1			int		1
PMULL/HW PMULHUW	(x)mm,(x)mm	1	1		1					int	3	1
PMULL/HW PMULHUW	(x)mm,m	1	1		1		1			int		1
PMULHSW h)	(x)mm,(x)mm	1	1		1					int	3	1
PMULHSW h)	(x)mm,m	1	1		1		1			int		1
PMULUDQ	(x)mm,(x)mm	1	1		1					int	3	1
PMULUDQ	(x)mm,m	1	1		1		1			int		1
PMADDWD	(x)mm,(x)mm	1	1		1					int	3	1
PMADDWD	(x)mm,m	1	1		1		1			int		1
PMADDUBSW h)	(x)mm,(x)mm	1	1		1					int	3	1
PMADDUBSW h)	(x)mm,m	1	1		1		1			int		1
PAVGB/W	(x)mm,(x)mm	1	1	x		x				int	1	0.5
PAVGB/W	(x)mm,m	1	1	x		x	1			int		1
PMIN/MAXUB/SW	(x)mm,(x)mm	1	1	x		x				int	1	0.5
PMIN/MAXUB/SW	(x)mm,m	1	1	x		x	1			int		1
PASB PABSW PABSD h)	(x)mm,(x)mm	1	1	x		x				int	1	0.5
PASB PABSW PABSD h)	(x)mm,m	1	1	x		x	1			int		1
PSIGNB PSIGNW PSIGND h)	(x)mm,(x)mm	1	1	x		x				int	1	0.5
PSIGNB PSIGNW PSIGND h)	(x)mm,m	1	1	x		x	1			int		1
PSADBW	(x)mm,(x)mm	1	1		1					int	3	1
PSADBW	(x)mm,m	1	1		1		1			int		1
Logic instructions												
PAND(N) POR PXOR	(x)mm,(x)mm	1	1	x	x	x				int	1	0.33
PAND(N) POR PXOR	(x)mm,m	1	1	x	x	x	1			int		1
PSLL/RL/RAW/D/Q	mm,mm/i	1	1	1						int	1	1
PSLL/RL/RAW/D/Q	mm,m64	1	1	1			1			int		1
PSLL/RL/RAW/D/Q	xmm,i	1	1	1						int	1	1

PSLL/RL/RAW/D/Q	xmm,xmm	2	2	x	x					int	2	1
PSLL/RL/RAW/D/Q	xmm,m128	3	2	x	x		1			int		1
PSLL/RDQ	xmm,i	2	2	x	x					int	2	1
Other												
EMMS		11	11	x	x	x				float		6

Notes:

- g) SSE3 instruction set.
- h) "Supplementary SSE3" instruction set.
- k) MASM uses the name MOVD rather than MOVQ for this instruction even when moving 64 bits.

5.4 Floating point XMM instructions

Instruction	Operands	μops fused domain	μops unfused domain							Unit	Latency	Reciprocal throughput
Move instructions			p015	p0	p1	p5	p2	p3	p4			
MOVAPS/D	xmm,xmm	1	1	x	x	x				int	1	0.33
MOVAPS/D	xmm,m128	1					1			int	2	1
MOVAPS/D	m128,xmm	1						1	1		3	1
MOVUPS/D	xmm,m128	4	2	1		1	2			int	2-4	2
MOVUPS/D	m128,xmm	9	4	x	x	x	1	2	2		3-4	4
MOVSS/D	xmm,xmm	1	1	x	x	x				int	1	0.33
MOVSS/D	xmm,m32/64	1					1			int	2	1
MOVSS/D	m32/64,xmm	1						1	1		3	1
MOVHPS/D MOVLPS/D	xmm,m64	2	1			1	1			int	3	1
MOVHPS/D	m64,xmm	2	1	1				1	1		5	1
MOVLPS/D	m64,xmm	1						1	1		3	1
MOVLHPS MOVHLPS	xmm,xmm	1	1	1						float	1	1
MOVMSKPS/D	r32,xmm	1	1	1						float	1	1
MOVNTPS/D	m128,xmm	1						1	1			2-3
SHUFPS	xmm,xmm,i	3	3		3					flt→int	3	2
SHUFPS	xmm,m128,i	4	3		3		1			flt→int		2
SHUFPD	xmm,xmm,i	1	1	1						float	1	1
SHUFPD	xmm,m128,i	2	1	1			1			float		1
MOVDDUP g)	xmm,xmm	1	1	1						int	1	1
MOVDDUP g)	xmm,m64	2	1	1			1			int		1
MOVSH/LDUP g)	xmm,xmm	1	1			1				int	1	1
MOVSH/LDUP g)	xmm,m128	2	1			1	1			int		1
UNPCKH/LPS	xmm,xmm	3	3		3					flt→int	3	2
UNPCKH/LPS	xmm,m128	4	3		3		1			int		2
UNPCKH/LPD	xmm,xmm	1	1	1						float	1	1
UNPCKH/LPD	xmm,m128	2	1	1			1			float		1

Conversion												
CVTPD2PS	xmm,xmm	2	2							float	4	1
CVTPD2PS	xmm,m128	2	2				1			float		1
CVTSD2SS	xmm,xmm	2	2							float	4	1
CVTSD2SS	xmm,m64	2	2				1			float		1
CVTPS2PD	xmm,xmm	2	2	2						float	2	2
CVTPS2PD	xmm,m64	2	2	2			1			float		2
CVTSS2SD	xmm,xmm	2	2							float	2	2
CVTSS2SD	xmm,m32	2	2	2			1			float		2
CVTDQ2PS	xmm,xmm	1	1		1					float	3	1
CVTDQ2PS	xmm,m128	1	1		1		1			float		1
CVT(T) PS2DQ	xmm,xmm	1	1		1					float	3	1
CVT(T) PS2DQ	xmm,m128	1	1		1		1			float		1
CVTDQ2PD	xmm,xmm	2	2	1	1					float	4	1
CVTDQ2PD	xmm,m64	3	2				1			float		1
CVT(T)PD2DQ	xmm,xmm	2	2							float	4	1
CVT(T)PD2DQ	xmm,m128	2	2				1			float		1
CVTPI2PS	xmm,mm	1	1		1					float	3	3
CVTPI2PS	xmm,m64	1	1		1		1			float		3
CVT(T)PS2PI	mm,xmm	1	1		1					float	3	1
CVT(T)PS2PI	mm,m128	1	1		1		1			float		1
CVTPI2PD	xmm,mm	2	2	1	1					float	4	1
CVTPI2PD	xmm,m64	2	2	1	1		1			float		1
CVT(T) PD2PI	mm,xmm	2	2	1	1					float	4	1
CVT(T) PD2PI	mm,m128	2	2	1	1		1			float		1
CVTSI2SS	xmm,r32	1	1		1					float	4	3
CVTSI2SS	xmm,m32	1	1		1		1			float		3
CVT(T)SS2SI	r32,xmm	1	1		1					float	3	1
CVT(T)SS2SI	r32,m32	1	1		1		1			float		1
CVTSI2SD	xmm,r32	2	2	1	1					float	4	3
CVTSI2SD	xmm,m32	2	1		1		1			float		3
CVT(T)SD2SI	r32,xmm	1	1		1					float	3	1
CVT(T)SD2SI	r32,m64	1	1		1		1			float		1

Arithmetic												
ADDSS/D SUBSS/D	xmm,xmm	1	1		1					float	3	1
ADDSS/D SUBSS/D	xmm,m32/64	1	1		1		1			float		1
ADDPS/D SUBPS/D	xmm,xmm	1	1		1					float	3	1
ADDPS/D SUBPS/D	xmm,m128	1	1		1		1			float		1
ADDSUBPS/D g)	xmm,xmm	1	1		1					float	3	1
ADDSUBPS/D g)	xmm,m128	1	1		1		1			float		1
HADDPS HSUBPS g)	xmm,xmm	6	6							float	9	3
HADDPS HSUBPS g)	xmm,m128	7	6				1			float		3
HADDPD HSUBPD g)	xmm,xmm	3	3							float	5	2
HADDPD HSUBPD g)	xmm,m128	4	3				1			float		2
MULSS	xmm,xmm	1	1	1						float	4	1
MULSS	xmm,m32	1	1	1			1			float		1
MULSD	xmm,xmm	1	1	1						float	5	1
MULSD	xmm,m64	1	1	1			1			float		1
MULPS	xmm,xmm	1	1	1						float	4	1
MULPS	xmm,m128	1	1	1			1			float		1
MULPD	xmm,xmm	1	1	1						float	5	1
MULPD	xmm,m128	1	1	1			1			float		1
DIVSS	xmm,xmm	1	1	1						float	6-18 d)	5-17 d)
DIVSS	xmm,m32	1	1	1			1			float		5-17 d)
DIVSD	xmm,xmm	1	1	1						float	6-32 d)	5-31 d)
DIVSD	xmm,m64	1	1	1			1			float		5-31 d)
DIVPS	xmm,xmm	1	1	1						float	6-18 d)	5-17 d)
DIVPS	xmm,m128	1	1	1			1			float		5-17 d)
DIVPD	xmm,xmm	1	1	1						float	6-32 d)	5-31 d)
DIVPD	xmm,m128	1	1	1			1			float		5-31 d)
RCPSS/PS	xmm,xmm	1	1		1					float	3	2
RCPSS/PS	xmm,m	1	1		1		1			float		2
CMPccSS/D	xmm,xmm	1	1		1					float	3	1
CMPccSS/D	xmm,m32/64	1	1		1		1			float		1
CMPccPS/D	xmm,xmm	1	1		1					float	3	1
CMPccPS/D	xmm,m128	1	1		1		1			float		1
COMISS/D UCOMISS/D	xmm,xmm	1	1		1					float	3	1
COMISS/D UCOMISS/D	xmm,m32/64	1	1		1		1			float		1
MAXSS/D MINSS/D	xmm,xmm	1	1		1					float	3	1
MAXSS/D MINSS/D	xmm,m32/64	1	1		1		1			float		1
MAXPS/D MINPS/D	xmm,xmm	1	1		1					float	3	1
MAXPS/D MINPS/D	xmm,m128	1	1		1		1			float		1
Math												
SQRTSS/PS	xmm,xmm	1	1	1						float	6-29	6-29
SQRTSS/PS	xmm,m	2	1	1			1			float		6-29
SQRTSD/PD	xmm,xmm	1	1	1						float	6-58	6-58
SQRTSD/PD	xmm,m	2	1	1			1			float		6-58
RSQRTSS/PS	xmm,xmm	1	1		1					float	3	2
RSQRTSS/PS	xmm,m	1	1		1		1			float		2

Logic												
AND/ANDN/OR/XORPS/D	xmm,xmm	1	1	x	x	x				int	1	0.33
AND/ANDN/OR/XORPS/D	xmm,m128	1	1	x	x	x	1			int		1
Other												
LDMXCSR	m32	14	13				1					42
STMXCSR	m32	6	4					1	1			19
FXSAVE	m4096	141									145	145
FXRSTOR	m4096	119									164	164

Notes:

- d) Round divisors give low values.
- g) SSE3 instruction set.

6 List of instruction timings and μ op breakdown for Core 2 (45nm)

Explanation of column headings:

Operands: i = immediate data, r = register, mm = 64 bit mmx register, xmm = 128 bit xmm register, (x)mm = mmx or xmm register, sr = segment register, m = memory, m32 = 32-bit memory operand, etc.

μ ops fused domain: The number of μ ops at the decode, rename, allocate and retirement stages in the pipeline. Fused μ ops count as one.

μ ops unfused domain: The number of μ ops for each execution port. Fused μ ops count as two. Fused macro-ops count as one. The instruction has μ op fusion if the sum of the numbers listed under p015 + p2 + p3 + p4 exceeds the number listed under μ ops fused domain. An x under p0, p1 or p5 means that at least one of the μ ops listed under p015 can optionally go to this port. For example, a 1 under p015 and an x under p0 and p5 means one μ op which can go to either port 0 or port 5, whichever is vacant first. A value listed under p015 but nothing under p0, p1 and p5 means that it is not known which of the three ports these μ ops go to.

p015: The total number of μ ops going to port 0, 1 and 5.

p0: The number of μ ops going to port 0 (execution units).

p1: The number of μ ops going to port 1 (execution units).

p5: The number of μ ops going to port 5 (execution units).

p2: The number of μ ops going to port 2 (memory read).

p3: The number of μ ops going to port 3 (memory write address).

p4: The number of μ ops going to port 4 (memory write data).

Unit: Tells which execution unit cluster is used. An additional delay of 1 clock cycle is generated if a register written by a μ op in the integer unit (int) is read by a μ op in the floating point unit (float) or vice versa. flt \rightarrow int means that an instruction with multiple μ ops receive the input in the float unit and delivers the output in the int unit. Delays for moving data between different units are included under latency when they are unavoidable. For example, `movd eax, xmm0` has an extra 1 clock delay for moving from the XMM-integer unit to the general purpose integer unit. This is included under latency because it occurs regardless of which instruction comes next. Nothing listed under unit means that additional delays are either unlikely to occur or unavoidable and therefore included in the latency figure.

Latency: This is the delay that the instruction generates in a dependence chain. The numbers are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably. Floating point operands are presumed to be normal numbers. Denormal numbers, NAN's and infinity increase the delays very much, except in XMM move, shuffle and Boolean instructions. Floating point overflow, underflow, denormal or NAN results give a similar delay. The time unit used is core clock cycles, not the reference clock cycles given by the time stamp counter.

Reciprocal throughput: The average number of core clock cycles per instruction for a series of independent instructions of the same kind in the same thread.

6.1 Integer instructions

Instruction	Operands	jops fused domain	jops unfused domain							Latency	Reciprocal throughput
Move instructions			p015	p0	p1	p5	p2	p3	p4		
MOV	r,r/i	1	1	x	x	x				1	0.33
MOV a)	r,m	1					1			2	1
MOV a)	m,r	1						1	1	3	1
MOV	m,i	1						1	1	3	1
MOV	r,sr	1					1				1
MOV	m,sr	2					1	1	1		1
MOV	sr,r	8	4	x	x	x	4				16
MOV	sr,m	8	3	x		x	5				16
MOVNTI	m,r	2						1	1		2
MOVSX MOVZX MOVSD	r,r	1	1	x	x	x				1	0.33
MOVSX MOVZX	r16/32,m	1					1				1
MOVSX MOVSD	r64,m	2	1	x	x	x	1				1
CMOVcc	r,r	2	2	x	x	x				2	1
CMOVcc	r,m	2	2	x	x	x	1				
XCHG	r,r	3	3	x	x	x				2	2
XCHG	r,m	7					1	1	1	high b)	
XLAT		2	1				1			4	1
PUSH	r	1						1	1	3	1
PUSH	i	1						1	1		1
PUSH	m	2					1	1	1		1
PUSH	sr	2	1					1	1		1
PUSHF(D/Q)		17	15	x	x	x		1	1		7
PUSHA(D) i)		18	9					1	8		8
POP	r	1					1			2	1
POP	(E/R)SP	4	3				1				
POP	m	2					1	1	1		1.5
POP	sr	10	9				1				17
POPF(D/Q)		24	23	x	x	x	1			20	
POPA(D) i)		10	2				8				7
LAHF SAHF		1	1	x	x	x				1	0.33
SALC i)		2	2	x	x	x				4	1
LEA a)	r,m	1	1	1						1	1
BSWAP	r	2	2	1		1				4	1
LDS LES LFS LGS LSS	m	11	11				1				17
PREFETCHNTA	m	1					1				1
PREFETCHT0/1/2	m	1					1				1
LFENCE		2						1	1		8
MFENCE		2						1	1		6
SFENCE		2						1	1		9
CLFLUSH	m8	4	2	1		1		1	1	120	90
IN											
OUT											

Arithmetic instructions											
ADD SUB	r,r/i	1	1	x	x	x				1	0.33
ADD SUB	r,m	1	1	x	x	x	1				1
ADD SUB	m,r/i	2	1	x	x	x	1	1	1	6	1
ADC SBB	r,r/i	2	2	x	x	x				2	2
ADC SBB	r,m	2	2	x	x	x	1			2	2
ADC SBB	m,r/i	4	3	x	x	x	1	1	1	7	
CMP	r,r/i	1	1	x	x	x				1	0.33
CMP	m,r/i	1	1	x	x	x	1			1	1
INC DEC NEG NOT	r	1	1	x	x	x				1	0.33
INC DEC NEG NOT	m	3	1	x	x	x	1	1	1	6	1
AAA AAS DAA DAS i)		1	1		1						1
AAD i)		3	3	x	x	x					1
AAM i)		5	5	x	x	x				17	
MUL IMUL	r8	1	1		1					3	1
MUL IMUL	r16	3	3	x	x	x				5	1.5
MUL IMUL	r32	3	3	x	x	x				5	1.5
MUL IMUL	r64	3	3	x	x	x				7	4
IMUL	r16,r16	1	1		1					3	1
IMUL	r32,r32	1	1		1					3	1
IMUL	r64,r64	1	1	1						5	2
IMUL	r16,r16,i	1	1		1					3	1
IMUL	r32,r32,i	1	1		1					3	1
IMUL	r64,r64,i	1	1	1						5	2
MUL IMUL	m8	1	1		1		1			3	1
MUL IMUL	m16	3	3	x	x	x	1			5	1.5
MUL IMUL	m32	3	3	x	x	x	1			5	1.5
MUL IMUL	m64	3	2	2			1			7	4
IMUL	r16,m16	1	1		1		1			3	1
IMUL	r32,m32	1	1		1		1			3	1
IMUL	r64,m64	1	1	1			1			5	2
IMUL	r16,m16,i	1	1		1		1				2
IMUL	r32,m32,i	1	1		1		1				1
IMUL	r64,m64,i	1	1	1			1				2
DIV IDIV	r8	4	4	1	2	1				9-18 c)	
DIV IDIV	r16	7	7	x	x	x				14-22 c)	
DIV IDIV	r32	7	7	2	3	2				14-23 c)	
DIV	r64	32-38	32-38	9	10	13				18-57 c)	
IDIV	r64	56-62	56-62	x	x	x				34-88 c)	
DIV IDIV	m8	4	3	1	2		1			9-18	
DIV IDIV	m16	7	6	2	3	2	1			14-22 c)	
DIV IDIV	m32	7	6	x	x	x	1			14-23 c)	
DIV	m64	32	31	x	x	x	1			34-88 c)	
IDIV	m64	56	55	x	x	x	1			39-72 c)	
CBW CWDE CDQE		1	1	x	x	x				1	
CWD CDQ CQO		1	1	x		x				1	
Logic instructions											
AND OR XOR	r,r/i	1	1	x	x	x				1	0.33
AND OR XOR	r,m	1	1	x	x	x	1				1

AND OR XOR	m,r/i	2	1	x	x	x	1	1	1	6	1
TEST	r,r/i	1	1	x	x	x				1	0.33
TEST	m,r/i	1	1	x	x	x	1				1
SHR SHL SAR	r,i/cl	1	1	x		x				1	0.5
SHR SHL SAR	m,i/cl	3	2	x		x	1	1	1	6	1
ROR ROL	r,i/cl	1	1	x		x				1	1
ROR ROL	m,i/cl	3	2	x		x	1	1	1	6	1
RCR RCL	r,l	2	2	x	x	x				2	2
RCR	r8,i/cl	9	9	x	x	x				12	
RCL	r8,i/cl	8	8	x	x	x				11	
RCR RCL	r16/32/64,i/cl	6	6	x	x	x				11	
RCR RCL	m,l	4	3	x	x	x	1	1	1	7	
RCR	m8,i/cl	12	9	x	x	x	1	1	1	14	
RCL	m8,i/cl	11	8	x	x	x	1	1	1	13	
RCR RCL	m16/32/64,i/cl	10	7	x	x	x	1	1	1	13	
SHLD SHRD	r,r,i/cl	2	2	x	x	x				2	1
SHLD SHRD	m,r,i/cl	3	2	x	x	x	1	1	1	7	
BT	r,r/i	1	1	x	x	x				1	1
BT	m,r	9	8	x	x	x	1				4
BT	m,i	3	2	x	x	x	1				1
BTR BTS BTC	r,r/i	1	1	x	x	x				1	
BTR BTS BTC	m,r	10	7	x	x	x	1	1	1	5	
BTR BTS BTC	m,i	3	1	x	x	x	1	1	1	6	
BSF BSR	r,r	2	2	x	1	x				2	1
BSF BSR	r,m	2	2	x	1	x	1				1
SETcc	r	1	1	x	x	x				1	1
SETcc	m	2	1	x	x	x		1	1		1
CLC STC CMC		1	1	x	x	x				1	0.33
CLD		6	6	x	x	x					3
STD		6	6	x	x	x					14
Control transfer instructions											
JMP	short/near	1	1			1				0	1-2
JMP i)	far	30	30								76
JMP	r	1	1			1				0	1-2
JMP	m(near)	1	1			1	1			0	1-2
JMP	m(far)	31	29				2				68
Conditional jump	short/near	1	1			1				0	1
Fused compare and branch e,i)		1	1			1				0	1
Fused test and branch e,i)		1	1			1				0	1
J(E/R)CXZ	short	2	2	x	x	1					1-2
LOOP	short	11	11	x	x	x					5
LOOP(N)E	short	11	11	x	x	x					5
CALL	near	3	2	x	x	x		1	1		2
CALL i)	far	43	43								75
CALL	r	3	2					1	1		2
CALL	m(near)	4	3				1	1	1		2
CALL	m(far)	44	42				2				75
RETN		1				1	1				2
RETN	i	3	1			1	1				2
RETF		32	30				2				78

RETf	i	32	30				2				78
BOUND i)	r,m	15	13				2				8
INTO i)		5	5								3
String instructions											
LODS		3	2				1				1
REP LODS		4+7n - 14+6n								1+5n - 21+3n	
STOS		4	2					1	1		1
REP STOS		8+5n - 20+1.2n								7+2n - 0.55n	
MOVS		8	5				1	1	1		5
REP MOVS		7+7n - 13+n								1+3n - 0.63n	
SCAS		4	3				1				1
REP(N)E SCAS		7+8n - 17+7n								3+8n - 23+6n	
CMPS		7	5				2				3
REP(N)E CMPS		7+10n - 7+9n								2+7n - 22+5n	
Other											
NOP (90)		1	1	x	x	x					0.33
NOP (0F 1F mod000rm)		1	1	x	x	x					1
PAUSE		3	3	x	x	x					8
ENTER	i,0	12	10					1	1		8
ENTER	a,b										
LEAVE		3	2				1				
CPUID		53-117									53-211
RDTSC		13									32
RDPMS		23									54

Notes:

- a) Applies to all addressing modes
- b) Has an implicit LOCK prefix.
- c) Low values are for small results, high values for high results. The reciprocal throughput is only slightly less than the latency.
- e) See manual 3: "The microarchitecture of Intel, AMD and VIA CPUs" for restrictions on macro-op fusion.
- i) Not available in 64 bit mode.

6.2 Floating point x87 instructions

Instruction	Operands	jops fused domain	jops unfused domain							Unit	Latency	Reciprocal throughput
Move instructions			p015	p0	p1	p5	p2	p3	p4			
FLD	r	1	1	1						float	1	1
FLD	m32/64	1	1				1			float	3	1
FLD	m80	4	2	2			2			float	4	3
FBLD	m80	40	38	x	x	x	2			float	45	20
FST(P)	r	1	1	1						float	1	1
FST(P)	m32/m64	1						1	1	float	3	1
FSTP	m80	7	3	x	x	x		2	2	float	4	5
FBSTP	m80	171	167	x	x	x		2	2	float	164	166
FXCH	r	1	0 f)							float	0	1
FILD	m	1	1		1		1			float	6	1
FIST	m	2	1		1			1	1	float	6	1
FISTP	m	3	1		1			1	1	float	6	1
FISTTP g)	m	3	1		1			1	1	float	6	1
FLDZ		1	1	1						float		1
FLD1		2	2	1	1					float		2
FLDPI FLDL2E etc.		2	2		2					float		2
FCMOVcc	r	2	2	2						float	2	2
FNSTSW	AX	1	1	1						float		1
FNSTSW	m16	2	1	1				1	1	float		2
FLDCW	m16	2	1				1			float		10
FNSTCW	m16	3	1			1		1	1	float		8
FINCSTP FDECSTP		1	1	1						float	1	1
FFREE(P)	r	2	2	x	x	x				float		2
FNSAVE	m	141	95	x	x	x	7	23	23	float		142
FRSTOR	m	78	51	x	x	x	27			float		177
Arithmetic instructions												
FADD(P) FSUB(R)(P)	r	1	1		1					float	3	1
FADD(P) FSUB(R)(P)	m	1	1		1		1			float		1
FMUL(P)	r	1	1	1						float	5	2
FMUL(P)	m	1	1	1			1			float		2
FDIV(R)(P)	r	1	1	1						float	6-21 d)	5-20 d)
FDIV(R)(P)	m	1	1	1			1			float	6-21 d)	5-20 d)
FABS		1	1	1						float	1	1
FCHS		1	1	1						float	1	1
FCOM(P) FUCOM	r	1	1		1					float		1
FCOM(P) FUCOM	m	1	1		1		1			float		1
FCOMPP FUCOMPP		2	2	1	1					float		
FCOMI(P) FUCOMI(P)	r	1	1		1					float		1
FIADD FISUB(R)	m	2	2		2		1			float	3	2
FIMUL	m	2	2	1	1		1			float	5	2
FIDIV(R)	m	2	2	1	1		1			float	6-21	5-20 d)

FICOM(P)	m	2	2		2		1			float		2
FTST		1	1		1					float		1
FXAM		1	1		1					float		1
FPREM		26-29	26-29	x	x	x				float	13-40	
FPREM1		28-35	28-35	x	x	x				float	18-41	
FRNDINT		17-19	17-19	x	x	x				float	10-22	
Math												
FSCALE		28	28	x	x	x				float	43	
EXTRACT		53-84	53-84	x	x	x				float	~170	
FSQRT		1	1	1						float	6-20	
FSIN		18-85	18-85	x	x	x				float	32-85	
FCOS		76-100		x	x	x				float	70-100	
FSINCOS		18-105		x	x	x				float	38-107	
F2XM1		19	19	x	x	x				float	45	
FYL2X FYL2XP1		57-65	57-65	x	x	x				float	50-100	
FPTAN		19-100		x	x	x				float	40-130	
FPATAN		23-87	23-87	x	x	x				float	55-130	
Other												
FNOP		1	1	1						float		1
WAIT		2	2	x	x	x				float		1
FNCLEX		4	4		x	x				float		15
FNINIT		15	15	x	x	x				float		63

Notes:

- d) Round divisors or low precision give low values.
- f) Resolved by register renaming. Generates no µops in the unfused domain.
- g) SSE3 instruction set.

6.3 Integer MMX and XMM instructions

Instruction	Operands	jops fused domain	jops unfused domain							Unit	Latency	Reciprocal throughput
Move instructions			p015	p0	p1	p5	p2	p3	p4			
MOVD k)	r32/64,(x)mm	1	1	x	x	x				int	2	0.33
MOVD k)	m32/64,(x)mm	1						1	1		3	1
MOVD k)	(x)mm,r32/64	1	1	x		x				int	2	0.5
MOVD k)	(x)mm,m32/64	1					1			int	2	1
MOVQ	(x)mm, (x)mm	1	1	x	x	x				int	1	0.33
MOVQ	(x)mm,m64	1					1			int	2	1
MOVQ	m64, (x)mm	1						1	1		3	1
MOVDQA	xmm, xmm	1	1	x	x	x				int	1	0.33
MOVDQA	xmm, m128	1					1			int	2	1
MOVDQA	m128, xmm	1						1	1		3	1
MOVDQU	m128, xmm	9	4	x	x	x	1	2	2		3-8	4
MOVDQU	xmm, m128	4	2	x		x	2			int	2-8	2
LDDQU g)	xmm, m128	4	2	x		x	2			int	2-8	2
MOVDQ2Q	mm, xmm	1	1	x	x	x				int	1	0.33
MOVQ2DQ	xmm,mm	1	1	x	x	x				int	1	0.33
MOVNTQ	m64,mm	1						1	1			2
MOVNTDQ	m128,xmm	1						1	1			2
MOVNTDQA j)	xmm, m128	1					1				2	1
PACKSSWB/DW PACKUSWB	mm,mm	1	1	1						int	1	1
PACKSSWB/DW PACKUSWB	mm,m64	1	1	1			1			int		1
PACKSSWB/DW PACKUSWB	xmm,xmm	1	1			1				int	1	1
PACKSSWB/DW PACKUSWB	xmm,m128	1	1			1	1			int		1
PACKUSDW j)	xmm,xmm	1	1			1				int	1	1
PACKUSDW j)	xmm,m	1	1			1	1			int		1
PUNPCKH/LBW/WD/DQ	mm,mm	1	1	1						int	1	1
PUNPCKH/LBW/WD/DQ	mm,m64	1	1	1			1			int		1
PUNPCKH/LBW/WD/DQ	xmm,xmm	1	1			1				int	1	1
PUNPCKH/LBW/WD/DQ	xmm,m128	1	1			1	1			int		1
PUNPCKH/LQDQ	xmm,xmm	1	1			1				int	1	1
PUNPCKH/LQDQ	xmm, m128	2	1			1	1			int		1
PMOVSX/ZXBW j)	xmm,xmm	1	1			1				int	1	1
PMOVSX/ZXBW j)	xmm,m64	1	1			1	1			int		1
PMOVSX/ZXBD j)	xmm,xmm	1	1			1				int	1	1
PMOVSX/ZXBD j)	xmm,m32	1	1			1	1			int		1
PMOVSX/ZXBQ j)	xmm,xmm	1	1			1				int	1	1
PMOVSX/ZXBQ j)	xmm,m16	1	1			1	1			int		1
PMOVSX/ZXWD j)	xmm,xmm	1	1			1				int	1	1
PMOVSX/ZXWD j)	xmm,m64	1	1			1	1			int		1
PMOVSX/ZXWQ j)	xmm,xmm	1	1			1				int	1	1
PMOVSX/ZXWQ j)	xmm,m32	1	1			1	1			int		1
PMOVSX/ZXDQ j)	xmm,xmm	1	1			1				int	1	1
PMOVSX/ZXDQ j)	xmm,m64	1	1			1	1			int		1

PSHUFB h)	mm,mm	1	1			1				int	1	1
PSHUFB h)	mm,m64	2	1			1	1			int		1
PSHUFB h)	xmm,xmm	1	1			1				int	1	1
PSHUFB h)	xmm,m128	1	1			1	1			int		1
PSHUFW	mm,mm,i	1	1			1				int	1	1
PSHUFW	mm,m64,i	2	1			1	1			int		1
PSHUFD	xmm,xmm,i	1	1			1				int	1	1
PSHUFD	xmm,m128,i	2	1			1	1			int		1
PSHUFL/HW	xmm,xmm,i	1	1			1				int	1	1
PSHUFL/HW	xmm, m128,i	2	1			1	1			int		1
PALIGNR h)	mm,mm,i	2	2			2				int	2	1
PALIGNR h)	mm,m64,i	3	2			3	1			int		1
PALIGNR h)	xmm,xmm,i	1	1			1				int	1	1
PALIGNR h)	xmm,m128,i	1	1			1	1			int		1
PBLENDVB j)	xmm,xmm,xmm0	2	2			2				int	2	2
PBLENDVB j)	xmm,m,xmm0	2	2			2	1			int		2
PBLENDW j)	xmm,xmm,i	1	1			1				int	1	1
PBLENDW j)	xmm,m,i	1	1			1	1			int		1
MASKMOVQ	mm,mm	4	1	1			1	1	1	int		2-5
MASKMOVDQU	xmm,xmm	10	4	1		3	2	2	3	int		6-10
PMOVBMSKB	r32,(x)mm	1	1	1						int	2	1
PEXTRB j)	r32,xmm,i	2	2	x	x	x				int	3	1
PEXTRB j)	m8,xmm,i	2	2	x	x	x				int	3	1
PEXTRW	r32,(x)mm,i	2	2	x	x	x	1			int	3	1
PEXTRW j)	m16,(x)mm,i	2	2			1		1	1	int		1
PEXTRD j)	r32,xmm,i	2	2	x	x	x				int	3	1
PEXTRD j)	m32,xmm,i	2	1			1		1	1	int		1
PEXTRQ j,m)	r64,xmm,i	2	2	x	x	x				int	3	1
PEXTRQ j,m)	m64,xmm,i	2	1			1		1	1	int		1
PINSRB j)	xmm,r32,i	1	1			1				int	1	1
PINSRB j)	xmm,m8,i	2	1			1	1			int		1
PINSRW	(x)mm,r32,i	1	1			1				int	2	1
PINSRW	(x)mm,m16,i	2	1			1	1			int		1
PINSRD j)	xmm,r32,i	1	1			1				int	1	1
PINSRD j)	xmm,m32,i	2	1			1	1			int		1
PINSRQ j,m)	xmm,r64,i	1	1			1				int	1	1
PINSRQ j,m)	xmm,m64,i	2	1			1	1			int		1
Arithmetic instructions												
PADD/SUB(U)(S)B/W/D	(x)mm, (x)mm	1	1	x		x				int	1	0.5
PADD/SUB(U)(S)B/W/D	(x)mm,m	1	1	x		x	1			int		1
PADDQ PSUBQ	(x)mm, (x)mm	2	2	x		x				int	2	1
PADDQ PSUBQ	(x)mm,m	2	2	x		x	1			int		1
PHADD(S)W PHSUB(S)W h)	(x)mm, (x)mm	3	3	1		2				int	3	2
PHADD(S)W PHSUB(S)W h)	(x)mm,m64	4	3	1		2	1			int		2
PHADDD PHSUBD h)	(x)mm, (x)mm	3	3	1		2				int	3	2
PHADDD PHSUBD h)	(x)mm,m64	4	3	1		2	1			int		2
PCMPEQ/GTB/W/D	(x)mm,(x)mm	1	1	x		x				int	1	0.5
PCMPEQ/GTB/W/D	(x)mm,m	1	1	x		x	1			int		1
PCMPEQQ j)	xmm,xmm	1	1			1				int	1	1
PCMPEQQ j)	xmm,m128	1	1			1	1			int		1

PMULL/HW PMULHUW	(x)mm,(x)mm	1	1		1					int	3	1
PMULL/HW PMULHUW	(x)mm,m	1	1		1		1			int		1
PMULHSW h)	(x)mm,(x)mm	1	1		1					int	3	1
PMULHSW h)	(x)mm,m	1	1		1		1			int		1
PMULLD j)	xmm,xmm	4	4		2	2				int	5	2
PMULLD j)	xmm,m128	6	5	1	2	2	1			int	5	4
PMULDQ j)	xmm,xmm	1	1		1					int	3	1
PMULDQ j)	xmm,m128	1	1		1		1			int		1
PMULUDQ	(x)mm,(x)mm	1	1		1					int	3	1
PMULUDQ	(x)mm,m	1	1		1		1			int		1
PMADDWD	(x)mm,(x)mm	1	1		1					int	3	1
PMADDWD	(x)mm,m	1	1		1		1			int		1
PMADDUBSW h)	(x)mm,(x)mm	1	1		1					int	3	1
PMADDUBSW h)	(x)mm,m	1	1		1		1			int		1
PAVGB/W	(x)mm,(x)mm	1	1	x		x				int	1	0.5
PAVGB/W	(x)mm,m	1	1	x		x	1			int		1
PMIN/MAXSB j)	xmm,xmm	1	1	1						int	1	1
PMIN/MAXSB j)	xmm,m128	1	1	1			1			int		1
PMIN/MAXUB	(x)mm,(x)mm	1	1	x		x				int	1	0.5
PMIN/MAXUB	(x)mm,m	1	1	x		x	1			int		1
PMIN/MAXSW	(x)mm,(x)mm	1	1	x		x				int	1	0.5
PMIN/MAXSW	(x)mm,m	1	1	x		x	1			int		1
PMIN/MAXUW j)	xmm,xmm	1	1	1						int	1	1
PMIN/MAXUW j)	xmm,m	1	1				1			int		1
PMIN/MAXSD j)	xmm,xmm	1	1	1						int	1	1
PMIN/MAXSD j)	xmm,m128	1	1	1			1			int		1
PMIN/MAXUD j)	xmm,xmm	1	1	1						int	1	1
PMIN/MAXUD j)	xmm,m128	1	1	1			1			int		1
PHMINPOSUW j)	xmm,xmm	4	4			4				int	4	4
PHMINPOSUW j)	xmm,m128	4	4			4	1			int		4
PASB PASW PASD h)	(x)mm,(x)mm	1	1	x		x				int	1	0.5
PASB PASW PASD h)	(x)mm,m	1	1	x		x	1			int		1
PSIGNB PSIGNW PSIGND h)	(x)mm,(x)mm	1	1	x		x				int	1	0.5
PSIGNB PSIGNW PSIGND h)	(x)mm,m	1	1	x		x	1			int		1
PSADBW	(x)mm,(x)mm	1	1		1					int	3	1
PSADBW	(x)mm,m	1	1		1		1			int		1
MPSADBW j)	xmm,xmm,i	3	3		1	2				int	5	2
MPSADBW j)	xmm,m,i	4	3		1	2	1			int		2
Logic instructions												
PAND(N) POR PXOR	(x)mm,(x)mm	1	1	x	x	x				int	1	0.33
PAND(N) POR PXOR	(x)mm,m	1	1	x	x	x	1			int		1
PTEST j)	xmm,xmm	2	2	1	x	x				int	1	1
PTEST j)	xmm,m128	2	2	1	x	x	1			int		1
PSLL/RL/RAW/D/Q	mm,mm/i	1	1	1						int	1	1
PSLL/RL/RAW/D/Q	mm,m64	1	1	1			1			int		1
PSLL/RL/RAW/D/Q	xmm,i	1	1	1						int	1	1
PSLL/RL/RAW/D/Q	xmm,xmm	2	2	x		x				int	2	1
PSLL/RL/RAW/D/Q	xmm,m128	3	2	x		x	1			int		1
PSLL/RLDQ	xmm,i	1	1	x		x				int	1	1

Other												
EMMS		11	11	x	x	x				float		6

Notes:

- g) SSE3 instruction set.
- h) "Supplementary SSE3" instruction set.
- j) SSE4.1 instruction set
- k) MASM uses the name MOVD rather than MOVQ for this instruction even when moving 64 bits
- m) Only available in 64 bit mode

6.4 Floating point XMM instructions

Instruction	Operands	µops fused domain	µops unfused domain							Unit	Latency	Reciprocal throughput
Move instructions			p015	p0	p1	p5	p2	p3	p4			
MOVAPS/D	xmm,xmm	1	1	x	x	x				int	1	0.33
MOVAPS/D	xmm,m128	1					1			int	2	1
MOVAPS/D	m128,xmm	1						1	1		3	1
MOVUPS/D	xmm,m128	4	2	1		1	2			int	2-4	2
MOVUPS/D	m128,xmm	9	4	x	x	x	1	2	2		3-4	4
MOVSS/D	xmm,xmm	1	1	x	x	x				int	1	0.33
MOVSS/D	xmm,m32/64	1					1			int	2	1
MOVSS/D	m32/64,xmm	1						1	1		3	1
MOVHPS/D MOVLPD/D	xmm,m64	2	1			1	1			int	3	1
MOVHPS/D	m64,xmm	2	1	1				1	1		5	1
MOVLPS/D	m64,xmm	1						1	1		3	1
MOVLHPS MOVHLPS	xmm,xmm	1	1	1						float	1	1
MOVMSKPS/D	r32,xmm	1	1	1						float	1	1
MOVNTPS/D	m128,xmm	1						1	1			2-3
SHUFPS	xmm,xmm,i	1	1			1				int	1	1
SHUFPS	xmm,m128,i	2	1			1	1			int		1
SHUFPD	xmm,xmm,i	1	1	1						float	1	1
SHUFPD	xmm,m128,i	2	1	1			1			float		1
BLENDPS/PD j)	xmm,xmm,i	1	1			1				int	1	1
BLENDPS/PD j)	xmm,m128,i	1	1			1	1			int		1
BLENDVPS/PD j)	xmm,xmm,xmm0	2	2			2				int	2	2
BLENDVPS/PD j)	xmm,m,xmm0	2	2			2	1			int		2
MOVDDUP g)	xmm,xmm	1	1	1						int	1	1
MOVDDUP g)	xmm,m64	2	1	1			1			int		1
MOVSH/LDUP g)	xmm,xmm	1	1			1				int	1	1
MOVSH/LDUP g)	xmm,m128	2	1			1	1			int		1
UNPCKH/LPS	xmm,xmm	1	1			1				int	1	1
UNPCKH/LPS	xmm,m128	1	1			1	1			int		1
UNPCKH/LPD	xmm,xmm	1	1	1						float	1	1
UNPCKH/LPD	xmm,m128	2	1	1			1			float		1
EXTRACTPS j)	r32,xmm,i	2	2	x	x	x				int	4	1
EXTRACTPS j)	m32,xmm,i	2	1			1		1	1	int		1
INSERTPS j)	xmm,xmm,i	1	1			1				int	1	1
INSERTPS j)	xmm,m32,i	2	1			1	1			int		1

Conversion												
CVTPD2PS	xmm,xmm	2	2	1	1					float	4	1
CVTPD2PS	xmm,m128	2	2	1	1		1			float		1
CVTSD2SS	xmm,xmm	2	2	1	1					float	4	1
CVTSD2SS	xmm,m64	2	2	1	1		1			float		1
CVTPS2PD	xmm,xmm	2	2	2						float	2	2
CVTPS2PD	xmm,m64	2	2	2			1			float		2
CVTSS2SD	xmm,xmm	2	2	2						float	2	2
CVTSS2SD	xmm,m32	2	2	2			1			float		2
CVTDQ2PS	xmm,xmm	1	1		1					float	3	1
CVTDQ2PS	xmm,m128	1	1		1		1			float		1
CVT(T) PS2DQ	xmm,xmm	1	1		1					float	3	1
CVT(T) PS2DQ	xmm,m128	1	1		1		1			float		1
CVTDQ2PD	xmm,xmm	2	2	1	1					float	4	1
CVTDQ2PD	xmm,m64	2	2	1	1		1			float		1
CVT(T)PD2DQ	xmm,xmm	2	2	1	1					float	4	1
CVT(T)PD2DQ	xmm,m128	2	2	1	1		1			float		1
CVTPI2PS	xmm,mm	1	1		1					float	3	3
CVTPI2PS	xmm,m64	1	1		1		1			float		3
CVT(T)PS2PI	mm,xmm	1	1		1					float	3	1
CVT(T)PS2PI	mm,m128	1	1		1		1			float		1
CVTPI2PD	xmm,mm	2	2	1	1					float	4	1
CVTPI2PD	xmm,m64	2	2	1	1		1			float		1
CVT(T) PD2PI	mm,xmm	2	2	1	1					float	4	1
CVT(T) PD2PI	mm,m128	2	2	1	1		1			float		1
CVTSI2SS	xmm,r32	1	1		1					float	4	3
CVTSI2SS	xmm,m32	1	1		1		1			float		3
CVT(T)SS2SI	r32,xmm	1	1		1					float	3	1
CVT(T)SS2SI	r32,m32	1	1		1		1			float		1
CVTSI2SD	xmm,r32	2	2	1	1					float	4	3
CVTSI2SD	xmm,m32	2	1		1		1			float		3
CVT(T)SD2SI	r32,xmm	1	1		1					float	3	1
CVT(T)SD2SI	r32,m64	1	1		1		1			float		1
Arithmetic												
ADDSS/D SUBSS/D	xmm,xmm	1	1		1					float	3	1
ADDSS/D SUBSS/D	xmm,m32/64	1	1		1		1			float		1
ADDPS/D SUBPS/D	xmm,xmm	1	1		1					float	3	1
ADDPS/D SUBPS/D	xmm,m128	1	1		1		1			float		1
ADDSUBPS/D g)	xmm,xmm	1	1		1					float	3	1
ADDSUBPS/D g)	xmm,m128	1	1		1		1			float		1
HADDPS HSUBPS g)	xmm,xmm	3	3		1	2				float	7	3
HADDPS HSUBPS g)	xmm,m128	4	3		1	2	1			float		3
HADDPD HSUBPD g)	xmm,xmm	3	3	x	x	x				float	6	1.5
HADDPD HSUBPD g)	xmm,m128	4	3	x	x	x	1			float		1.5
MULSS	xmm,xmm	1	1	1						float	4	1
MULSS	xmm,m32	1	1	1			1			float		1
MULSD	xmm,xmm	1	1	1						float	5	1
MULSD	xmm,m64	1	1	1			1			float		1
MULPS	xmm,xmm	1	1	1						float	4	1
MULPS	xmm,m128	1	1	1			1			float		1

MULPD	xmm,xmm	1	1	1						float	5	1
MULPD	xmm,m128	1	1	1			1			float		1
DIVSS	xmm,xmm	1	1	1						float	6-13 d)	5-12 d)
DIVSS	xmm,m32	1	1	1			1			float		5-12 d)
DIVSD	xmm,xmm	1	1	1						float	6-21 d)	5-20 d)
DIVSD	xmm,m64	1	1	1			1			float		5-20 d)
DIVPS	xmm,xmm	1	1	1						float	6-13 d)	5-12 d)
DIVPS	xmm,m128	1	1	1			1			float		5-12 d)
DIVPD	xmm,xmm	1	1	1						float	6-21 d)	5-20 d)
DIVPD	xmm,m128	1	1	1			1			float		5-20 d)
RCPSS/PS	xmm,xmm	1	1		1					float	3	2
RCPSS/PS	xmm,m	1	1		1		1			float		2
CMPccSS/D	xmm,xmm	1	1		1					float	3	1
CMPccSS/D	xmm,m32/64	1	1		1		1			float		1
CMPccPS/D	xmm,xmm	1	1		1					float	3	1
CMPccPS/D	xmm,m128	1	1		1		1			float		1
COMISS/D UCOMISS/D	xmm,xmm	1	1		1					float	3	1
COMISS/D UCOMISS/D	xmm,m32/64	1	1		1		1			float		1
MAXSS/D MINSS/D	xmm,xmm	1	1		1					float	3	1
MAXSS/D MINSS/D	xmm,m32/64	1	1		1		1			float		1
MAXPS/D MINPS/D	xmm,xmm	1	1		1					float	3	1
MAXPS/D MINPS/D	xmm,m128	1	1		1		1			float		1
ROUNDSS/D j)	xmm,xmm,i	1	1		1					float	3	1
ROUNDSS/D j)	xmm,m128,i	1	1		1		1			float		1
ROUNDPS/D j)	xmm,xmm,i	1	1		1					float	3	1
ROUNDPS/D j)	xmm,m128,i	1	1		1		1			float		1
DPPS j)	xmm,xmm,i	4	4	2	2					float	11	3
DPPS j)	xmm,m128,i	4	4	2	2		1			float		3
DPPD j)	xmm,xmm,i	4	4	x	x	x				float	9	3
DPPD j)	xmm,xmm,i	4	4	x	x	x	1			float		3
Math												
SQRTSS/PS	xmm,xmm	1	1	1						float	6-13	5-12
SQRTSS/PS	xmm,m	2	1	1			1			float		5-12
SQRTSD/PD	xmm,xmm	1	1	1						float	6-20	5-19
SQRTSD/PD	xmm,m	2	1	1			1			float		5-19
RSQRTSS/PS	xmm,xmm	1	1		1					float	3	2
RSQRTSS/PS	xmm,m	1	1		1		1			float		2
Logic												
AND/ANDN/OR/XORPS/D	xmm,xmm	1	1	x	x	x				int	1	0.33
AND/ANDN/OR/XORPS/D	xmm,m128	1	1	x	x	x	1			int		1
Other												
LDMXCSR	m32	13	12	x	x	x	1					38
STMXCSR	m32	10	8	x	x	x		1	1			20
FXSAVE	m4096	151	67	x	x	x	8	38	38			145
FXRSTOR	m4096	121	74	x	x	x	47					150

Notes:

- d) Round divisors give low values.
g) SSE3 instruction set.

7 List of instruction timings and μ ops breakdown for Core i7

Explanation of column headings:

Operands: i = immediate data, r = register, mm = 64 bit mmx register, xmm = 128 bit xmm register, (x)mm = mmx or xmm register, sr = segment register, m = memory, m32 = 32-bit memory operand, etc.

μ ops fused domain: The number of μ ops at the decode, rename, allocate and retirement stages in the pipeline. Fused μ ops count as one.

μ ops unfused domain: The number of μ ops for each execution port. Fused μ ops count as two. Fused macro-ops count as one. The instruction has μ op fusion if the sum of the numbers listed under p015 + p2 + p3 + p4 exceeds the number listed under μ ops fused domain. An x under p0, p1 or p5 means that at least one of the μ ops listed under p015 can optionally go to this port. For example, a 1 under p015 and an x under p0 and p5 means one μ op which can go to either port 0 or port 5, whichever is vacant first. A value listed under p015 but nothing under p0, p1 and p5 means that it is not known which of the three ports these μ ops go to.

p015: The total number of μ ops going to port 0, 1 and 5.

p0: The number of μ ops going to port 0 (execution units).

p1: The number of μ ops going to port 1 (execution units).

p5: The number of μ ops going to port 5 (execution units).

p2: The number of μ ops going to port 2 (memory read).

p3: The number of μ ops going to port 3 (memory write address).

p4: The number of μ ops going to port 4 (memory write data).

Domain: Tells which execution unit domain is used: "int" = integer unit (general purpose registers), "si" = SIMD integer unit (XMM integer), "fp" = floating point unit (XMM and x87 floating point). An additional "bypass delay" is generated if a register written by a μ op in one domain is read by a μ op in another domain. The bypass delay is 1 clock cycle between the "int" and "si" units, and 2 clock cycles between the "int" and "fp", and between the "si" and "fp" units.

The bypass delay is indicated under latency only where it is unavoidable because either the source operand or the destination operand is in an unnatural domain such as a general purpose register (e.g. `eax`) in the "si" domain. For example, the `PEXTRW` instruction executes in the "int" domain. The source operand is an xmm register and the destination operand is a general purpose register. The latency for this instruction is indicated as 2+1, where 2 is the latency of the instruction itself and 1 is the bypass delay, assuming that the xmm operand is most likely to come from the "si" domain. If the xmm operand comes from the "fp" domain then the bypass delay will be 2 rather than one. The flags register can also have a bypass delay. For example, the `COMISS` instruction (floating point compare) executes in the "fp" domain and returns the result in the integer flags. Almost all instructions that read these flags execute in the "int" domain. Here the latency is indicated as 1+2, where 1 is the latency of the instruction itself and 2 is the bypass delay from the "fp" domain to the "int" domain.

The bypass delay from the memory read unit to any other unit and from any unit to the memory write unit are included in the latency figures in the table. Where the domain is not listed, the bypass delays are either unlikely to occur or unavoidable and therefore included in the latency figure.

Latency: This is the delay that the instruction generates in a dependence chain. The numbers are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably. Floating point operands are presumed to be normal numbers. Denormal numbers, NAN's and infinity increase the delays very much, except in XMM move, shuffle and Boolean instructions. Floating point overflow, underflow, denormal or NAN results give a similar delay. The time unit used is core clock cycles, not the reference clock cycles given by the time stamp counter.

Reciprocal throughput: The average number of core clock cycles per instruction for a series of independent instructions of the same kind in the same thread.

7.1 Integer instructions

Instruction	Operands	µops fused domain	µops unfused domain							Latency	Reciprocal throughput
			p015	p0	p1	p5	p2	p3	p4		
Move instructions											
MOV	r,r/i	1	1	x	x	x				1	0.33
MOV a)	r,m	1					1			2	1
MOV a)	m,r	1						1	1	3	1
MOV	m,i	1						1	1	3	1
MOV	r,sr	1					1				1
MOV	m,sr	2					1	1	1		1
MOV	sr,r	6	3	x	x	x	3				13
MOV	sr,m	6	2	x		x	4				14
MOVNTI	m,r	2						1	1	~270	1
MOVSX MOVZX MOVSLD	r,r	1	1	x	x	x				1	0.33
MOVSX MOVZX MOVSLD	r,m	1					1				1
CMOVcc	r,r	2	2	x	x	x				2	1
CMOVcc	r,m	2	2	x	x	x	1				
XCHG	r,r	3	3	x	x	x				2	2
XCHG	r,m	7					1	1	1	20 b)	
XLAT		2	1				1			5	1
PUSH	r	1						1	1	3	1
PUSH	i	1						1	1		1
PUSH	m	2					1	1	1		1
PUSH	sr	2	1					1	1		1
PUSHF(D/Q)		3	2	x	x	x		1	1		1
PUSHA(D) i)		18	2	x	1	x		8	8		8
POP	r	1					1			2	1
POP	(E/R)SP	3	2	x	1	x	1				5
POP	m	2					1	1	1		1
POP	sr	7	2				5				15
POPF(D/Q)		8	7	x	x	x	1				14

POPA(D) i)		10	2				8				8
LAHF SAHF		1	1	x	x	x				1	0.33
SALC i)		2	2	x	x	x				4	1
LEA a)	r,m	1	1		1					1	1
BSWAP	r32	1	1		1					1	1
BSWAP	r64	1	1		1					3	1
LDS LES LFS LGS LSS	m	9	3	x	x	x	6				15
PREFETCHNTA	m	1					1				1
PREFETCHT0/1/2	m	1					1				1
LFENCE		2						1	1		9
MFENCE		3	1	x	x	x		1	1		23
SFENCE		2						1	1		5
Arithmetic instructions											
ADD SUB	r,r/i	1	1	x	x	x				1	0.33
ADD SUB	r,m	1	1	x	x	x	1				1
ADD SUB	m,r/i	2	1	x	x	x	1	1	1	6	1
ADC SBB	r,r/i	2	2	x	x	x				2	2
ADC SBB	r,m	2	2	x	x	x	1			2	2
ADC SBB	m,r/i	4	3	x	x	x	1	1	1	7	
CMP	r,r/i	1	1	x	x	x				1	0.33
CMP	m,r/i	1	1	x	x	x	1			1	1
INC DEC NEG NOT	r	1	1	x	x	x				1	0.33
INC DEC NEG NOT	m	3	1	x	x	x	1	1	1	6	1
AAA AAS DAA DAS i)		1	1		1					3	1
AAD i)		3	3	x	x	x				15	2
AAM i)		5	5	x	x	x				20	7
MUL IMUL	r8	1	1		1					3	1
MUL IMUL	r16	3	3	x	x	x				5	2
MUL IMUL	r32	3	3	x	x	x				5	2
MUL IMUL	r64	3	3	x	x	x				3	2
IMUL	r16,r16	1	1		1					3	1
IMUL	r32,r32	1	1		1					3	1
IMUL	r64,r64	1	1	1						3	1
IMUL	r16,r16,i	1	1		1					3	1
IMUL	r32,r32,i	1	1		1					3	1
IMUL	r64,r64,i	1	1	1						3	2
MUL IMUL	m8	1	1		1		1			3	1
MUL IMUL	m16	3	3	x	x	x	1			5	2
MUL IMUL	m32	3	3	x	x	x	1			5	2
MUL IMUL	m64	3	2	2			1			3	2
IMUL	r16,m16	1	1		1		1			3	1
IMUL	r32,m32	1	1		1		1			3	1
IMUL	r64,m64	1	1	1			1			3	1
IMUL	r16,m16,i	1	1		1		1				1
IMUL	r32,m32,i	1	1		1		1				1
IMUL	r64,m64,i	1	1	1			1				1
DIV c)	r8	4	4	1	2	1				11-21	7-11
DIV c)	r16	6	6	x	4	x				17-22	7-12
DIV c)	r32	6	6	x	3	x				17-28	7-17
DIV c)	r64	~40		x	x	x				28-90	19-69

IDIV c)	r8	4	4	1	2	1				10-22	7-11
IDIV c)	r16	8	8	x	5	x				18-23	7-12
IDIV c)	r32	7	7	x	3	x				17-28	7-17
IDIV c)	r64	~60		x	x	x				37-100	26-86
CBW CWDE CDQE		1	1	x	x	x				1	1
CWD CDQ CQO		1	1	x		x				1	1
POPCNT ℓ)	r,r	1	1		1					3	1
POPCNT ℓ)	r,m	1	1		1		1				1
CRC32 ℓ)	r,r	1	1		1					3	1
CRC32 ℓ)	r,m	1	1		1		1				1
Logic instructions											
AND OR XOR	r,r/i	1	1	x	x	x				1	0.33
AND OR XOR	r,m	1	1	x	x	x	1				1
AND OR XOR	m,r/i	2	1	x	x	x	1	1	1	6	1
TEST	r,r/i	1	1	x	x	x				1	0.33
TEST	m,r/i	1	1	x	x	x	1				1
SHR SHL SAR	r,i/cl	1	1	x		x				1	0.5
SHR SHL SAR	m,i/cl	3	2	x		x	1	1	1	6	1
ROR ROL	r,i/cl	1	1	x		x				1	1
ROR ROL	m,i/cl	3	2	x		x	1	1	1	6	1
RCR RCL	r,l	2	2	x	x	x				2	2
RCR	r8,i/cl	9	9	x	x	x				13	
RCL	r8,i/cl	8	8	x	x	x				11	
RCR RCL	r16/32/64,i/cl	6	6	x	x	x				12-13	12-13
RCR RCL	m,l	4	3	x	x	x	1	1	1	7	
RCR	m8,i/cl	12	9	x	x	x	1	1	1	16	
RCL	m8,i/cl	11	8	x	x	x	1	1	1	14	
RCR RCL	m16/32/64,i/cl	10	7	x	x	x	1	1	1	15	
SHLD	r,r,i/cl	2	2	x	x	x				3	1
SHLD	m,r,i/cl	3	2	x	x	x	1	1	1	8	
SHRD	r,r,i/cl	2	2	x	x	x				4	1
SHRD	m,r,i/cl	3	2	x	x	x	1	1	1	9	
BT	r,r/i	1	1	x		x				1	1
BT	m,r	9	8	x		x	1				5
BT	m,i	2	2	x		x	1				1
BTR BTS BTC	r,r/i	1	1	x		x				1	1
BTR BTS BTC	m,r	10	7	x	x	x	1	1	1	6	
BTR BTS BTC	m,i	3	3	x		x	1	1	1	6	
BSF BSR	r,r	1	1		1					3	1
BSF BSR	r,m	2	1		1		1			3	1
SETcc	r	1	1	x		x				1	1
SETcc	m	2	1	x	x	x		1	1		1
CLC STC CMC		1	1	x	x	x				1	0.33
CLD		2	2	x	x	x					4
STD		2	2	x	x	x					5
Control transfer instructions											
JMP	short/near	1	1			1				0	2
JMP i)	far	31	31								67
JMP	r	1	1			1				0	2

JMP	m(near)	1	1			1	1			0	2
JMP	m(far)	31	31				11				73
Conditional jump	short/near	1	1			1				0	2
Fused compare and branch e)		1	1			1				0	2
Fused test and branch e)		1	1			1				0	2
J(E/R)CXZ	short	2	2	x	x	1					2
LOOP	short	6	6	x	x	x					4
LOOP(N)E	short	11	11	x	x	x					7
CALL	near	2	2			1		1	1		2
CALL i)	far	46	46				9				74
CALL	r	3	2			1		1	1		2
CALL	m(near)	4	3			1	1	1	1		2
CALL	m(far)	47	47				1				79
RETN		1	1			1	1				2
RETN	i	3	2			1	1				2
RETF		39	39								120
RETF	i	40	40								124
BOUND i)	r,m	15	13				2				7
INTO i)		4	4								5
String instructions											
LODS		2	1	x	x	x	1				1
REP LODS		11+4n								40+12n	
STOS		3	1	x	x	x		1	1		1
REP STOS	small n	60+n								12+n	
REP STOS	large n	2.5/16 bytes								1 clock / 16 bytes	
MOVS		5	2	x	x	x	1	1	1		4
REP MOVS	small n	13+6n								12+n	
REP MOVS	large n	2/16 bytes								1 clock / 16 bytes	
SCAS		3	2	x	x	x	1				1
REP SCAS		37+6n								40+2n	
CMPS		5	3	x	x	x	2				4
REP CMPS		65+8n								42+2n	
Other											
NOP (90)		1	1	x	x	x					0.33
NOP (0F 1F mod000rm)		1	1	x	x	x					1
PAUSE		5	5	x	x	x					9
ENTER	a,0	11	9	x	x	x	1	1	1		8
ENTER	a,b	34+7b								79+5b	
LEAVE		3	3				1				5
CPUID		25-100								~200	
RDTSC		22									24
RDPMSR		28									40-60

Notes:

- Applies to all addressing modes
- Has an implicit LOCK prefix.
- Low values are for small results, high values for high results.
- See manual 3: "The microarchitecture of Intel, AMD and VIA CPUs" for restrictions on macro-op fusion.
- Not available in 64 bit mode.

ℓ) SSE4.2 instruction set.

7.2 Floating point x87 instructions

Instruction	Operands	jops fused domain	jops unfused domain							Domain	Latency	Reciprocal throughput
Move instructions			p015	p0	p1	p5	p2	p3	p4			
FLD	r	1	1	1						float	1	1
FLD	m32/64	1	1				1			float	3	1
FLD	m80	4	2	1	1		2			float	4	2
FBLD	m80	41	38	x	x	x	3			float	45	20
FST(P)	r	1	1	1						float	1	1
FST(P)	m32/m64	1						1	1	float	4	1
FSTP	m80	7	3	x	x	x		2	2	float	5	5
FBSTP	m80	208	204	x	x	x		2	2	float	242	245
FXCH	r	1	0 f)							float	0	1
FILD	m	1	1		1		1			float	6	1
FIST(P)	m	3	1		1			1	1	float	7	1
FISTTP g)	m	3	1		1			1	1	float	7	1
FLDZ		1	1	1						float		1
FLD1		2	2	1	1					float		2
FLDPI FLDL2E etc.		2	2		2					float		2
FCMOVcc	r	2	2	2						float	2+2	2
FNSTSW	AX	2	2							float		1
FNSTSW	m16	3	2					1	1	float		2
FLDCW	m16	2	1				1			float	7	31
FNSTCW	m16	2	1	1				1	1	float	5	1
FINCSTP FDECSTP		1	1	1						float	1	1
FFREE(P)	r	2	2	x	x	x				float		4
FNSAVE	m	143	89	x	x	x	8	23	23	float	178	178
FRSTOR	m	79	52	x	x	x	27			float	156	156
Arithmetic instructions												
FADD(P) FSUB(R)(P)	r	1	1		1					float	3	1
FADD(P) FSUB(R)(P)	m	1	1		1		1			float		1
FMUL(P)	r	1	1	1						float	5	1
FMUL(P)	m	1	1	1			1			float		1
FDIV(R)(P)	r	1	1	1						float	7-27 d)	7-27 d)
FDIV(R)(P)	m	1	1	1			1			float	7-27 d)	7-27 d)
FABS		1	1	1						float	1	1
FCHS		1	1	1						float	1	1
FCOM(P) FUCOM	r	1	1		1					float		1
FCOM(P) FUCOM	m	1	1		1		1			float		1
FCOMPP FUCOMPP		2	2	1	1					float		1
FCOMI(P) FUCOMI(P)	r	1	1		1					float		1
FIADD FISUB(R)	m	2	2		2		1			float	3	2
FIMUL	m	2	2	1	1		1			float	5	2
FIDIV(R)	m	2	2	1	1		1			float	7-27 d)	7-27 d)
FICOM(P)	m	2	2		2		1			float		1

FTST		1	1		1					float		1
FXAM		1	1		1					float		1
FPREM		25	25	x	x	x				float	14	
FPREM1		35	35	x	x	x				float	19	
FRNDINT		17	17	x	x	x				float	22	
Math												
FSCALE		24	24	x	x	x				float	12	
EXTRACT		17	17	x	x	x				float	13	
FSQRT		1	1	1						float	~27	
FSIN		~100	~100	x	x	x				float	40-100	
FCOS		~100	~100	x	x	x				float	40-100	
FSINCOS		~100	~100	x	x	x				float	~110	
F2XM1		19	19	x	x	x				float	58	
FYL2X FYL2XP1		~55	~55	x	x	x				float	~80	
FPTAN		~100	~100	x	x	x				float	~115	
FPATAN		~82	~82	x	x	x				float	~120	
Other												
FNOP		1	1	1						float		1
WAIT		2	2	x	x	x				float		1
FNCLEX		3	3		x	x				float		17
FNINIT		~190	~190	x	x	x				float		77

Notes:

- d) Round divisors or low precision give low values.
- f) Resolved by register renaming. Generates no μ ops in the unfused domain.
- g) SSE3 instruction set.

7.3 Integer MMX and XMM instructions

Instruction	Operands	jops fused domain	jops unfused domain							Domain	Latency	Reciprocal throughput
Move instructions			p015	p0	p1	p5	p2	p3	p4			
MOVD k)	r32/64,(x)mm	1	1	x	x	x				int	1+1	0.33
MOVD k)	m32/64,(x)mm	1						1	1		3	1
MOVD k)	(x)mm,r32/64	1	1	x	x	x				si	1+1	0.33
MOVD k)	(x)mm,m32/64	1					1				2	1
MOVQ	(x)mm, (x)mm	1	1	x	x	x				si	1	0.33
MOVQ	(x)mm,m64	1					1				2	1
MOVQ	m64, (x)mm	1						1	1		3	1
MOVDQA	xmm, xmm	1	1	x	x	x				si	1	0.33
MOVDQA	xmm, m128	1					1				2	1
MOVDQA	m128, xmm	1						1	1		3	1
MOVDQU	xmm, m128	1	1				1				2	1
MOVDQU	m128, xmm	1	1					1	1		3	1
LDDQU g)	xmm, m128	1	1				1				2	1
MOVDQ2Q	mm, xmm	1	1	x	x	x				si	1	0.33
MOVQ2DQ	xmm,mm	1	1	x	x	x				si	1	0.33
MOVNTQ	m64,mm	1						1	1		~270	2
MOVNTDQ	m128,xmm	1						1	1		~270	2
MOVNTDQA j)	xmm, m128	1					1				2	1
PACKSSWB/DW PACKUSWB	mm,mm	1	1		1					si	1	1
PACKSSWB/DW PACKUSWB	mm,m64	1	1		1		1					2
PACKSSWB/DW PACKUSWB	xmm,xmm	1	1	x		x				si	1	0.5
PACKSSWB/DW PACKUSWB	xmm,m128	1	1	x		x	1					2
PACKUSDW j)	xmm,xmm	1	1	x		x				si	1	2
PACKUSDW j)	xmm,m	1	1	x		x	1					2
PUNPCKH/LBW/WD/DQ	(x)mm, (x)mm	1	1	x		x				si	1	0.5
PUNPCKH/LBW/WD/DQ	(x)mm,m	1	1	x		x	1					2
PUNPCKH/LQDQ	xmm,xmm	1	1	x		x				si	1	0.5
PUNPCKH/LQDQ	xmm, m128	2	1	x		x	1					1
PMOVSX/ZXBW j)	xmm,xmm	1	1	x		x				si	1	1
PMOVSX/ZXBW j)	xmm,m64	1	1	x		x	1					2
PMOVSX/ZXBD j)	xmm,xmm	1	1	x		x				si	1	1
PMOVSX/ZXBD j)	xmm,m32	1	1	x		x	1					2
PMOVSX/ZXBQ j)	xmm,xmm	1	1	x		x				si	1	1
PMOVSX/ZXBQ j)	xmm,m16	1	1	x		x	1					2
PMOVSX/ZXWD j)	xmm,xmm	1	1	x		x				si	1	1
PMOVSX/ZXWD j)	xmm,m64	1	1	x		x	1					2
PMOVSX/ZXWQ j)	xmm,xmm	1	1	x		x				si	1	1
PMOVSX/ZXWQ j)	xmm,m32	1	1	x		x	1					2
PMOVSX/ZXDQ j)	xmm,xmm	1	1	x		x				si	1	1
PMOVSX/ZXDQ j)	xmm,m64	1	1	x		x	1					2
PSHUFB h)	(x)mm, (x)mm	1	1	x		x				si	1	0.5
PSHUFB h)	(x)mm,m	2	1	x		x	1					1

PSHUFW	mm,mm,i	1	1	x		x				si	1	0.5
PSHUFW	mm,m64,i	2	1	x		x	1					1
PSHUFD	xmm,xmm,i	1	1	x		x				si	1	0.5
PSHUFD	xmm,m128,i	2	1	x		x	1					1
PSHUFL/HW	xmm,xmm,i	1	1	x		x				si	1	0.5
PSHUFL/HW	xmm, m128,i	2	1	x		x	1					1
PALIGNR h)	(x)mm,(x)mm,i	1	1	x		x				si	1	1
PALIGNR h)	(x)mm,m,i	2	1	x		x	1					1
PBLENDVB j)	xmm,xmm,xmm0	2	2	1		1				si	2	1
PBLENDVB j)	xmm,m,xmm0	3	2	1		1	1					1
PBLENDW j)	xmm,xmm,i	1	1	x		x				si	1	0.5
PBLENDW j)	xmm,m,i	2	1	x		x	1					1
MASKMOVQ	mm,mm	4	1	1			1	1	1	si		2
MASKMOVDQU	xmm,xmm	10	4	x	x	x	2	2	x	si		7
PMOVBMSKB	r32,(x)mm	1	1	1						float	2+2	1
PEXTRB j)	r32,xmm,i	2	2	x	x	x				si	2+1	1
PEXTRB j)	m8,xmm,i	2	2	x		x						1
PEXTRW	r32,(x)mm,i	2	2	x	x	x				si	2+1	1
PEXTRW j)	m16,(x)mm,i	2	2	x		x		1	1			1
PEXTRD j)	r32,xmm,i	2	2	x	x	x				si	2+1	1
PEXTRD j)	m32,xmm,i	2	1	x		x		1	1			1
PEXTRQ j,m)	r64,xmm,i	2	2	x	x	x				si	2+1	1
PEXTRQ j,m)	m64,xmm,i	2	1	x		x		1	1			1
PINSRB j)	xmm,r32,i	1	1	x		x				si	1+1	1
PINSRB j)	xmm,m8,i	2	1	x		x	1					1
PINSRW	(x)mm,r32,i	1	1	x		x				si	1+1	1
PINSRW	(x)mm,m16,i	2	1	x		x	1					1
PINSRD j)	xmm,r32,i	1	1	x		x				si	1+1	1
PINSRD j)	xmm,m32,i	2	1	x		x	1					1
PINSRQ j,m)	xmm,r64,i	1	1	x		x				si	1+1	1
PINSRQ j,m)	xmm,m64,i	2	1	x		x	1					1
Arithmetic instructions												
PADD/SUB(U)(S)B/W/D/Q	(x)mm, (x)mm	1	1	x		x				si	1	0.5
PADD/SUB(U)(S)B/W/D/Q	(x)mm,m	1	1	x		x	1					2
PHADD/SUB(S)W/D h)	(x)mm, (x)mm	3	3	x		x				si	3	1.5
PHADD/SUB(S)W/D h)	(x)mm,m64	4	3	x		x	1					3
PCMPEQ/GTB/W/D	(x)mm,(x)mm	1	1	x		x				si	1	0.5
PCMPEQ/GTB/W/D	(x)mm,m	1	1	x		x	1					2
PCMPEQQ j)	xmm,xmm	1	1	x		x				si	1	0.5
PCMPEQQ j)	xmm,m128	1	1	x		x	1					2
PCMPGTQ ℓ)	xmm,xmm	1	1		1					si	3	1
PCMPGTQ ℓ)	xmm,m128	1	1		1		1					1
PMULL/HW PMULHUW	(x)mm,(x)mm	1	1		1					si	3	1
PMULL/HW PMULHUW	(x)mm,m	1	1		1		1					1
PMULHSW h)	(x)mm,(x)mm	1	1		1					si	3	1
PMULHSW h)	(x)mm,m	1	1		1		1					1
PMULLD j)	xmm,xmm	2	2		2					si	6	2
PMULLD j)	xmm,m128	3	2		2		1					
PMULDQ j)	xmm,xmm	1	1		1					si	3	1
PMULDQ j)	xmm,m128	1	1		1		1					1

PMULUDQ	(x)mm,(x)mm	1	1		1					si	3	1
PMULUDQ	(x)mm,m	1	1		1		1					1
PMADDWD	(x)mm,(x)mm	1	1		1					si	3	1
PMADDWD	(x)mm,m	1	1		1		1					1
PMADDUBSW h)	(x)mm,(x)mm	1	1		1					si	3	1
PMADDUBSW h)	(x)mm,m	1	1		1		1					1
PAVGB/W	(x)mm,(x)mm	1	1	x		x				si	1	0.5
PAVGB/W	(x)mm,m	1	1	x		x	1					1
PMIN/MAXSB j)	xmm,xmm	1	1	x		x				si	1	1
PMIN/MAXSB j)	xmm,m128	1	1	x		x	1					2
PMIN/MAXUB	(x)mm,(x)mm	1	1	x		x				si	1	0.5
PMIN/MAXUB	(x)mm,m	1	1	x		x	1					2
PMIN/MAXSW	(x)mm,(x)mm	1	1	x		x				si	1	0.5
PMIN/MAXSW	(x)mm,m	1	1	x		x	1					2
PMIN/MAXUW j)	xmm,xmm	1	1	x		x				si	1	1
PMIN/MAXUW j)	xmm,m	1	1	x		x	1					2
PMIN/MAXU/SD j)	xmm,xmm	1	1	x		x				si	1	1
PMIN/MAXU/SD j)	xmm,m128	1	1	x		x	1					2
PHMINPOSUW j)	xmm,xmm	1	1		1					si	3	1
PHMINPOSUW j)	xmm,m128	1	1		1		1					3
PASB PABSW PABSD h)	(x)mm,(x)mm	1	1	x		x				si	1	0.5
PASB PABSW PABSD h)	(x)mm,m	1	1	x		x	1					1
PSIGNB PSIGNW PSIGND h)	(x)mm,(x)mm	1	1	x		x				si	1	0.5
PSIGNB PSIGNW PSIGND h)	(x)mm,m	1	1	x		x	1					2
PSADBW	(x)mm,(x)mm	1	1		1					si	3	1
PSADBW	(x)mm,m	1	1		1		1					3
MPSADBW j)	xmm,xmm,i	3	3	x	x	x				si	5	1
MPSADBW j)	xmm,m,i	4	3	x	x	x	1					2
PCLMULQDQ n)	xmm,xmm,i										12	8
AESDEC, AESDECLAST, AESENC, AESENCLAST n)	xmm,xmm										~5	~2
AESIMC n)	xmm,xmm										~5	~2
AESKEYGENASSIST n)	xmm,xmm,i										~5	~2
Logic instructions												
PAND(N) POR PXOR	(x)mm,(x)mm	1	1	x	x	x				si	1	0.33
PAND(N) POR PXOR	(x)mm,m	1	1	x	x	x	1					1
PTEST j)	xmm,xmm	2	2	x	x	x				si	3	1
PTEST j)	xmm,m128	2	2	x	x	x	1					1
PSLL/RL/RAW/D/Q	mm,mm/i	1	1		1					si	1	1
PSLL/RL/RAW/D/Q	mm,m64	1	1		1		1					2
PSLL/RL/RAW/D/Q	xmm,i	1	1		1					si	1	1
PSLL/RL/RAW/D/Q	xmm,xmm	2	2	x	1	x				si	2	2
PSLL/RL/RAW/D/Q	xmm,m128	3	2	x	1	x	1					1
PSLL/RLDQ	xmm,i	1	1	x		x				si	1	1
String instructions												
PCMPESTRI ℓ)	xmm,xmm,i	8	8	x	x	x				si	14	5
PCMPESTRI ℓ)	xmm,m128,i	9	8	x	x	x	1			si	14	6
PCMPESTRM ℓ)	xmm,xmm,i	9	9	x	x	x				si	7	6
PCMPESTRM ℓ)	xmm,m128,i	10	10	x	x	x	1			si	7	6

PCMPISTRI ℓ)	xmm,xmm,i	3	3	x	x	x				si	8	2
PCMPISTRI ℓ)	xmm,m128,i	4	4	x	x	x	1			si	8	2
PCMPISTRM ℓ)	xmm,xmm,i	4	4	x	x	x				si	7	2
PCMPISTRM ℓ)	xmm,m128,i	6	5	x	x	x	1			si	7	5
Other												
EMMS		11	11	x	x	x				float		6

Notes:

- g) SSE3 instruction set.
- h) "Supplementary SSE3" instruction set.
- j) SSE4.1 instruction set
- k) MASM uses the name MOVD rather than MOVQ for this instruction even when moving 64 bits
- ℓ) SSE4.2 instruction set
- m) Only available in 64 bit mode
- n) Only available on newer models

7.4 Floating point XMM instructions

Instruction	Operands	μops fused domain	μops unfused domain							Domain	Latency	Reciprocal throughput
Move instructions			p015	p0	p1	p5	p2	p3	p4			
MOVAPS/D	xmm,xmm	1	1			1				float	1	1
MOVAPS/D	xmm,m128	1					1				2	1
MOVAPS/D	m128,xmm	1						1	1		3	1
MOVUPS/D	xmm,m128	1					1				2	1-4
MOVUPS/D	m128,xmm	1						1	1		3	1-3
MOVSS/D	xmm,xmm	1	1			1					1	1
MOVSS/D	xmm,m32/64	1					1				2	1
MOVSS/D	m32/64,xmm	1						1	1		3	1
MOVHPS/D MOVLP/D	xmm,m64	2	1			1	1				3	2
MOVH/LPS/D	m64,xmm	2	1			1		1	1		5	1
MOVLHPS MOVHLPS	xmm,xmm	1	1			1				float	1	1
MOVMSKPS/D	r32,xmm	1	1	1						float	1+2	1
MOVNTPS/D	m128,xmm	1						1	1		~270	2
SHUFPS/D	xmm,xmm,i	1	1			1				float	1	1
SHUFPS/D	xmm,m128,i	2	1			1	1			float		1
BLENDPS/PD j)	xmm,xmm,i	1	1			1				float	1	1
BLENDPS/PD j)	xmm,m128,i	2	1			1	1			float		1
BLENDVPS/PD j)	xmm,xmm,xmm0	2	2			2				float	2	2
BLENDVPS/PD j)	xmm,m,xmm0	3	2			2	1			float		2
MOVDDUP g)	xmm,xmm	1	1			1				float	1	1
MOVDDUP g)	xmm,m64	1					1				2	1
MOVSH/LDUP g)	xmm,xmm	1	1			1				float	1	1
MOVSH/LDUP g)	xmm,m128	1					1					1
UNPCKH/LPS/D	xmm,xmm	1	1			1				float	1	1
UNPCKH/LPS/D	xmm,m128	1	1			1	1			float		1
EXTRACTPS j)	r32,xmm,i	1	1			1				float	1+2	1
EXTRACTPS j)	m32,xmm,i	2	1			1		1	1			1
INSERTPS j)	xmm,xmm,i	1	1			1				float	1	1
INSERTPS j)	xmm,m32,i	3	1			2	1			float		2

Conversion												
CVTPD2PS	xmm,xmm	2	2		1	1				float	4	1
CVTPD2PS	xmm,m128	2	2		1		1			float		1
CVTSD2SS	xmm,xmm	2	2		1	1				float	4	1
CVTSD2SS	xmm,m64	2	2		1		1			float		1
CVTPS2PD	xmm,xmm	2	2	1		1				float	2	1
CVTPS2PD	xmm,m64	2	2	1		1	1			float		1
CVTSS2SD	xmm,xmm	1	1	1						float	1	1
CVTSS2SD	xmm,m32	1	1	1			1			float		2
CVTDQ2PS	xmm,xmm	1	1		1					float	3+2	1
CVTDQ2PS	xmm,m128	1	1		1		1			float		1
CVT(T) PS2DQ	xmm,xmm	1	1		1					float	3+2	1
CVT(T) PS2DQ	xmm,m128	1	1		1		1			float		1
CVTDQ2PD	xmm,xmm	2	2		1	1				float	4+2	1
CVTDQ2PD	xmm,m64	2	2		1	1	1			float		1
CVT(T)PD2DQ	xmm,xmm	2	2		1	1				float	4+2	1
CVT(T)PD2DQ	xmm,m128	2	2		1	1	1			float		1
CVTPI2PS	xmm,mm	1	1		1					float	3+2	3
CVTPI2PS	xmm,m64	1	1		1		1			float		3
CVT(T)PS2PI	mm,xmm	1	1		1					float	3+2	1
CVT(T)PS2PI	mm,m128	1	1		1		1			float		1
CVTPI2PD	xmm,mm	2	2		1	1				si/float	6	1
CVTPI2PD	xmm,m64	2	2		1	1	1					1
CVT(T) PD2PI	mm,xmm	2	2	x	1	x				float/si	6	1
CVT(T) PD2PI	mm,m128	2	2	x	1	x	1					1
CVTSI2SS	xmm,r32	1	1		1					float	3+2	3
CVTSI2SS	xmm,m32	1	1		1		1			float		3
CVT(T)SS2SI	r32,xmm	1	1		1					float	3+2	1
CVT(T)SS2SI	r32,m32	1	1		1		1			float		1
CVTSI2SD	xmm,r32	2	2	1	1					float	4+2	3
CVTSI2SD	xmm,m32	2	1		1		1			float		3
CVT(T)SD2SI	r32,xmm	1	1		1					float	3+2	1
CVT(T)SD2SI	r32,m64	1	1		1		1			float		1
Arithmetic												
ADDSS/D SUBSS/D	xmm,xmm	1	1		1					float	3	1
ADDSS/D SUBSS/D	xmm,m32/64	1	1		1		1			float		1
ADDPS/D SUBPS/D	xmm,xmm	1	1		1					float	3	1
ADDPS/D SUBPS/D	xmm,m128	1	1		1		1			float		1
ADDSUBPS/D g)	xmm,xmm	1	1		1					float	3	1
ADDSUBPS/D g)	xmm,m128	1	1		1		1			float		1
HADDPS HSUBPS g)	xmm,xmm	3	3		1	2				float	5	2
HADDPS HSUBPS g)	xmm,m128	4	3		1	2	1			float		2
HADDPD HSUBPD g)	xmm,xmm	3	3		1	2				float	3	2
HADDPD HSUBPD g)	xmm,m128	4	3		1	2	1			float		2
MULSS MULPS	xmm,xmm	1	1	1						float	4	1
MULSS MULPS	xmm,m	1	1	1			1			float		1
MULSD MULPD	xmm,xmm	1	1	1						float	5	1
MULSD MULPD	xmm,m	1	1	1			1			float		1

DIVSS DIVPS	xmm,xmm	1	1	1						float	7-14	7-14
DIVSS DIVPS	xmm,m	1	1	1			1			float		7-14
DIVSD DIVPD	xmm,xmm	1	1	1						float	7-22	7-22
DIVSD DIVPD	xmm,m	1	1	1			1			float		7-22
RCPSS/PS	xmm,xmm	1	1		1					float	3	2
RCPSS/PS	xmm,m	1	1		1		1			float		2
CMPccSS/D CMPccPS/D	xmm,xmm	1	1		1					float	3	1
CMPccSS/D CMPccPS/D	xmm,m	2	1		1		1			float		1
COMISS/D UCOMISS/D	xmm,xmm	1	1		1					float	1+2	1
COMISS/D UCOMISS/D	xmm,m32/64	1	1		1		1			float		1
MAXSS/D MINSS/D	xmm,xmm	1	1		1					float	3	1
MAXSS/D MINSS/D	xmm,m32/64	1	1		1		1			float		1
MAXPS/D MINPS/D	xmm,xmm	1	1		1					float	3	1
MAXPS/D MINPS/D	xmm,m128	1	1		1		1			float		1
ROUNDSS/D ROUNDPS/D j)	xmm,xmm,i	1	1		1					float	3	1
ROUNDSS/D ROUNDPS/D j)	xmm,m128,i	2	1		1		1			float		1
DPSS j)	xmm,xmm,i	4	4	1	2	1				float	11	2
DPSS j)	xmm,m128,i	6	5	x	x	x	1			float		
DPPD j)	xmm,xmm,i	3	3	x	x	x				float	9	1
DPPD j)	xmm,xmm,i	4	3	x	x	x	1			float		3
Math												
SQRTSS/PS	xmm,xmm	1	1	1						float	7-18	7-18
SQRTSS/PS	xmm,m	2	1	1			1			float		7-18
SQRTSD/PD	xmm,xmm	1	1	1						float	7-32	7-32
SQRTSD/PD	xmm,m	2	1	1			1			float		7-32
RSQRTSS/PS	xmm,xmm	1	1		1					float	3	2
RSQRTSS/PS	xmm,m	1	1		1		1			float		2
Logic												
AND/ANDN/OR/XORPS/D	xmm,xmm	1	1			1				float	1	1
AND/ANDN/OR/XORPS/D	xmm,m128	1	1			1	1			float		1
Other												
LDMXCSR	m32	6	6	x	x	x	1					5
STMXCSR	m32	2	1			1		1	1			1
FXSAVE	m4096	141	141	x	x	x	5	38	38		90	90
FXRSTOR	m4096	112	90	x	x	x	42					100

Notes:

g) SSE3 instruction set.

8 List of instruction timings and μ op breakdown for P4

This list is measured for a Pentium 4, model 2. Timings for model 3 may be more like the values for P4E, listed in chapter 9.

Explanation of column headings:

Instruction: Instruction name. cc means any condition code. For example, Jcc can be JB, JNE, etc.

Operands: i = immediate constant, r = any register, r32 = 32-bit register, etc., mm = 64 bit mmx register, xmm = 128 bit xmm register, sr = segment register, m = any memory operand including indirect operands, m64 means 64-bit memory operand, etc.

μ ops: Number of μ ops issued from instruction decoder and stored in trace cache.

Microcode: Number of additional μ ops issued from microcode ROM.

Latency: The number of clock cycles from the execution of an instruction begins to the next dependent instruction can begin, if the latter instruction starts in the same execution unit. The numbers are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably. Floating point operands are presumed to be normal numbers. Denormal numbers, NAN's, infinity and exceptions increase the delays. The latency of moves to and from memory cannot be measured accurately because of the problem with memory intermediates explained in manual 3: "The microarchitecture of Intel, AMD and VIA CPUs". Avoid making optimizations that rely on the latency of memory operations.

Additional latency: This number is added to the latency if the next dependent instruction is in a different execution unit. There is no additional latency between ALU0 and ALU1.

Reciprocal throughput: This is also called issue latency. This value indicates the number of clock cycles from the execution of an instruction begins to a subsequent independent instruction can begin to execute in the same execution subunit. A value of 0.25 indicates 4 instructions per clock cycle in one thread.

Port: The port through which each μ op goes to an execution unit. Two independent μ ops can start to execute simultaneously only if they are going through different ports.

Execution unit: Use this information to determine additional latency. When an instruction with more than one μ op uses more than one execution unit, only the first and the last execution unit is listed.

Execution subunit: Throughput measures apply only to instructions executing in the same subunit.

Backwards compatibility: Indicates the first microprocessor in the Intel 80x86 family that supported the instruction.

8.1 integer instructions

Instruction	Operands	μops	Microcode	Latency	Additional latency	Reciprocal throughput	Port	Execution unit	Subunit	Backwards compatibility	Notes
Move instructions											
MOV	r,r	1	0	0.5	0.5-1	0.25	0/1	alu0/1		86	c
MOV	r,i	1	0	0.5	0.5-1	0.25	0/1	alu0/1		86	
MOV	r32,m	1	0	2	0	1	2	load		86	
MOV	r8/16,m	2	0	3	0	1	2	load		86	
MOV	m,r	1	0	1		2	0	store		86	b, c
MOV	m,i	3	0			2	0,3	store		86	
MOV	r,sr	4	2			6				86	
MOV	sr,r/m	4	4	12	0	14				86	a, q
MOVNTI	m,r32	2	0			≈33				sse2	
MOVZX	r,r	1	0	0.5	0.5-1	0.25	0/1	alu0/1		386	c
MOVZX	r,m	1	0	2	0	1	2	load		386	
MOVSX	r,r	1	0	0.5	0.5-1	0.5	0	alu0		386	c
MOVSX	r,m	2	0	3	0.5-1	1	2,0			386	
CMOVcc	r,r/m	3	0	6	0	3				ppro	a, e
XCHG	r,r	3	0	1.5	0.5-1	1	0/1	alu0/1		86	
XCHG	r,m	4	8	>100						86	
XLAT		4	0	3						86	
PUSH	r	2	0	1		2				86	
PUSH	i	2	0	1		2				186	
PUSH	m	3	0			2				86	
PUSH	sr	4	4			7				86	
PUSHF(D)		4	4			10				86	
PUSHA(D)		4	10			19				186	
POP	r	2	0	1	0	1				86	
POP	m	4	8			14				86	
POP	sr	4	5			13				86	
POPF(D)		4	8			52				86	
POPA(D)		4	16			14				186	
LEA	r,[r+r/i]	1	0	0.5	0.5-1	0.25	0/1	alu0/1		86	
LEA	r,[r+r+i]	2	0	1	0.5-1	0.5	0/1	alu0/1		86	
LEA	r,[r*i]	3	0	4	0.5-1	1	1	int,alu		386	
LEA	r,[r+r*i]	2	0	4	0.5-1	1	1	int,alu		386	
LEA	r,[r+r*i+i]	3	0	4	0.5-1	1	1	int,alu		386	
LAHF		1	0	4	0	4	1	int		86	
SAHF		1	0	0.5	0.5-1	0.5	0/1	alu0/1		86	d
SALC		3	0	5	0	1	1	int		86	
LDS, LES, ...	r,m	4	7			15				86	
BSWAP	r	3	0	7	0	2		int,alu		486	
IN, OUT	r,r/i	8	64			>1000				86	
PREFETCHCNTA	m	4	2			6				sse	
PREFETCHT0/1/2	m	4	2			6				sse	
SFENCE		4	2			40				sse	
LFENCE		4	2			38				sse2	
MFENCE		4	2			100				sse2	

Arithmetic instructions											
ADD, SUB	r,r	1	0	0.5	0.5-1	0.25	0/1	alu0/1		86	c
ADD, SUB	r,m	2	0	1	0.5-1	1				86	c
ADD, SUB	m,r	3	0	≥ 8		≥ 4				86	c
ADC, SBB	r,r	4	4	6	0	6	1	int,alu		86	
ADC, SBB	r,i	3	0	6	0	6	1	int,alu		86	
ADC, SBB	r,m	4	6	8	0	8	1	int,alu		86	
ADC, SBB	m,r	4	7	≥ 9		8				86	
CMP	r,r	1	0	0.5	0.5-1	0.25	0/1	alu0/1		86	c
CMP	r,m	2	0	1	0.5-1	1				86	c
INC, DEC	r	2	0	0.5	0.5-1	0.5	0/1	alu0/1		86	
INC, DEC	m	4	0	4		≥ 4				86	
NEG	r	1	0	0.5	0.5-1	0.5	0	alu0		86	
NEG	m	3	0			≥ 3				86	
AAA, AAS		4	27	90						86	
DAA, DAS		4	57	100						86	
AAD		4	10	22			1	int	fpmul	86	
AAM		4	22	56			1	int	fpdiv	86	
MUL, IMUL	r8/32	4	6	16	0	8	1	int	fpmul	86	
MUL, IMUL	r16	4	7	17	0	8	1	int	fpmul	86	
MUL, IMUL	m8/32	4	7-8	16	0	8	1	int	fpmul	86	
MUL, IMUL	m16	4	10	16	0	8	1	int	fpmul	86	
IMUL	r32,r	4	0	14	0	4.5	1	int	fpmul	386	
IMUL	r32,(r),i	4	0	14	0	4.5	1	int	fpmul	386	
IMUL	r16,r	4	5	16	0	9	1	int	fpmul	386	
IMUL	r16,r,i	4	5	15	0	8	1	int	fpmul	186	
IMUL	r16,m16	4	7	15	0	10	1	int	fpmul	386	
IMUL	r32,m32	4	0	14	0	8	1	int	fpmul	386	
IMUL	r,m,i	4	7	14	0	10	1	int	fpmul	186	
DIV	r8/m8	4	20	61	0	24	1	int	fpdiv	86	a
DIV	r16/m16	4	18	53	0	23	1	int	fpdiv	86	a
DIV	r32/m32	4	21	50	0	23	1	int	fpdiv	386	
IDIV	r8/m8	4	24	61	0	24	1	int	fpdiv	86	a
IDIV	r16/m16	4	22	53	0	23	1	int	fpdiv	86	a
IDIV	r32/m32	4	20	50	0	23	1	int	fpdiv	386	a
CBW		2	0	1	0.5-1	1	0	alu0		86	
CWD, CDQ		2	0	1	0.5-1	0.5	0/1	alu0/1		86	
CWDE		1	0	0.5	0.5-1	0.5	0	alu0		386	
Logic											
AND, OR, XOR	r,r	1	0	0.5	0.5-1	0.5	0	alu0		86	c
AND, OR, XOR	r,m	2	0	≥ 1	0.5-1	≥ 1				86	c
AND, OR, XOR	m,r	3	0	≥ 8		≥ 4				86	c
TEST	r,r	1	0	0.5	0.5-1	0.5	0	alu0		86	c
TEST	r,m	2	0	≥ 1	0.5-1	≥ 1				86	c
NOT	r	1	0	0.5	0.5-1	0.5	0	alu0		86	
NOT	m	4	0			≥ 4				86	
SHL, SHR, SAR	r,i	1	0	4	1	1	1	int	mmxsh	186	
SHL, SHR, SAR	r,CL	2	0	6	0	1	1	int	mmxsh	86	d
ROL, ROR	r,i	1	0	4	1	1	1	int	mmxsh	186	d
ROL, ROR	r,CL	2	0	6	0	1	1	int	mmxsh	86	d
RCL, RCR	r,l	1	0	4	1	1	1	int	mmxsh	86	d
RCL, RCR	r,i	4	15	16	0	15	1	int	mmxsh	186	d
RCL, RCR	r,CL	4	15	16	0	14	1	int	mmxsh	86	d
SHL,SHR,SAR,ROL,ROR	m,i/CL	4	7-8	10	0	10	1	int	mmxsh	86	d
RCL, RCR	m,l	4	7	10	0	10	1	int	mmxsh	86	d
RCL, RCR	m,i/CL	4	18	18-28		14	1	int	mmxsh	86	d
SHLD, SHRD	r,r,i/CL	4	14	14	0	14	1	int	mmxsh	386	
SHLD, SHRD	m,r,i/CL	4	18	14	0	14	1	int	mmxsh	386	
BT	r,i	3	0	4	0	2	1	int	mmxsh	386	d
BT	r,r	2	0	4	0	1	1	int	mmxsh	386	d

BT	m,i	4	0	4	0	2	1	int	mmxsh	386	d
BT	m,r	4	12	12	0	12	1	int	mmxsh	386	d
BTR, BTS, BTC	r,i	3	0	6	0	2	1	int	mmxsh	386	
BTR, BTS, BTC	r,r	2	0	6	0	4	1	int	mmxsh	386	
BTR, BTS, BTC	m,i	4	7	18	0	8	1	int	mmxsh	386	
BTR, BTS, BTC	m,r	4	15	14	0	14	1	int	mmxsh	386	
BSF, BSR	r,r	2	0	4	0	2	1	int	mmxsh	386	
BSF, BSR	r,m	3	0	4	0	3	1	int	mmxsh	386	
SETcc	r	3	0	5	0	1	1	int		386	
SETcc	m	4	0	5	0	3	1	int		386	
CLC, STC		3	0	10	0	2				86	d
CMC		3	0	10	0	2				86	
CLD		4	7	52	0	52				86	
STD		4	5	48	0	48				86	
CLI		4	5	35		35				86	
STI		4	12	43		43				86	
Control transfer instructions											
JMP	short/near	1	0	0	0	1	0	alu0	branch	86	
JMP	far	4	28	118		118	0			86	
JMP	r	3	0	4		4	0	alu0	branch	86	
JMP	m(near)	3	0	4		4	0	alu0	branch	86	
JMP	m(far)	4	31	11		11	0			86	
Jcc	short/near	1	0	0		2-4	0	alu0	branch	86	
J(E)CXZ	short	4	4	0		2-4	0	alu0	branch	86	
LOOP	short	4	4	0		2-4	0	alu0	branch	86	
CALL	near	3	0	2		2	0	alu0	branch	86	
CALL	far	4	34				0			86	
CALL	r	4	4	8			0	alu0	branch	86	
CALL	m(near)	4	4	9			0	alu0	branch	86	
CALL	m(far)	4	38				0			86	
RETn		4	0	2			0	alu0	branch	86	
RETn	i	4	0	2			0	alu0	branch	86	
RETF		4	33	11			0			86	
RETF	i	4	33	11			0			86	
IRET		4	48	24			0			86	
ENTER	i,0	4	12	26		26				186	
ENTER	i,n	4	45+24n			128+16n				186	
LEAVE		4	0	3		3				186	
BOUND	m	4	14	14		14				186	
INTO		4	5	18		18				86	
INT	i	4	84	644						86	
String instructions											
LODS		4	3	6		6				86	
REP LODS		4	5n	≈ 4n+36						86	
STOS		4	2	6		6				86	
REP STOS		4	2n+3	≈ 3n+10						86	
MOVS		4	4	6		4				86	
REP MOVS		4	≈ 163+1.1n			≈ n				86	
SCAS		4	3			6				86	
REP SCAS		4	≈ 40+6n			≈ 4n				86	
CMPS		4	5			8				86	
REP CMPS		4	≈ 50+8n			≈ 4n				86	
Other											
NOP (90)		1	0	0		0.25	0/1	alu0/1		86	
NOP (0F 1F mod000rm)		1	0	0		0.25	0/1	alu0/1		ppro	
PAUSE		4	2							sse2	
CPUID		4	39-81			200-500				p5	
RDTSC		4	7			80				p5	

Notes:

- a) Add 1 μ op if source is a memory operand.
- b) Uses an extra μ op (port 3) if SIB byte used. A SIB byte is needed if the memory operand has more than one pointer register, or a scaled index, or [ESP](#) is used as base pointer.
- c) Add 1 μ op if source or destination, but not both, is a high 8-bit register ([AH](#), [BH](#), [CH](#), [DH](#)).
- d) Has (false) dependence on the flags in most cases.
- e) Not available on PMMX
- q) Latency is 12 in 16-bit real or virtual mode, 24 in 32-bit protected mode.

8.2 Floating point x87 instructions

Instruction	Operands	μ ops	Microcode	Latency	Additional latency	Reciprocal throughput	Port	Execution unit	Subunit	Backwards compatibility	Notes
Move instructions											
FLD	r	1	0	6	0	1	0	mov		87	
FLD	m32/64	1	0	≈ 7	0	1	2	load		87	
FLD	m80	3	4			6	2	load		87	
FBLD	m80	3	75			90	2	load		87	
FST(P)	r	1	0	6	0	1	0	mov		87	
FST(P)	m32/64	2	0	≈ 7		2-3	0	store		87	
FSTP	m80	3	8			8	0	store		87	
FBSTP	m80	3	311			400	0	store		87	
FXCH	r	1	0	0	0	1	0	mov		87	
FILD	m16	3	3	≈ 10		6	2	load		87	
FILD	m32/64	2	0	≈ 10		1	2	load		87	
FIST	m16	3	0	≈ 10		2-4	0	store		87	
FIST	m32/64	2	0	≈ 10		2-3	0	store		87	
FISTP	m	3	0	≈ 10		2-4	0	store		87	
FLDZ		1	0			2	0	mov		87	
FLD1		2	0			2	0	mov		87	
FCMOVcc	st0,r	4	0	2-4	1	4	1	fp		PPro	e
FFREE	r	3	0			4	0	mov		87	
FINCSTP, FDECSTP		1	0	0	0	1	0	mov		87	
FNSTSW	AX	4	0	11	0	3	1			287	
FSTSW	AX	6	0	11	0	3	1			287	
FNSTSW	m16	4	4			6	0			87	
FNSTCW	m16	4	4			6	0			87	
FLDCW	m16	4	7	(3)		(8)	0,2			87	f
Arithmetic instructions											
FADD(P),FSUB(R)(P)	r	1	0	5	1	1	1	fp	add	87	
FADD,FSUB(R)	m	2	0	5	1	1	1	fp	add	87	
FIADD,FISUB(R)	m16	3	4	6	0	6	1	fp	add	87	
FIADD,FISUB(R)	m32	3	0	5	1	2	1	fp	add	87	
FMUL(P)	r	1	0	7	1	2	1	fp	mul	87	
FMUL	m	2	0	7	1	2	1	fp	mul	87	
FIMUL	m16	3	4	7	1	6	1	fp	mul	87	
FIMUL	m32	3	0	7	1	2	1	fp	mul	87	
FDIV(R)(P)	r	1	0	43	0	43	1	fp	div	87	g, h
FDIV(R)	m	2	0	43	0	43	1	fp	div	87	g, h
FIDIV(R)	m16	3	4	43	0	43	1	fp	div	87	g, h
FIDIV(R)	m32	3	0	43	0	43	1	fp	div	87	g, h
FABS		1	0	2	1	1	1	fp	misc	87	
FCHS		1	0	2	1	1	1	fp	misc	87	
FCOM(P), FUCOM(P)	r	1	0	2	0	1	1	fp	misc	87	
FCOM(P)	m	2	0	2	0	1	1	fp	misc	87	
FCOMPP, FUCOMPP		2	0	2	0	1	1	fp	misc	87	
FCOMI(P)	r	3	0	10	0	3	0,1	fp	misc	PPro	
FICOM(P)	m16	4	4			6	1	fp	misc	87	

FICOM(P)	m32	3	0	2	0	2	1,2	fp	misc	87	
FTST		1	0	2	0	1	1	fp	misc	87	
FXAM		1	0	2	0	1	1	fp	misc	87	
FRNDINT		3	15	23	0	15	0,1			87	
FPREM		6	84	212			1	fp		87	
FPREM1		6	84	212			1	fp		387	
Math											
FSQRT		1	0	43	0	43	1	fp	div	87	g, h
FLDPI, etc.		2	0			3	1	fp		87	
FSIN		6	≈150	≈180		≈170	1	fp		387	
FCOS		6	≈175	≈207		≈207	1	fp		387	
FSINCOS		7	≈178	≈216		≈211	1	fp		387	
FPTAN		6	≈160	≈230		≈200	1	fp		87	
FPATAN		3	92	≈187		≈153	1	fp		87	
FSCALE		3	24	57		66	1	fp		87	
FXTRACT		3	15	20		20	1	fp		87	
F2XM1		3	45	≈165		63	1	fp		87	
FYL2X		3	60	≈200		90	1	fp		87	
FYL2XP1		11	134	≈242		≈220	1	fp		87	
Other											
FNOP		1	0	1	0	1	0		mov	87	
(F)WAIT		2	0	0	0	1	0		mov	87	
FNCLEX		4	4			96	1			87	
FNINIT		6	29			172				87	
FNSAVE		4	174	456		420	0,1			87	
FRSTOR		4	96	528		532				87	
FXSAVE		4	69	132		96				sse	i
FXRSTOR		4	94	208		208				sse	i

Notes:

e) Not available on PMMX

f) The latency for **FLDCW** is 3 when the new value loaded is the same as the value of the control word before the preceding **FLDCW**, i.e. when alternating between the same two values. In all other cases, the latency and reciprocal throughput is 143.

g) Latency and reciprocal throughput depend on the precision setting in the F.P. control word. Single precision: 23, double precision: 38, long double precision (default): 43.

h) Throughput of FP-MUL unit is reduced during the use of the FP-DIV unit.

i) Takes 6 μ ops more and 40-80 clocks more when XMM registers are disabled.

8.3 Integer MMX and XMM instructions

Instruction	Operands	μ ops	Microcode	Latency	Additional latency	Reciprocal throughput	Port	Execution unit	Subunit	Backwards compatibility	Notes
Move instructions											
MOVD	r32, mm	2	0	5	1	1	0	fp		mmx	
MOVD	mm, r32	2	0	2	0	2	1	mmx	alu	mmx	
MOVD	mm,m32	1	0	≈ 8	0	1	2	load		mmx	
MOVD	r32, xmm	2	0	10	1	2	0	fp		sse2	

MOVD	xmm, r32	2	0	6	1	2	1	mmx	shift	sse2	
MOVD	xmm,m32	1	0	≈ 8	0	1	2	load		sse2	
MOVD	m32, r	2	0	≈ 8		2	0,1			mmx	
MOVQ	mm,mm	1	0	6	0	1	0	mov		mmx	
MOVQ	xmm,xmm	1	0	2	1	2	1	mmx	shift	sse2	
MOVQ	r,m64	1	0	≈ 8		1	2	load		mmx	
MOVQ	m64,r	2	0	≈ 8		2	0	mov		mmx	
MOVDQA	xmm,xmm	1	0	6	0	1	0	mov		sse2	
MOVDQA	xmm,m	1	0	≈ 8		1	2	load		sse2	
MOVDQA	m,xmm	2	0	≈ 8		2	0	mov		sse2	
MOVDQU	xmm,m	4	0			2	2	load		sse2	k
MOVDQU	m,xmm	4	6			2	0	mov		sse2	k
MOVDQ2Q	mm,xmm	3	0	8	1	2	0,1	mov-mmx		sse2	
MOVQ2DQ	xmm,mm	2	0	8	1	2	0,1	mov-mmx		sse2	
MOVNTQ	m,mm	3	0			75	0	mov		sse	
MOVNTDQ	m,xmm	2	0			18	0	mov		sse2	
PACKSSWB/DW PACKUSWB	mm,r/m	1	0	2	1	1	1	mmx	shift	mmx	a
PACKSSWB/DW PACKUSWB	xmm,r/m	1	0	4	1	2	1	mmx	shift	mmx	a
PUNPCKH/LBW/WD/DQ	mm,r/m	1	0	2	1	1	1	mmx	shift	mmx	a
PUNPCKHBW/WD/DQ/QDQ	xmm,r/m	1	0	4	1	2	1	mmx	shift	sse2	a
PUNPCKLBW/WD/DQ/QDQ	xmm,r/m	1	0	2	1	2	1	mmx	shift	sse2	a
PSHUFD	xmm,xmm,i	1	0	4	1	2	1	mmx	shift	sse2	
PSHUFL/HW	xmm,xmm,i	1	0	2	1	2	1	mmx	shift	sse2	
PSHUFW	mm,mm,i	1	0	2	1	1	1	mmx	shift	mmx	
MASKMOVQ	mm,mm	4	4			7	0	mov		sse	
MASKMOVDQU	xmm,xmm	4	6			10	0	mov		sse2	
PMOVMskb	r32,r	2	0	7	1	3	0,1	mmx-alu0		sse	
PEXTRW	r32,mm,i	3	0	8	1	2	1	mmx-int		sse	
PEXTRW	r32,xmm,i	3	0	9	1	2	1	mmx-int		sse2	
PINSRW	mm,r32,i	2	0	3	1	2	1	int-mmx		sse	
PINSRW	xmm,r32,i	2	0	4	1	2	1	int-mmx		sse2	
Arithmetic instructions											
PADDB/W/D PADD(U)SB/W	r,r/m	1	0	2	1	1,2	1	mmx	alu	mmx	a,j
PSUBB/W/D PSUB(U)SB/W	r,r/m	1	0	2	1	1,2	1	mmx	alu	mmx	a,j
PADDQ, PSUBQ	mm,r/m	1	0	2	1	1	1	mmx	alu	sse2	a
PADDQ, PSUBQ	xmm,r/m	1	0	4	1	2	1	fp	add	sse2	a
PCMPEQB/W/D PCMPGTB/W/D	r,r/m	1	0	2	1	1,2	1	mmx	alu	mmx	a,j
PMULLW PMULHW	r,r/m	1	0	6	1	1,2	1	fp	mul	mmx	a,j
PMULHUW	r,r/m	1	0	6	1	1,2	1	fp	mul	sse	a,j
PMADDWD	r,r/m	1	0	6	1	1,2	1	fp	mul	mmx	a,j
PMULUDQ	r,r/m	1	0	6	1	1,2	1	fp	mul	sse2	a,j
PAVGB/W	r,r/m	1	0	2	1	1,2	1	mmx	alu	sse	a,j
PMIN/MAXUB	r,r/m	1	0	2	1	1,2	1	mmx	alu	sse	a,j
PMIN/MAXSW	r,r/m	1	0	2	1	1,2	1	mmx	alu	sse	a,j
PSADBW	r,r/m	1	0	4	1	1,2	1	mmx	alu	sse	a,j
Logic											
PAND, PANDN	r,r/m	1	0	2	1	1,2	1	mmx	alu	mmx	a,j
POR, PXOR	r,r/m	1	0	2	1	1,2	1	mmx	alu	mmx	a,j
PSLL/RLW/D/Q, PSRAW/D	r,i/t/m	1	0	2	1	1,2	1	mmx	shift	mmx	a,j
PSLLDQ, PSRLDQ	xmm,i	1	0	4	1	2	1	mmx	shift	sse2	a
Other											
EMMS		4	11	12		12	0			mmx	

Notes:

- a) Add 1 μop if source is a memory operand.
- j) Reciprocal throughput is 1 for 64 bit operands, and 2 for 128 bit operands.
- k) It may be advantageous to replace this instruction by two 64-bit moves

8.4 Floating point XMM instructions

Instruction	Operands	μ ops	Microcode	Latency	Additional latency	Reciprocal throughput	Port	Execution unit	Subunit	Backwards compatibility	Notes
Move instructions											
MOVAPS/D	r,r	1	0	6	0	1	0	mov		sse	
MOVAPS/D	r,m	1	0	≈ 7	0	1	2			sse	
MOVAPS/D	m,r	2	0	≈ 7		2	0			sse	
MOVUPS/D	r,r	1	0	6	0	1	0	mov		sse	
MOVUPS/D	r,m	4	0			2	2			sse	k
MOVUPS/D	m,r	4	6			8	0			sse	k
MOVSS	r,r	1	0	2	0	2	1	mmx	shift	sse	
MOVSD	r,r	1	0	2	1	2	1	mmx	shift	sse	
MOVSS, MOVSD	r,m	1	0	≈ 7	0	1	2			sse	
MOVSS, MOVSD	m,r	2	0			2	0			sse	
MOVHLPs	r,r	1	0	4	0	2	1	mmx	shift	sse	
MOVLHPS	r,r	1	0	2	0	2	1	mmx	shift	sse	
MOVHPS/D, MOVLPS/D	r,m	3	0			4	2			sse	
MOVHPS/D, MOVLPS/D	m,r	2	0			2	0			sse	
MOVNTPS/D	m,r	2	0			4	0			sse/2	
MOVMSKPS/D	r32,r	2	0	6	1	3	1	fp		sse	
SHUFPS/D	r,r/m,i	1	0	4	1	2	1	mmx	shift	sse	
UNPCKHPS/D	r,r/m	1	0	4	1	2	1	mmx	shift	sse	
UNPCKLPS/D	r,r/m	1	0	2	1	2	1	mmx	shift	sse	
Conversion											
CVTTPS2PD	r,r/m	4	0	7	1	4	1	mmx	shift	sse2	a
CVTPD2PS	r,r/m	2	0	10	1	2	1	fp-mmx		sse2	a
CVTSD2SS	r,r/m	4	0	14	1	6	1	mmx	shift	sse2	a
CVTSS2SD	r,r/m	4	0	10	1	6	1	mmx	shift	sse2	a
CVTDQ2PS	r,r/m	1	0	4	1	2	1	fp		sse2	a
CVTDQ2PD	r,r/m	3	0	9	1	4	1	mmx-fp		sse2	a
CVT(T)PS2DQ	r,r/m	1	0	4	1	2	1	fp		sse2	a
CVT(T)PD2DQ	r,r/m	2	0	9	1	2	1	fp-mmx		sse2	a
CVTPI2PS	xmm,mm	4	0	10	1	4	1	mmx		sse	a
CVTPI2PD	xmm,mm	4	0	11	1	5	1	fp-mmx		sse2	a
CVT(T)PS2PI	mm,xmm	3	0	7	0	2	0,1	fp-mmx		sse	a
CVT(T)PD2PI	mm,xmm	3	0	11	1	3	0,1	fp-mmx		sse2	a
CVTSI2SS	xmm,r32	3	0	10	1	3	1	fp-mmx		sse	a
CVTSI2SD	xmm,r32	4	0	15	1	6	1	fp-mmx		sse2	a
CVT(T)SD2SI	r32,xmm	2	0	8	1	2.5	1	fp		sse2	a
CVT(T)SS2SI	r32,xmm	2	0	8	1	2.5	1	fp		sse	a
Arithmetic											
ADDPS/D ADDSS/D	r,r/m	1	0	4	1	2	1	fp	add	sse	a
SUBPS/D SUBSS/D	r,r/m	1	0	4	1	2	1	fp	add	sse	a
MULPS/D MULSS/D	r,r/m	1	0	6	1	2	1	fp	mul	sse	a
DIVSS	r,r/m	1	0	23	0	23	1	fp	div	sse	a,h
DIVPS	r,r/m	1	0	39	0	39	1	fp	div	sse	a,h
DIVSD	r,r/m	1	0	38	0	38	1	fp	div	sse2	a,h

DIVPD	r,r/m	1	0	69	0	69	1	fp	div	sse2	a,h
RCPPS RCPSS	r,r/m	2	0	4	1	4	1	mmx		sse	a
MAXPS/D MAXSS/D MINPS/D MINSS/D	r,r/m	1	0	4	1	2	1	fp	add	sse	a
CMPccPS/D CMPccSS/D	r,r/m	1	0	4	1	2	1	fp	add	sse	a
COMISS/D UCOMISS/D	r,r/m	2	0	6	1	3	1	fp	add	sse	a
Logic											
ANDPS/D ANDNPS/D ORPS/D XORPS/D	r,r/m	1	0	2	1	2	1	mmx	alu	sse	a
Math											
SQRTSS	r,r/m	1	0	23	0	23	1	fp	div	sse	a,h
SQRTPS	r,r/m	1	0	39	0	39	1	fp	div	sse	a,h
SQRTSD	r,r/m	1	0	38	0	38	1	fp	div	sse2	a,h
SQRTPD	r,r/m	1	0	69	0	69	1	fp	div	sse2	a,h
RSQRTSS	r,r/m	2	0	4	1	3	1	mmx		sse	a
RSQRTPS	r,r/m	2	0	4	1	4	1	mmx		sse	a
Other											
LDMXCSR	m	4	8	98		100	1			sse	
STMXCSR	m	4	4			6	1			sse	

Notes:

- a) Add 1 μ op if source is a memory operand.
- h) Throughput of FP-MUL unit is reduced during the use of the FP-DIV unit.
- k) It may be advantageous to replace this instruction by two 64-bit moves.

9 List of instruction timings and μ op breakdown for P4E

Explanation of column headings:

Instruction: Instruction name. cc means any condition code. For example, Jcc can be JB, JNE, etc.

Operands: i = immediate constant, r = any register, r32 = 32-bit register, etc., mm = 64 bit mmx register, xmm = 128 bit xmm register, sr = segment register, m = any memory operand including indirect operands, m64 means 64-bit memory operand, etc., mabs = memory operand with 64-bit absolute address.

μ ops: Number of μ ops issued from instruction decoder and stored in trace cache.

Microcode: Number of additional μ ops issued from microcode ROM.

Latency: The number of clock cycles from the execution of an instruction begins to the next dependent instruction can begin, if the latter instruction starts in the same execution unit. The numbers are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably. Floating point operands are presumed to be normal numbers. Denormal numbers, NAN's, infinity and exceptions increase the delays. The latency of moves to and from memory cannot be measured accurately because of the problem with memory intermediates explained in manual 3: "The microarchitecture of Intel, AMD and VIA CPUs". Avoid making optimizations that rely on the latency of memory operations.

Additional latency: This number is added to the latency if the next dependent instruction is in a different execution unit. There is no additional latency between ALU0 and ALU1.

Reciprocal throughput: This is also called issue latency. This value indicates the number of clock cycles from the execution of an instruction begins to a subsequent independent instruction can begin to execute in the same execution subunit. A value of 0.25 indicates 4 instructions per clock cycle in one thread.

Port: The port through which each μ op goes to an execution unit. Two independent μ ops can start to execute simultaneously only if they are going through different ports.

Execution unit: Use this information to determine additional latency. When an instruction with more than one μ op uses more than one execution unit, only the first and the last execution unit is listed.

Execution subunit: Throughput measures apply only to instructions executing in the same subunit.

Backwards compatibility: Indicates the first microprocessor in the Intel 80x86 family that supported the instruction.

9.1 Integer instructions

Notes	Backwards compatibility	Subunit	Execution unit	Port	Reciprocal throughput	Additional latency	Latency	Microcode	μops	Operands	Instruction
Move instructions											
	86		alu0/1	0/1	0.25	0	1	0	1	r,r	MOV
c	86		alu0/1	0/1	0.25	0	1	0	1	r8/16/32,i	MOV
	x64		alu0/1	0/1	0.5	0		0	1	r64,i32	MOV
	x64		alu1	1	1	0		0	2	r64,i64	MOV
	86		load	2	1	0	3	0	2	r8/16,m	MOV
	86		load	2	1	0	2	0	1	r32/64,m	MOV
b,c	86		store	0	2				1	m,r	MOV
	86		store	0,3	2				2	m,i	MOV
	x64		store	0,3	2				2	m64,i32	MOV
	86				8				1	r,sr	MOV
a,q	86				27				1	sr,r/m	MOV
ℓ	x64				1				3	r,mabs	MOV
ℓ	x64				2				3	mabs,r	MOV
	sse2				2				2	m,r32	MOVNTI
c	386		alu0/1	0/1	0.25	0	1	0	1	r,r	MOVZX
c	386		alu0/1	0/1	1	0	2	0	2	r16,r8	MOVZX
	386		load	2	1	0	2	0	1	r,m	MOVZX
a,c,o	386		alu0	0	0.5	0	1	0	1	r16,r8	MOVSX
a,c,o	386		alu0	0	0.5	0	1	0	1	r32/64,r8/16	MOVSX
	386		load	2	1	0	3	0	2	r,m	MOVSX
a	x64		alu0	0	0.5	0	1	0	1	r64,r32	MOVSXD
a,e	PPro				3	0	9.5	0	3	r,r/m	CMOVcc
	86		alu0/1	0/1	1	0	2	0	3	r,r	XCHG
	86						≈ 100		2	r,m	XCHG
	86						6	0	4		XLAT
	86				2		2	0	2	r	PUSH
	186				2		2	0	2	i	PUSH
	86				2		2	0	3	m	PUSH
	86				9			3	1	sr	PUSH
	86				9			3	1		PUSHF(D/Q)
m	186				16			9	1		PUSHA(D)
	86				1	0	1	0	2	r	POP
	86				10			6	2	m	POP
	86				30			8	1	sr	POP
	86				70			8	1		POPF(D/Q)
m	186				15			16	2		POPA(D)
p	86		alu0/1	0/1	0.25			0	1	r,[m]	LEA
	86		alu0/1	0/1	0.25	0	2.5	0	1	r,[r+r/i]	LEA
	86		alu0/1	0/1	0.5	0	3.5	0	2	r,[r+r+i]	LEA
	386		alu	1	1	0	3.5	0	3	r,[r*i]	LEA
	386		alu0,1	0,1	1	0	3.5	0	2	r,[r+r*i]	LEA
	386		alu	1	1	0	3.5	0	3	r,[r+r*i+i]	LEA
n	86		int	1		0	4	0	1		LAHF
d,n	86		alu0/1	0/1		0	5	0	1		SAHF
m	86		int	1	1	0		0	2		SALC
m	86				28				2	r,m	LDS, LES, ...

LODS		1	3	8		8				86	
REP LODS		1	5n	$\approx 4n+50$						86	
STOS		1	2	8		8				86	
REP STOS		1	2.5n	$\approx 3n$						86	
MOVS		1	4	8		8				86	
REP MOVSB		9	$\approx 0.3 n$			$\approx 0.3n$				86	
REP MOVSW		1	$\approx 0.5-1.1 n$			$\approx 0.6-1.4 n$				86	
REP MOVSD		1	$\approx 1.1 n$			$\approx 1.4 n$				86	
REP MOVSQ		1	$\approx 1.1 n$			$\approx 1.4 n$				x64	
BSWAP	r	1	0	1	0	1		alu		486	
IN, OUT	r,r/i	1	52			>1000				86	
PREFETCHCNTA	m	1	0			1				sse	
PREFETCHT0/1/2	m	1	0			1				sse	
SFENCE		1	2			50				sse	
LFENCE		1	2			50				sse2	
MFENCE		1	4			124				sse2	

Arithmetic instructions

ADD, SUB	r,r	1	0	1	0	0.25	0/1	alu0/1		86	c
ADD, SUB	r,m	2	0	1	0	1				86	c
ADD, SUB	m,r	3	0	5		2				86	c
ADC, SBB	r,r/i	3	0	10	0	10	1	int,alu		86	
ADC, SBB	r,m	2	5	10	0	10	1	int,alu		86	
ADC, SBB	m,r	2	6	20		10				86	
ADC, SBB	m,i	3	5	22		10				86	
CMP	r,r	1	0	1	0	0.25	0/1	alu0/1		86	c
CMP	r,m	2	0	1	0	1				86	c
INC, DEC	r	2	0	1	0	0.5	0/1	alu0/1		86	
INC, DEC	m	4	0	5		3				86	
NEG	r	1	0	1	0	0.5	0	alu0		86	
NEG	m	3	0	5		3				86	
AAA, AAS		1	10	26						86	m
DAA, DAS		1	16	29						86	m
AAD		2	5	13			1	int	mul	86	m
AAM		2	17	71			1	int	fpdiv	86	m
MUL, IMUL	r8	1	0	10	0		1	int	mul	86	
MUL, IMUL	r16	4	0	11	0		1	int	mul	86	
MUL, IMUL	r32	3	0	11	0		1	int	mul	86	
MUL, IMUL	r64	1	5	11	0		1	int	mul	x64	
MUL, IMUL	m8	2	0	10	0		1	int	mul	86	
MUL, IMUL	m16	2	5	11	0		1	int	mul	86	
MUL, IMUL	m32	3	0	11	0		1	int	mul	86	
MUL, IMUL	m64	2	6	11	0		1	int	mul	x64	
IMUL	r16,r16	1	0	10	0	2.5	1	int	mul	386	
IMUL	r16,r16,i	2	0	11	0	2.5	1	int	mul	186	
IMUL	r32,r32	1	0	10	0	2.5	1	int	mul	386	
IMUL	r32,(r32),i	1	0	10	0	2.5	1	int	mul	386	
IMUL	r64,r64	1	0	10	0	2.5	1	int	mul	x64	
IMUL	r64,(r64),i	1	0	10	0	2.5	1	int	mul	x64	
IMUL	r16,m16	2	0	10	0	2.5	1	int	mul	386	
IMUL	r32,m32	2	0	10	0	2.5	1	int	mul	386	
IMUL	r64,m64	2	0	10	0	2.5	1	int	mul	x64	
IMUL	r,m,i	3	0	10	0	1-2.5	1	int	mul	186	
DIV	r8/m8	1	20	74	0	34	1	int	fpdiv	86	a
DIV	r16/m16	1	19	73	0	34	1	int	fpdiv	86	a
DIV	r32/m32	1	21	76	0	34	1	int	fpdiv	386	a
DIV	r64/m64	1	31	63	0	52	1	int	fpdiv	x64	a
IDIV	r8/m8	1	21	76	0	34	1	int	fpdiv	86	a
IDIV	r16/m16	1	19	79	0	34	1	int	fpdiv	86	a
IDIV	r32/m32	1	19	79	0	34	1	int	fpdiv	386	a
IDIV	r64/m64	1	58	96	0	91	1	int	fpdiv	x64	a

CBW		2	0	2	0	1	0	alu0		86	
CWD		2	0	2	0	1	0/1	alu0/1		86	
CDQ		1	0	1	0	1	0/1	alu0/1		386	
CQO		1	0	7	0	1	0/1	alu0/1		x64	
CWDE		2	0	2	0	1	0/1	alu0/1		386	
CDQE		1	0	1	0	1	0/1	alu0/1		x64	
SCAS		1	3		0	8				86	
REP SCAS		1	≈ 54+6n			≈ 4n				86	
CMPS		1	5			10				86	
REP CMPS		1	≈ 81+8n			≈ 5n				86	
Logic											
AND, OR, XOR	r,r	1	0	1	0	0.5	0	alu0		86	c
AND, OR, XOR	r,m	2	0	1	0	1				86	c
AND, OR, XOR	m,r	3	0	5		2				86	c
TEST	r,r	1	0	1	0	0.5	0	alu0		86	c
TEST	r,m	2	0	1	0	1				86	c
NOT	r	1	0	1	0	0.5	0	alu0		86	
NOT	m	3	0	5		2				86	
SHL	r,i	1	0	1	0	0.5	1	alu1		186	
SHR, SAR	r8/16/32,i	1	0	1	0	0.5	1	alu1		186	
SHR, SAR	r64,i	1	0	7	0	2	1	alu1		x64	
SHL	r,CL	2	0	2	0	2	1	alu1		86	
SHR, SAR	r8/16/32,CL	2	0	2	0	2	1	alu1		86	
SHR, SAR	r64,CL	2	0	8	0		1	alu1		x64	
ROL, ROR	r8/16/32,i	1	0	1	0	1	1	alu1		186	d
ROL, ROR	r64,i	1	0	7	0	7	1	alu1		x64	d
ROL, ROR	r8/16/32,CL	2	0	2	0	2	1	alu1		86	d
ROL, ROR	r64,CL	2	0	8	0	8	1	alu1		x64	d
RCL, RCR	r,l	1	0	7	0	7	1	alu1		86	d
RCL	r,i	2	11	31	0	31	1	alu1		186	d
RCR	r,i	2	11	25	0	25	1	alu1		186	d
RCL	r,CL	1	11	31	0	31	1	alu1		86	d
RCR	r,CL	1	11	25	0	25	1	alu1		86	d
SHL, SHR, SAR	m8/16/32,i	3	6	10	0		1	alu1		86	
ROL, ROR	m8/16/32,i	3	6	10	0		1	alu1		86	d
SHL, SHR, SAR	m8/16/32,cl	2	6	10	0		1	alu1		86	
ROL, ROR	m8/16/32,cl	2	6	10	0		1	alu1		86	d
RCL, RCR	m8/16/32,l	2	5	27	0	27	1	alu1		86	d
RCL, RCR	m8/16/32,i	3	13	38	0	38	1	alu1		86	d
RCL, RCR	m8/16/32,cl	2	13	37	0	37	1	alu1		86	d
SHLD, SHRD	r8/16/32,r,i	3	0	8	0	7	1	alu1		386	
SHLD	r64,r64,i	4	5	10	0		1	alu1		x64	
SHRD	r64,r64,i	3	7	10	0		1	alu1		x64	
SHLD, SHRD	r8/16/32,r,cl	4	0	9	0	8	1	alu1		386	
SHLD	r64,r64,cl	4	5	14	0		1	alu1		x64	
SHRD	r64,r64,cl	3	8	12	0		1	alu1		x64	
SHLD, SHRD	m,r,i	3	8	20	0	10	1	alu1		386	
SHLD, SHRD	m,r,CL	2	8	20	0	10	1	alu1		386	
BT	r,i	1	0	8	0	8	1	alu1		386	d
BT	r,r	2	0	9	0	9	1	alu1		386	d
BT	m,i	3	0	8	0	8	1	alu1		386	d
BT	m,r	2	7	10	0	10	1	alu1		386	d
BTR, BTS, BTC	r,i	1	0	8	0	8	1	alu1		386	
BTR, BTS, BTC	r,r	2	0	9	0	9	1	alu1		386	
BTR, BTS, BTC	m,i	3	6	28	0	10	1	alu1		386	
BTR, BTS, BTC	m,r	2	10	14	0	14	1	alu1		386	
BSF, BSR	r,r/m	2	0	16	0	4	1	alu1		386	
SETcc	r	2	0	9	0	1	1	int		386	
SETcc	m	3	0	9	0	2	1	int		386	
CLC, STC		2	0		0	8				86	d

CMC		3	0	15	0					86	
CLD, STD		1	8		0	53				86	
Control transfer instructions											
JMP	short/near	1	0	0	0	1	0	alu0	branch	86	
JMP	far	2	25			154	0			86	m
JMP	r	3	0			15	0	alu0	branch	86	
JMP	m(near)	3	0			10	0	alu0	branch	86	
JMP	m(far)	2	28			157	0			86	
Jcc	short/near	1	0			2-4	0	alu0	branch	86	
J(E)CXZ	short	4	0			4	0	alu0	branch	86	
LOOP	short	4	0			4	0	alu0	branch	86	
CALL	near	3	0			7	0	alu0	branch	86	
CALL	far	3	29			160	0			86	m
CALL	r	4	0			7	0	alu0	branch	86	
CALL	m(near)	4	0			9	0	alu0	branch	86	
CALL	m(far)	2	32			160	0			86	
RETN		4	0			7	0	alu0	branch	86	
RETN	i	4	0			7	0	alu0	branch	86	
RETF		1	30			160	0			86	
RETF	i	2	30			160	0			86	
IRET		1	49			325	0			86	
BOUND	m	2	11			12				186	m
INT	i	2	67			470				86	
INTO		1	4			26				86	m
Other											
NOP (90)		1	0	0		0.25	0/1	alu0/1		86	
NOP (0F 1F mod000rm)		1	0	0		0.25	0/1	alu0/1		ppro	
PAUSE		1	2			50				sse2	
LEAVE		4	0	5		5				186	
CLI		1	5			52				86	
STI		1	11			64				86	
CPUID		1	49-90			300-500				p5	
RDTSC		1	12			100				p5	
RDPMC (bit 31 = 1)		1	37			100				p5	
RDPMC (bit 31 = 0)		4	154			240				p5	
MONITOR										(sse3)	
MWAIT										(sse3)	

Notes:

- Add 1 μ op if source is a memory operand.
- Uses an extra μ op (port 3) if SIB byte used.
- Add 1 μ op if source or destination, but not both, is a high 8-bit register (AH, BH, CH, DH).
- Has (false) dependence on the flags in most cases.
- Not available on PMMX
- Move accumulator to/from memory with 64 bit absolute address (opcode A0 - A3).
- Not available in 64 bit mode.
- Not available in 64 bit mode on some processors.
- MOV_{SX} uses an extra μ op if the destination register is smaller than the biggest register size available. Use a 32 bit destination register in 16 bit and 32 bit mode, and a 64 bit destination register in 64 bit mode for optimal performance.
- LEA with a direct memory operand has 1 μ op and a reciprocal throughput of 0.25. This also applies if there is a RIP-relative address in 64-bit mode. A sign-extended 32-bit direct memory operand in 64-bit mode without RIP-relative address takes 2 μ ops because of the SIB byte. The throughput is 1 in this case. You may use a MOV instead.
- These values are measured in 32-bit mode. In 16-bit real mode there is 1 microcode μ op and a reciprocal throughput of 17.

9.2 Floating point x87 instructions

Instruction	Operands	µops	Microcode	Latency	Additional latency	Reciprocal throughput	Port	Execution unit	Subunit	Backwards compatibility	Notes
Move instructions											
FLD	r	1	0	7	0	1	0	mov		87	
FLD	m32/64	1	0		0	1	2	load		87	
FLD	m80	3	3			8	2	load		87	
FBLD	m80	3	74			90	2	load		87	
FST(P)	r	1	0	7	0	1	0	mov		87	
FST(P)	m32/64	2	0	7		2	0	store		87	
FSTP	m80	3	6			10	0	store		87	
FBSTP	m80	3	311			400	0	store		87	
FXCH	r	1	0	0	0	1	0	mov		87	
FILD	m16	3	2			8	2	load		87	
FILD	m32/64	2	0			2	2	load		87	
FIST(P)	m	3	0			2.5	0	store		87	
FISTTP	m	3	0			2.5	0	store		sse3	
FLDZ		1	0			2	0	mov		87	
FLDI		2	0			2	0	mov		87	
FCMOVcc	st0,r	4	0	5	1	4	1	fp		PPro	e
FFREE	r	3	0			3	0	mov		87	
FINCSTP, FDECSTP		1	0	0	0	1	0	mov		87	
FNSTSW	AX	4	0		0	3	1			287	
FSTSW	AX	6	0		0	3	1			287	
FNSTSW	m16	2	3			8	0			87	
FNSTCW	m16	4	0			3	0			87	
FLDCW	m16	3	6			10	0,2			87	f
Arithmetic instructions											
FADD(P),FSUB(R)(P)	r	1	0	6	1	1	1	fp	add	87	
FADD,FSUB(R)	m	2	0	6	1	1	1	fp	add	87	
FIADD,FISUB(R)	m16	3	3	7	1	6	1	fp	add	87	
FIADD,FISUB(R)	m32	3	0	6	1	2	1	fp	add	87	
FMUL(P)	r	1	0	8	1	2	1	fp	mul	87	
FMUL	m	2	0	8	1	2	1	fp	mul	87	
FIMUL	m16	3	3	8	1	8	1	fp	mul	87	
FIMUL	m32	3	0	8	1	3	1	fp	mul	87	
FDIV(R)(P)	r	1	0	45	1	45	1	fp	div	87	g,h
FDIV(R)	m	2	0	45	1	45	1	fp	div	87	g,h
FIDIV(R)	m16	3	3	45	1	45	1	fp	div	87	g,h
FIDIV(R)	m32	3	3	45	1	45	1	fp	div	87	g,h
FABS		1	0	3	1	1	1	fp	misc	87	
FCHS		1	0	3	1	1	1	fp	misc	87	
FCOM(P), FUCOM(P)	r	1	0	3	0	1	1	fp	misc	87	
FCOM(P)	m	2	0	3	0	1	1	fp	misc	87	
FCOMPP, FUCOMPP		2	0	3	0	1	1	fp	misc	87	
FCOMI(P)	r	3	0			3	0,1	fp	misc	PPro	
FICOM(P)	m16	3	3			8	1	fp	misc	87	
FICOM(P)	m32	3	0			2	1,2	fp	misc	87	
FTST		1	0			1	1	fp	misc	87	

FXAM		1	0			1	1	fp	misc	87	
FRNDINT		3	14	28	1	16	0,1			87	
FPREM		8	86	220	1		1	fp		87	
FPREM1		9	92	220	1		1	fp		387	
Math											
FSQRT		1	0	45	1	45	1	fp	div	87	g,h
FLDPI, etc.		2	0			2	1	fp		87	
FSIN, FCOS		3	≈100	≈200		≈200	1	fp		387	
FSINCOS		5	≈150	≈200		≈200	1	fp		387	
FPTAN		8	≈170	≈270		≈270	1	fp		87	
FPATAN		4	97	≈250		≈250	1	fp		87	
FSCALE		3	25	96			1	fp		87	
FXTRACT		4	16	27			1	fp		87	
F2XM1		3	190	≈270			1	fp		87	
FYL2X		3	63	≈170			1	fp		87	
FYL2XP1		3	58	≈170			1	fp		87	
Other											
FNOP		1	0	1	0	1	0		mov	87	
(F)WAIT		2	0	0	0	1	0		mov	87	
FNCLEX		1	4			120	1			87	
FNINIT		1	30			200				87	
FNSAVE		2	181	500			0,1			87	
FRSTOR		2	96	570						87	
FXSAVE		2	121			160				sse	i
FXRSTOR		2	118			244				sse	i

Notes:

- e) Not available on PMMX
- f) The latency for **FLDCW** is 3 when the new value loaded is the same as the value of the control word before the preceding **FLDCW**, i.e. when alternating between the same two values. In all other cases, the latency and reciprocal throughput is > 100.
- g) Latency and reciprocal throughput depend on the precision setting in the F.P. control word. Single precision: 32, double precision: 40, long double precision (default): 45.
- h) Throughput of FP-MUL unit is reduced during the use of the FP-DIV unit.
- i) Takes fewer microcode μops when XMM registers are disabled, but the throughput is the same.

9.3 Integer MMX and XMM instructions

Instruction	Operands	μops	Microcode	Latency	Additional latency	Reciprocal throughput	Port	Execution unit	Subunit	Backwards compatibility	Notes
Move instructions											
MOVD	r32, mm	2	0	6	1	1	0	fp		mmx	
MOVD	mm, r32	1	0	3	1	1	1	mmx	alu	mmx	
MOVD	mm, m32	1	0			1	2	load		mmx	
MOVD	r32, xmm	1	0	7	1	1	0	fp		sse2	
MOVD	xmm, r32	2	0	4	1	2	1	mmx	shift	sse2	
MOVD	xmm, m32	1	0			1	2	load		sse2	
MOVD	m32, r	2	0			2	0,1			mmx	
MOVQ	mm, mm	1	0	7	0	1	0	mov		mmx	
MOVQ	xmm, xmm	1	0	2	1	2	1	mmx	shift	sse2	
MOVQ	r, m64	1	0			1	2	load		mmx	
MOVQ	m64, r	2	0			2	0	mov		mmx	
MOVDQA	xmm, xmm	1	0	7	0	1	0	mov		sse2	
MOVDQA	xmm, m	1	0			1	2	load		sse2	
MOVDQA	m, xmm	2	0			2	0	mov		sse2	
MOVDQU	xmm, m	4	0			23	2	load		sse2	k
MOVDQU	m, xmm	4	2			8	0	mov		sse2	k
LDDQU	xmm, m	4	0			2.5	2	load		sse3	
MOVDQ2Q	mm, xmm	3	0	10	1	2	0,1	mov-mmx		sse2	
MOVQ2DQ	xmm, mm	2	0	10	1	2	0,1	mov-mmx		sse2	
MOVNTQ	m, mm	3	0			4	0	mov		sse	
MOVNTDQ	m, xmm	2	0			4	0	mov		sse2	
MOVDDUP	xmm, xmm	1	0	2	1	2	1	mmx	shift	sse3	
MOVSHDUP MOVSLDUP	xmm, xmm	1	0	4	1	2	1	mmx	shift	sse3	
PACKSSWB/DW PACKUSWB	mm, r/m	1	0	2	1	2	1	mmx	shift	mmx	a
PACKSSWB/DW PACKUSWB	xmm, r/m	1	0	4	1	4	1	mmx	shift	mmx	a
PUNPCKH/LBW/WD/DQ	mm, r/m	1	0	2	1	2	1	mmx	shift	mmx	a
PUNPCKHBW/WD/DQ/QDQ	xmm, r/m	1	0	4	1	4	1	mmx	shift	sse2	a
PUNPCKLBW/WD/DQ/QDQ	xmm, r/m	1	0	2	1	2	1	mmx	shift	sse2	a
PSHUFD	xmm, xmm, i	1	0	4	1	2	1	mmx	shift	sse2	
PSHUFL/HW	xmm, xmm, i	1	0	2	1	2	1	mmx	shift	sse	
PSHUFW	mm, mm, i	1	0	2	1	1	1	mmx	shift	sse	
MASKMOVQ	mm, mm	1	4			10	0	mov		sse	
MASKMOVDQU	xmm, xmm	1	6			12	0	mov		sse2	
PMOVMskb	r32, r	2	0	7		3	0,1	mmx-alu0		sse	
PEXTRW	r32, mm, i	2	0	7		2	1	mmx-int		sse	
PEXTRW	r32, xmm, i	2	0	7		3	1	mmx-int		sse2	
PINSRW	r, r32, i	2	0	4		2	1	int-mmx		sse	
Arithmetic instructions											
PADDB/W/D PADD(U)SB/W	r, r/m	1	0	2	1	1,2	1	mmx	alu	mmx	a, j
PSUBB/W/D PSUB(U)SB/W	r, r/m	1	0	2	1	1,2	1	mmx	alu	mmx	a, j
PADDQ, PSUBQ	mm, r/m	1	0	2	1	1	1	mmx	alu	sse2	a
PADDQ, PSUBQ	xmm, r/m	1	0	5	1	2	1	fp	add	sse2	a
PCMPEQB/W/D PCMPGTB/W/D	r, r/m	1	0	2	1	1,2	1	mmx	alu	mmx	a, j
PMULLW PMULHW	r, r/m	1	0	7	1	1,2	1	fp	mul	mmx	a, j

PMULHUW	r,r/m	1	0	7	1	1,2	1	fp	mul	sse	a ₂ j
PMADDWD	r,r/m	1	0	7	1	1,2	1	fp	mul	mmx	a ₂ j
PMULUDQ	r,r/m	1	0	7	1	1,2	1	fp	mul	sse2	a ₂ j
PAVGB/W	r,r/m	1	0	2	1	1,2	1	mmx	alu	sse	a ₂ j
PMIN/MAXUB	r,r/m	1	0	2	1	1,2	1	mmx	alu	sse	a ₂ j
PMIN/MAXSW	r,r/m	1	0	2	1	1,2	1	mmx	alu	sse	a ₂ j
PSADBW	r,r/m	1	0	4	1	1,2	1	mmx	alu	sse	a ₂ j
Logic											
PAND, PANDN	r,r/m	1	0	2	1	1,2	1	mmx	alu	mmx	a ₂ j
POR, PXOR	r,r/m	1	0	2	1	1,2	1	mmx	alu	mmx	a ₂ j
PSLL/RLW/D/Q, PSRAW/D	r,i/r/m	1	0	2	1	1,2	1	mmx	shift	mmx	a ₂ j
PSLLDQ, PSRLDQ	xmm,i	1	0	4	1	2	1	mmx	shift	sse2	
Other											
EMMS		10	10			12	0			mmx	

Notes:

- a) Add 1 μ op if source is a memory operand.
- j) Reciprocal throughput is 1 for 64 bit operands, and 2 for 128 bit operands.
- k) It may be advantageous to replace this instruction by two 64-bit moves or [LDDQU](#).

9.4 Floating point XMM instructions

Instruction	Operands	µops	Microcode	Latency	Additional latency	Reciprocal throughput	Port	Execution unit	Subunit	Backwards compatibility	Notes
Move instructions											
MOVAPS/D	r,r	1	0	7	0	1	0	mov		sse	
MOVAPS/D	r,m	1	0		0	1	2			sse	
MOVAPS/D	m,r	2	0			2	0			sse	
MOVUPS/D	r,r	1	0	7	0	1	0	mov		sse	
MOVUPS/D	r,m	4	0			2	2			sse	k
MOVUPS/D	m,r	4	2			8	0			sse	k
MOVSS	r,r	1	0	2	1	2	1	mmx	shift	sse	
MOVSD	r,r	1	0	4	1	2	1	mmx	shift	sse	
MOVSS, MOVSD	r,m	1	0		0	1	2			sse	
MOVSS, MOVSD	m,r	2	0			2	0			sse	
MOVHLPs	r,r	1	0	4	1	2	1	mmx	shift	sse	
MOVLHPS	r,r	1	0	2	1	2	1	mmx	shift	sse	
MOVHPS/D, MOVLPS/D	r,m	2	0			2	2			sse	
MOVHPS/D, MOVLPS/D	m,r	2	0			2	0			sse	
MOVSH/LDUP	r,r	1	0	4	1	2	1			sse3	
MOVDDUP	r,r	1	0	2	1	2	1			sse3	
MOVNTPS/D	m,r	2	0			4	0			sse	
MOVMSKPS/D	r32,r	2	0	5	1	3	1	fp		sse	
SHUFPS/D	r,r/m,i	1	0	4	1	2	1	mmx	shift	sse	
UNPCKHPS/D	r,r/m	2	0	4	1	2	1	mmx	shift	sse	
UNPCKLPS/D	r,r/m	1	0	2	1	2	1	mmx	shift	sse	
Conversion											
CVTTPS2PD	r,r/m	1	0	4	1	4	1	mmx	shift	sse2	a
CVTPD2PS	r,r/m	2	0	10	1	2	1	fp-mmx		sse2	a
CVTSD2SS	r,r/m	3	0	14	1	6	1	mmx	shift	sse2	a
CVTSS2SD	r,r/m	2	0	8	1	6	1	mmx	shift	sse2	a
CVTDQ2PS	r,r/m	1	0	5	1	2	1	fp		sse2	a
CVTDQ2PD	r,r/m	3	0	10	1	4	1	mmx-fp		sse2	a
CVT(T)PS2DQ	r,r/m	1	0	5	1	2	1	fp		sse2	a
CVT(T)PD2DQ	r,r/m	2	0	11	1	2	1	fp-mmx		sse2	a
CVTPI2PS	xmm,mm	4	0	12	1	6	1	mmx		sse	a
CVTPI2PD	xmm,mm	4	0	12	1	5	1	fp-mmx		sse2	a
CVT(T)PS2PI	mm,xmm	3	0	8	0	2	0,1	fp-mmx		sse	a
CVT(T)PD2PI	mm,xmm	4	0	12	1	3	0,1	fp-mmx		sse2	a
CVTSI2SS	xmm,r32	3	0	20	1	4	1	fp-mmx		sse	a
CVTSI2SD	xmm,r32	4	0	20	1	5	1	fp-mmx		sse2	a
CVT(T)SD2SI	r32,xmm	2	0	12	1	4	1	fp		sse2	a
CVT(T)SS2SI	r32,xmm	2	0	17	1	4	1	fp		sse	a
Arithmetic											
ADDPS/D ADDSS/D	r,r/m	1	0	5	1	2	1	fp	add	sse	a
SUBPS/D SUBSS/D	r,r/m	1	0	5	1	2	1	fp	add	sse	a
ADDSUBPS/D	r,r/m	1	0	5	1	2	1	fp	add	sse3	a
HADDPS/D HSUBPS/D	r,r/m	3	0	13	1	5-6	1	fp	add	sse3	a

MULPS/D MULSS/D	r,r/m	1	0	7	1	2	1	fp	mul	sse	a
DIVSS	r,r/m	1	0	32	1	23	1	fp	div	sse	a,h
DIVPS	r,r/m	1	0	41	1	41	1	fp	div	sse	a,h
DIVSD	r,r/m	1	0	40	1	40	1	fp	div	sse2	a,h
DIVPD	r,r/m	1	0	71	1	71	1	fp	div	sse2	a,h
RCPPS RCPSS	r,r/m	2	0	6	1	4	1	mmx		sse	a
MAXPS/D MAXSS/D MINPS/D MINSS/D	r,r/m	1	0	5	1	2	1	fp	add	sse	a
CMPccPS/D CMPccSS/D	r,r/m	1	0	5	1	2	1	fp	add	sse	a
COMISS/D UCOMISS/D	r,r/m	2	0	6	1	3	1	fp	add	sse	a
Logic											
ANDPS/D ANDNPS/D ORPS/D XORPS/D	r,r/m	1	0	2	1	2	1	mmx	alu	sse	a
Math											
SQRTSS	r,r/m	1	0	32	1	32	1	fp	div	sse	a,h
SQRTPS	r,r/m	1	0	41	1	41	1	fp	div	sse	a,h
SQRTSD	r,r/m	1	0	40	1	40	1	fp	div	sse2	a,h
SQRTPD	r,r/m	1	0	71	1	71	1	fp	div	sse2	a,h
RSQRTSS	r,r/m	2	0	5	1	3	1	mmx		sse	a
RSQRTPS	r,r/m	2	0	6	1	4	1	mmx		sse	a
Other											
LDMXCSR	m	2	11			13	1			sse	
STMXCSR	m	3	0			3	1			sse	

Notes:

- a) Add 1 μ op if source is a memory operand.
- h) Throughput of FP-MUL unit is reduced during the use of the FP-DIV unit.
- k) It may be advantageous to replace this instruction by two 64-bit moves or [LDDQU](#).

10 List of instruction timings and μ ops breakdown for Atom

Explanation of column headings:

Operands: i = immediate data, r = register, mm = 64 bit mmx register, xmm = 128 bit xmm register, (x)mm = mmx or xmm register, sr = segment register, m = memory, m32 = 32-bit memory operand, etc.

μ ops: The number of μ ops from the decoder or ROM.

Unit: Tells which execution unit is used. Instructions that use the same unit cannot execute simultaneously.

ALU0 and ALU1 means integer unit 0 or 1, respectively.

ALU0/1 means that either unit can be used. ALU0+1 means that both units are used.

Mem means memory in/out unit.

FP0 means floating point unit 0 (includes multiply, divide and other SIMD instructions).

FP1 means floating point unit 1 (adder).

MUL means multiplier, shared between FP and integer units.

DIV means divider, shared between FP and integer units.

np means not pairable: Cannot execute simultaneously with any other instruction.

Latency: This is the delay that the instruction generates in a dependency chain. The numbers are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably. Floating point operands are presumed to be normal numbers. Denormal numbers, NAN's and infinity increase the delays very much, except in XMM move, shuffle and Boolean instructions. Floating point overflow, underflow, denormal or NAN results give a similar delay.

Reciprocal throughput: The average number of clock cycles per instruction for a series of independent instructions of the same kind in the same thread.

10.1 Integer instructions

	Operands	μ ops	Unit	Latency	Reciprocal throughput	Remarks
Move instructions						
MOV	r,r	1	ALU0/1	1	1/2	
MOV	r,i	1	ALU0/1	1	1/2	
MOV	r,m	1	ALU0, Mem	1-3	1	All addressing modes
MOV	m,r	1	ALU0, Mem	1	1	All addressing modes
MOV	m,i	1	ALU0, Mem		1	
MOV	r,sr	1		1	1	
MOV	m,sr	2			5	
MOV	sr,r	7			21	
MOV	sr,m	8			26	
MOVNTI	m,r	1	ALU0, Mem		2.5	
MOVSX MOVZX MOVSSD	r,r/m	1	ALU0	1	1	
CMOVcc	r,r	1	ALU0+1	2	2	
CMOVcc	r,m	1			3	
XCHG	r,r	3		6	6	

XCHG	r,m	4		6	6	Implicit lock
XLAT		3		6	6	
PUSH	r	1	np	1	1	
PUSH	i	1	np		1	
PUSH	m	2			5	
PUSH	sr	3			6	
PUSHF(D/Q)		14			12	
PUSHA(D)		9			11	Not in x64 mode
POP	r	1	np	1	1	
POP	(E/R)SP	1	np	1	1	
POP	m	3			6	
POP	sr	7			31	
POPF(D/Q)		19			28	
POPA(D)		16			12	Not in x64 mode
LAHF		1	ALU0+1	2	2	
SAHF		1	ALU0/1	1	1/2	
SALC		2		7	5	Not in x64 mode
LEA	r,m	1	AGU1	1-4	1	4 clock latency on input register
BSWAP	r	1	ALU0	1	1	
LDS LES LFS LGS LSS	m	10		30	30	
PREFETCHNTA	m	1	Mem		1	
PREFETCHT0/1/2	m	1	Mem		1	
LFENCE		1			1/2	
MFENCE		1			1	
SFENCE		1			1	
Arithmetic instructions						
ADD SUB	r,r/i	1	ALU0/1	1	1/2	
ADD SUB	r,m	1	ALU0/1, Mem		1	
ADD SUB	m,r/i	1		2	1	
ADC SBB	r,r/i	1		2	2	
ADC SBB	r,m	1		2	2	
ADC SBB	m,r/i	1		2	2	
CMP	r,r/i	1	ALU0/1	1	1/2	
CMP	m,r/i	1			1	
INC DEC NEG NOT	r	1	ALU0/1	1	1/2	
INC DEC NEG NOT	m	1		1		
AAA		13		16		Not in x64 mode
AAS		13		12		Not in x64 mode
DAA		20		20		Not in x64 mode
DAS		21		25		Not in x64 mode
AAD		4		7		Not in x64 mode
AAM		10		24		Not in x64 mode
MUL IMUL	r8	3	ALU0, Mul	7	7	
MUL IMUL	r16	4	ALU0, Mul	6	6	
MUL IMUL	r32	3	ALU0, Mul	6	6	
MUL IMUL	r64	8	ALU0, Mul	14	14	
IMUL	r16,r16	2	ALU0, Mul	6	5	
IMUL	r32,r32	1	ALU0, Mul	5	2	
IMUL	r64,r64	6	ALU0, Mul	13	11	
IMUL	r16,r16,i	2	ALU0, Mul	5	5	

IMUL	r32,r32,i	1	ALU0, Mul	5	2	
IMUL	r64,r64,i	7	ALU0, Mul	14	14	
MUL IMUL	m8	3	ALU0, Mul	6		
MUL IMUL	m16	5	ALU0, Mul	7		
MUL IMUL	m32	4	ALU0, Mul	7		
MUL IMUL	m64	8	ALU0, Mul	14		
DIV	r/m8	9	ALU0, Div	22	22	
DIV	r/m16	12	ALU0, Div	33	33	
DIV	r/m32	12	ALU0, Div	49	49	
DIV	r/m 64	38	ALU0, Div	183	183	
IDIV	r/m8	26	ALU0, Div	38	38	
IDIV	r/m16	29	ALU0, Div	45	45	
IDIV	r/m32	29	ALU0, Div	61	61	
IDIV	r/m64	60	ALU0, Div	207	207	
CBW		2	ALU0	5		
CWDE		1	ALU0	1		
CDQE		1	ALU0	1		
CWD		2	ALU0	5		
CDQ		1	ALU0	1		
CQO		1	ALU0	1		
Logic instructions						
AND OR XOR	r,r/i	1	ALU0/1	1	1/2	
AND OR XOR	r,m	1	ALU0/1, Mem		1	
AND OR XOR	m,r/i	1	ALU0/1, Mem	1	1	
TEST	r,r/i	1	ALU0/1	1	1/2	
TEST	m,r/i	1	ALU0/1, Mem		1	
SHR SHL SAR	r,i/cl	1	ALU0	1	1	
SHR SHL SAR	m,i/cl	1	ALU0	1	1	
ROR ROL	r,i/cl	1	ALU0	1	1	
ROR ROL	m,i/cl	1	ALU0	1	1	
RCR	r,l	5	ALU0	7		
RCL	r,l	2	ALU0	1		
RCR	r/m,i/cl	12-17	ALU0	12-15		
RCL	r/m,i/cl	14-20	ALU0	14-18		
SHLD	r16,r16,i	10	ALU0	10		1-2 more if memory operand
SHLD	r32,r32,i	2	ALU0	5		1-2 more if memory operand
SHLD	r64,r64,i	10	ALU0	11		1-2 more if memory operand
SHLD	r16,r16,cl	9	ALU0	9		1-2 more if memory operand
SHLD	r32,r32,cl	2	ALU0	5		1-2 more if memory operand
SHLD	r64,r64,cl	9	ALU0	10		1-2 more if memory operand
SHRD	r16,r16,i	8	ALU0	8		1-2 more if memory operand
SHRD	r32,r32,i	2	ALU0	5		1-2 more if memory operand
SHRD	r64,r64,i	10	ALU0	9		1-2 more if memory operand
SHRD	r16,r16,cl	7	ALU0	8		1-2 more if memory operand
SHRD	r32,r32,cl	2	ALU0	5		1-2 more if memory operand
SHRD	r64,r64,cl	9	ALU0	9		1-2 more if memory operand
BT	r,r/i	1	ALU1	1	1	
BT	m,r	9		10		
BT	m,i	2		5		
BTR BTS BTC	r,r/i	1	ALU1	1	1	

BTR BTS BTC	m,r	10	ALU1	11		
BTR BTS BTC	m,i	3	ALU1	6		
BSF BSR	r,r/m	10		16		
SETcc	r	1	ALU0+1	2	2	
SETcc	m	2			5	
CLC STC		1	ALU0/1		1/2	
CMC		1		2	2	
CLD		5			7	
STD		6			25	
Control transfer instructions						
JMP	short/near	1	ALU1		2	
JMP	far	29			66	Not in x64 mode
JMP	r	1			4	
JMP	m(near)	2			7	
JMP	m(far)	30			78	
Conditional jump	short/near	1	ALU1		2	
J(E/R)CXZ	short	3			7	
LOOP	short	8			8	
LOOP(N)E	short	8			8	
CALL	near	1			3	
CALL	far	37			65	Not in x64 mode
CALL	r	1			18	
CALL	m(near)	2			20	
CALL	m(far)	38			64	
RETN		1	np		6	
RETN	i	1	np		6	
RETF		36			80	
RETF	i	36			80	
BOUND	r,m	11			10	Not in x64 mode
INTO		4			6	Not in x64 mode
String instructions						
LODS		3		6		
REP LODS		5n+11		3n+50		
STOS		2		5		
REP STOS		3n+10		2n+4		
MOVS		4		6		
REP MOVS		4n+11		2n - 4n		fastest for high n
SCAS		3		6		
REP SCAS		5n+16		3n+60		
CMPS		5		7		
REP CMPS		6n+16		4n+40		
Other						
NOP (90)		1	ALU0/1		1/2	
NOP (0F 1F mod000rm)		1	ALU0/1		1/2	
PAUSE		5		24		
ENTER	a,0	14		23		
ENTER	a,b	20+6b				
LEAVE		4			6	

CPUID		40-80		100-170		
RDTSC		16		29		
RDPMC		24		48		

10.2 Floating point x87 instructions

	Operands	µops	Unit	Latency	Reciprocal throughput	Remarks
Move instructions						
FLD	r	1		1	1	
FLD	m32/m64	1		3	1	
FLD	m80	4		9	10	
FBLD	m80	52		92	92	
FST(P)	r	1		1	1	
FST(P)	m32/m64	3		7	9	
FSTP	m80	8		12	13	
FBSTP	m80	189		221	221	
FXCH	r	1		1	1	
FILD	m	1		7	6	
FIST(P)	m	3		11	9	
FISTP	m	3		11	9	SSE3
FLDZ		1			1	
FLD1		2			8	
FLDPI FLDL2E etc.		2			10	
FCMOVcc	r	3		9	9	
FNSTSW	AX	4			10	
FNSTSW	m16	4			10	
FLDCW	m16	2			8	
FNSTCW	m16	3			9	
FINCSTP FDECSTP		1		1	1	
FFREE(P)		1			1	
FNSAVE	m	166		321	321	
FRSTOR	m	83		177	177	
Arithmetic instructions						
FADD(P) FSUB(R)(P)	r/m	1		5	1	
FMUL(P)	r/m	1	Mul	5	2	
FDIV(R)(P)	r/m	1	Div	71	71	
FABS		1		1	1	
FCHS		1		1	1	
FCOM(P) FUCOM	r/m	1		1	1	
FCOMPP FUCOMPP		1		1	1	
FCOMI(P) FUCOMI(P)	r	5			10	
FIADD FISUB(R)	m	3			9	
FIMUL	m	3	Mul		9	
FIDIV(R)	m	3	Div		73	
FICOM(P)	m	3			9	
FTST		1		1	1	
FXAM		1		1	1	
FPREM		26		~110		
FPREM1		37		~130		
FRNDINT		19		48		

Math						
FSCALE		30		56		
EXTRACT		15		24		
FSQRT		1	Div	71		
FSIN FCOS		9		~260		
FSINCOS		112		~260		
F2XM1		25		~100		
FYL2X FYL2XP1		63		~220		
FPTAN		100		~300		
FPATAN		91		~300		
Other						
FNOP		1			1	
WAIT		2		5	5	
FNCLEX		4			26	
FNINIT		23		74		

10.3 Integer MMX and XMM instructions

Move instructions	Operands	μops	Unit	Latency	Reciprocal throughput	Remarks
MOVD	r32/64,(x)mm	1		4	2	
MOVD	m32/64,(x)mm	1	Mem	5	1	
MOVD	(x)mm,r32/64	1		3	1	
MOVD	(x)mm,m32/64	1	Mem	4	1	
MOVQ	(x)mm, (x)mm	1	FP0/1	1	1/2	
MOVQ	(x)mm,m64	1	Mem	4	1	
MOVQ	m64, (x)mm	1	Mem	5	1	
MOVDQA	xmm, xmm	1	FP0/1	1	1/2	
MOVDQA	xmm, m128	1	Mem	4	1	
MOVDQA	m128, xmm	1	Mem	5	1	
MOVDQU	m128, xmm	3	Mem	6	6	
MOVDQU	xmm, m128	4	Mem	6	6	
LDDQU	xmm, m128	4	Mem	6	6	
MOVDQ2Q	mm, xmm	1		1	1	
MOVQ2DQ	xmm,mm	1		1	1	
MOVNTQ	m64,mm	1	Mem	~400	1	
MOVNTDQ	m128,xmm	1	Mem	~450	3	
PACKSSWB/DW PACKUSWB	(x)mm, (x)mm	1	FP0	1	1	
PUNPCKH/LBW/WD/DQ	(x)mm, (x)mm	1	FP0	1	1	
PUNPCKH/LQDQ	(x)mm, (x)mm	1	FP0	1	1	
PSHUFB	mm,mm	1	FP0	1	1	
PSHUFB	xmm,xmm	4		6	6	
PSHUFW	mm,mm,i	1	FP0	1	1	
PSHUFL/HW	xmm,xmm,i	1	FP0	1	1	
PSHUFD	xmm,xmm,i	1	FP0	1	1	
PALIGNR	xmm, xmm,i	1	FP0	1	1	
MASKMOVQ	mm,mm	1	Mem		2	
MASKMOVDQU	xmm,xmm	2	Mem		7	
PMOVMSKB	r32,(x)mm	1		4	2	
PINSRW	(x)mm,r32,i	1		3	1	
PEXTRW	r32,(x)mm,i	2		5	5	
Arithmetic instructions						
PADD/SUB(U)(S)B/W/D	(x)mm, (x)mm	1	FP0/1	1	1/2	
PADDQ PSUBQ	(x)mm, (x)mm	2		5	5	
PHADD(S)W PHSUB(S)W	(x)mm, (x)mm	7		8	8	
PHADDD PHSUBD	(x)mm, (x)mm	3		6		
PCMPEQ/GTB/W/D	(x)mm,(x)mm	1	FP0/1	1	1/2	
PMULL/HW PMULHUW	mm,mm	1	FP0, Mul	4	1	
PMULL/HW PMULHUW	xmm,xmm	1	FP0, Mul	5	2	
PMULHSW	mm,mm	1	FP0, Mul	4	1	
PMULHSW	xmm,xmm	1	FP0, Mul	5	2	
PMULUDQ	mm,mm	1	FP0, Mul	4	1	
PMULUDQ	xmm,xmm	1	FP0, Mul	5	2	

PMADDWD	mm,mm	1	FP0, Mul	4	1	
PMADDWD	xmm,xmm	1	FP0, Mul	5	2	
PMADDUBSW	mm,mm	1	FP0, Mul	4	1	
PMADDUBSW	xmm,xmm	1	FP0, Mul	5	2	
PSADBW	mm,mm	1	FP0, Mul	4	1	
PSADBW	xmm,xmm	1	FP0, Mul	5	2	
PAVGB/W	(x)mm,(x)mm	1	FP0/1	1	1/2	
PMIN/MAXUB	(x)mm,(x)mm	1	FP0/1	1	1/2	
PMIN/MAXSW	(x)mm,(x)mm	1	FP0/1	1	1/2	
PABSB PABSW PABSD	(x)mm,(x)mm	1	FP0/1	1	1/2	
PSIGNB PSIGNW PSIGND	(x)mm,(x)mm	1	FP0/1	1	1/2	
Logic instructions						
PAND(N) POR PXOR	(x)mm,(x)mm	1	FP0/1	1	1/2	
PSLL/RL/RAW/D/Q	(x)mm,(x)mm	2	FP0	5	5	
PSLL/RL/RAW/D/Q	(x)xmm,i	1	FP0	1	1	
PSLL/RLDQ	xmm,i	1	FP0	1	1	
Other						
EMMS		9			9	

10.4 Floating point XMM instructions

Move instructions	Operands	µops	Unit	Latency	Reciprocal throughput	Remarks
MOVAPS/D	xmm,xmm	1	FP0/1	1	1/2	
MOVAPS/D	xmm,m128	1	Mem	4	1	
MOVAPS/D	m128,xmm	1	Mem	5	1	
MOVUPS/D	xmm,m128	4	Mem	6	6	
MOVUPS/D	m128,xmm	3	Mem	6	6	
MOVSS/D	xmm,xmm	1	FP0/1	1	1/2	
MOVSS/D	xmm,m32/64	1	Mem	4	1	
MOVSS/D	m32/64,xmm	1	Mem	5	1	
MOVHPS/D MOVLPS/D	xmm,m64	1	Mem	5	1	
MOVHPS/D	m64,xmm	1	Mem	4	1	
MOVLPS/D	m64,xmm	1	Mem	4	1	
MOVLHPS MOVHLPS	xmm,xmm	1	FP0	1	1	
MOVMSKPS/D	r32,xmm	1		4	2	
MOVNTPS/D	m128,xmm	1	Mem	~500	3	
SHUFPS	xmm,xmm,i	1	FP0	1	1	
SHUFPD	xmm,xmm,i	1	FP0	1	1	
MOVDDUP	xmm,xmm	1	FP0	1	1	
MOVSH/LDUP	xmm,xmm	1	FP0	1	1	
UNPCKH/LPS	xmm,xmm	1	FP0	1	1	
UNPCKH/LPD	xmm,xmm	1	FP0	1		
Conversion						
CVTPD2PS	xmm,xmm	4		11	11	
CVTSD2SS	xmm,xmm	3		10	10	
CVTPS2PD	xmm,xmm	4		7	6	
CVTSS2SD	xmm,xmm	3		6	6	
CVTDQ2PS	xmm,xmm	3		6	6	
CVT(T) PS2DQ	xmm,xmm	3		6	6	
CVTDQ2PD	xmm,xmm	3		7	6	
CVT(T)PD2DQ	xmm,xmm	3		6	6	
CVTPS2PI	xmm,mm	1		6	5	
CVT(T)PS2PI	mm,xmm	1		4	1	
CVTPI2PD	xmm,mm	3		7	6	
CVT(T) PD2PI	mm,xmm	4		7	7	
CVTSI2SS	xmm,r32	3		7	6	
CVT(T)SS2SI	r32,xmm	3		10	8	
CVTSI2SD	xmm,r32	3		8	6	
CVT(T)SD2SI	r32,xmm	3		10	8	

Arithmetic						
ADDSS SUBSS	xmm,xmm	1	FP1	5	1	
ADDSD SUBSD	xmm,xmm	1	FP1	5	1	
ADDPS SUBPS	xmm,xmm	1	FP1	5	1	
ADDPD SUBPD	xmm,xmm	3	FP1	6	6	
ADDSUBPS	xmm,xmm	1	FP1	5	1	
ADDSUBPD	xmm,xmm	3	FP1	6	6	
HADDPS HSUBPS	xmm,xmm	5	FP0+1	8	7	
HADDPD HSUBPD	xmm,xmm	5	FP0+1	8	7	
MULSS	xmm,xmm	1	FP0, Mul	4	1	
MULSD	xmm,xmm	1	FP0, Mul	5	2	
MULPS	xmm,xmm	1	FP0, Mul	5	2	
MULPD	xmm,xmm	6	FP0, Mul	9	9	
DIVSS	xmm,xmm	3	FP0, Div	31	31	
DIVSD	xmm,xmm	3	FP0, Div	60	60	
DIVPS	xmm,xmm	6	FP0, Div	64	64	
DIVPD	xmm,xmm	6	FP0, Div	122	122	
RCPSS	xmm,xmm	1		4	1	
RCPPS	xmm,xmm	5		9	8	
CMPccSS/D	xmm,xmm	1	FP0	5	1	
CMPccPS/D	xmm,xmm	3	FP0	6	6	
COMISS/D UCOMISS/D	xmm,xmm	4	FP0	9	9	
MAXSS/D MINSS/D	xmm,xmm	1	FP0	5	1	
MAXPS/D MINPS/D	xmm,xmm	3	FP0	6	6	
Math						
SQRTSS	xmm,xmm	3	FP0, Div	31	31	
SQRTPS	xmm,xmm	5	FP0, Div	63	63	
SQRTSD	xmm,xmm	3	FP0, Div	60	60	
SQRTPD	xmm,xmm	5	FP0, Div	121	121	
RSQRTSS	xmm,xmm	1	FP0	4	1	
RSQRTPS	xmm,xmm	5	FP0	9	8	
Logic						
ANDPS/D	xmm,xmm	1	FP0/1	1	1/2	
ANDNPS/D	xmm,xmm	1	FP0/1	1	1/2	
ORPS/D	xmm,xmm	1	FP0/1	1	1/2	
XORPS/D	xmm,xmm	1	FP0/1	1	1/2	
Other						
LDMXCSR	m32	4		5	6	
STMXCSR	m32	4		14	15	
FXSAVE	m4096	121		142	144	
FXRSTOR	m4096	116		149	150	

11 List of instruction timings and μ ops breakdown for VIA Nano 2000 series

Explanation of column headings:

Operands: i = immediate data, r = register, mm = 64 bit mmx register, xmm = 128 bit xmm register, (x)mm = mmx or xmm register, sr = segment register, m = memory, m32 = 32-bit memory operand, etc.

μ ops: The number of micro-operations from the decoder or ROM. Note that the VIA Nano 2000 processor has no reliable performance monitor counter for μ ops. Therefore the number of μ ops cannot be determined except in simple cases.

Port: Tells which execution port is used. Instructions that use the same port cannot execute simultaneously.

I1: Integer add, Boolean, shift, etc.

I2: Integer add, Boolean, move, jump.

I12: Can use either I1 or I2, whichever is vacant first.

MA: Multiply, divide and square root on all operand types.

MB: Various Integer and floating point SIMD operations.

MBfadd: Floating point addition subunit under MB.

SA: Memory store address.

ST: Memory store.

LD: Memory load.

Latency: This is the delay that the instruction generates in a dependency chain. The numbers are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably. Floating point operands are presumed to be normal numbers. Denormal numbers, NAN's and infinity increase the delays very much, except in XMM move, shuffle and Boolean instructions. Floating point overflow, underflow, denormal or NAN results give a similar delay.

Note: There is an additional latency for moving data from one unit or subunit to another. A table of these latencies is given in manual 3: "The microarchitecture of Intel, AMD and VIA CPUs". These additional latencies are not included in the listings below where the source and destination operands are of the same type.

Reciprocal throughput: The average number of clock cycles per instruction for a series of independent instructions of the same kind in the same thread.

11.1 Integer instructions

	Operands	μ ops	Unit	Latency	Reciprocal throughput	Remarks
Move instructions						
MOV	r,r	1	I2	1	1	
MOV	r,i	1	I2	1	1	
MOV	r,m	1	LD	2	1	Latency 4 on pointer register
MOV	m,r	1	SA, ST	2	1.5	
MOV	m,i	1	SA, ST		1.5	
MOV	r,sr				1	
MOV	m,sr				2	

MOV	sr,r			20	20	
MOV	sr,m			20	20	
MOVNTI	m,r		SA, ST	2	1.5	
MOVSX MOVSLD MOVZX	r,r	1	I2	1	1	
MOVSX MOVSLD	r,m	2	LD, I2	3	1	
MOVZX	r,m	1	LD	2	1	
CMOVCc	r,r	2	I1, I2	2	1	
CMOVCc	r,m		LD, I1	5	2	
XCHG	r,r	3	I2	3	3	
XCHG	r,m			20	20	Implicit lock
XLAT	m			6		
PUSH	r		SA, ST		1-2	
PUSH	i		SA, ST		1-2	
PUSH	m		Ld, SA, ST		2	
PUSH	sr				17	
PUSHF(D/Q)				8	8	
PUSHA(D)					15	Not in x64 mode
POP	r		LD		1.25	
POP	(E/R)SP				4	
POP	m				5	
POP	sr				20	
POPF(D/Q)				9	9	
POPA(D)					12	Not in x64 mode
LAHF		1	I1	1	1	
SAHF		1	I1	1	1	
SALC				9	6	Not in x64 mode
LEA	r,m	1	SA	1	1	3 clock latency on input register
BSWAP	r	1	I2	1	1	
LDS LES LFS LGS LSS	m			30	30	
PREFETCHNTA	m		LD		1-2	
PREFETCHT0/1/2	m		LD		1-2	
LFENCE					14	
MFENCE					14	
SFENCE					14	
Arithmetic instructions						
ADD SUB	r,r/i	1	I12	1	1/2	
ADD SUB	r,m	2	LD I12		1	
ADD SUB	m,r/i	3	LD I12 SA ST	5	2	
ADC SBB	r,r/i	1	I1	1	1	
ADC SBB	r,m	2	LD I1		1	
ADC SBB	m,r/i	3	LD I1 SA ST	5	2	
CMP	r,r/i	1	I12	1	1/2	
CMP	m,r/i	2	LD I12		1	
INC DEC NEG NOT	r	1	I12	1	1/2	
INC DEC NEG NOT	m	3	LD I12 SA ST	5		
AAA					37	Not in x64 mode
AAS					37	Not in x64 mode
DAA					22	Not in x64 mode
DAS					24	Not in x64 mode
AAD					23	Not in x64 mode

AAM					30	Not in x64 mode
MUL IMUL	r8		MA	7-9		Extra latency to other ports
MUL IMUL	r16		MA	7-9		Extra latency to other ports
MUL IMUL	r32		MA	7-9		Extra latency to other ports
MUL IMUL	r64		MA	8-10		Extra latency to other ports
IMUL	r16,r16		MA	4-6	1	Extra latency to other ports
IMUL	r32,r32		MA	4-6	1	Extra latency to other ports
IMUL	r64,r64		MA	5-7	2	Extra latency to other ports
IMUL	r16,r16,i		MA	4-6	1	Extra latency to other ports
IMUL	r32,r32,i		MA	4-6	1	Extra latency to other ports
IMUL	r64,r64,i		MA	5-7	2	Extra latency to other ports
DIV	r8		MA	26	26	Extra latency to other ports
DIV	r16		MA	27-35	27-35	Extra latency to other ports
DIV	r32		MA	25-41	25-41	Extra latency to other ports
DIV	r64		MA	148-183	148-183	Extra latency to other ports
IDIV	r8		MA	26	26	Extra latency to other ports
IDIV	r16		MA	27-35	27-35	Extra latency to other ports
IDIV	r32		MA	23-39	23-39	Extra latency to other ports
IDIV	r64		MA	187-222	187-222	Extra latency to other ports
CBW CWDE CDQE		1	I1	1	1	
CWD CDQ CQO		1	I1	1	1	
Logic instructions						
AND OR XOR	r,r/i	1	I12	1	1/2	
AND OR XOR	r,m	2	LD I12		1	
AND OR XOR	m,r/i	3	LD I12 SA ST	5	2	
TEST	r,r/i	1	I12	1	1/2	
TEST	m,r/i	2	LD I12		1	
SHR SHL SAR	r,i/cl	1	I1	1	1	
ROR ROL	r,i/cl	1	I1	1	1	
RCR RCL	r,l	1	I1	1	1	
RCR RCL	r,i/cl		I1	28+3n	28+3n	
SHLD SHRD	r16,r16,i		I1	11	11	
SHLD SHRD	r32,r32,i		I1	7	7	
SHLD	r64,r64,i		I1	33	33	
SHRD	r64,r64,i		I1	43	43	
SHLD SHRD	r16,r16,cl		I1	11	11	
SHLD SHRD	r32,r32,cl		I1	7	7	
SHLD	r64,r64,cl		I1	33	33	
SHRD	r64,r64,cl		I1	43	43	
BT	r,r/i	1	I1	1	1	
BT	m,r		I1		8	
BT	m,i	2	I1		1	
BTR BTS BTC	r,r/i	2	I1	2	2	
BTR BTS BTC	m,r		I1	10	10	
BTR BTS BTC	m,i		I1	8	8	
BSF BSR	r,r		I1	3	2	
SETcc	r		I1	2	1	
SETcc	m				1	
CLC STC CMC			I1	3	3	
CLD STD				3	3	

Control transfer instructions						
JMP	short/near	1	I2	3	3	8 if >2 jumps in 16 bytes block
JMP	far			58		Not in x64 mode
JMP	r		I2	3	3	8 if >2 jumps in 16 bytes block
JMP	m(near)			3	3	8 if >2 jumps in 16 bytes block
JMP	m(far)			55		
Conditional jump	short/near			1-3-8	1-3-8	1 if not jumping.
J(E/R)CXZ	short			1-3-8	1-3-8	3 if jumping.
LOOP	short			1-3-8	1-3-8	8 if >2 jumps in 16 bytes block
LOOP(N)E	short			25	25	
CALL	near			3	3	8 if >2 jumps in 16 bytes block
CALL	far			72	72	Not in x64 mode
CALL	r			3	3	8 if >2 jumps in 16 bytes block
CALL	m(near)			4	3	8 if >2 jumps in 16 bytes block
CALL	m(far)			72	72	
RETN				3	3	8 if >2 jumps in 16 bytes block
RETN	i			3	3	8 if >2 jumps in 16 bytes block
RETF				39	39	
RETF	i			39	39	
BOUND	r,m				13	Not in x64 mode
INTO					7	Not in x64 mode
String instructions						
LODSB/W/D/Q					1	
REP LODSB/W/D/Q					3n+22	
STOSB/W/D/Q					1-2	
REP STOSB/W/D/Q				Small: 2n+2, Big: 6 bytes per clock		
MOVSX/W/D/Q					2	
REP MOVSX/W/D/Q				Small: 2n+45, Big: 6 bytes per clock		
SCASB/W/D/Q					1	
REP SCASB				2.2n		
REP SCASW/D/Q				Small: 2n+50, Big: 5 bytes per clock		
CMPSB/W/D/Q					6	
REP CMPSB/W/D/Q				2.4n+24		
Other						
NOP (90)		1	All		1	Blocks all ports
NOP (0F 1F mod000rm)		1	I12		1/2	
PAUSE					25	
ENTER	a,0				23	
ENTER	a,b				52+5b	
LEAVE				4	4	
CPUID				53-173		
RDTSC					39	
RDPMSR				40	40	

11.2 Floating point x87 instructions

	Operands	µops	Unit	Latency	Reciprocal throughput	Remarks
Move instructions						
FLD	r	1	MB	1	1	
FLD	m32/m64	2	LD MB	4	1	
FLD	m80	2	LD MB	4	1	
FBLD	m80			54	54	
FST(P)	r	1	MB	1	1	
FST(P)	m32/m64	3	MB SA ST	5	1-2	
FSTP	m80	3	MB SA ST	5	1-2	
FBSTP	m80			125	125	
FXCH	r	1	I2	0	1	
FILD	m16			7		
FILD	m32			5		
FILD	m64			5		
FIST(T)(P)	m16			6		
FIST(T)(P)	m32			5		
FIST(T)(P)	m64			5		
FLDZ FLD1		1	MB		1	
FLDPI FLDL2E etc.					10	
FCMOVcc	r			2	2	
FNSTSW	AX				5	
FNSTSW	m16				3	
FLDCW	m16			13	13	
FNSTCW	m16				2	
FINCSTP FDECSTP		1	I2	0	1	
FFREE(P)		1	MB		1	
FNSAVE	m			321	321	
FRSTOR	m			195	195	
Arithmetic instructions						
FADD(P) FSUB(R)(P)	r/m	1	MB	2	1	Lower precision: Lat: 4, Thr: 2
FMUL(P)	r/m	1	MA	4	2	
FDIV(R)(P)	r/m		MA	15-42	15-42	
FABS		1	MB	1	1	
FCHS		1	MB	1	1	
FCOM(P) FUCOM	r/m	1	MB		1	
FCOMPP FUCOMPP		1	MB		1	
FCOMI(P) FUCOMI(P)	r	1	MB		1	
FIADD FISUB(R)	m		MB		2	
FIMUL	m				4	
FIDIV(R)	m				42	
FICOM(P)	m	1			2	
FTST		1	MB		1	
FXAM					41	
FPREM				151-171		
FPREM1				106-155		

FRNDINT				29		
Math						
FSCALE				39		
EXTRACT				36-57		
FSQRT				73		
FSIN FCOS				51-159		
FSINCOS				270-360		
F2XM1				50-200		
FYL2X				~60		
FYL2XP1				~170		
FPTAN				300-370		
FPATAN				~170		
Other						
FNOP		1	MB		1	
WAIT		1	I12	0	1/2	
FNCLEX					57	
FNINIT					85	

11.3 Integer MMX and XMM instructions

Move instructions	Operands	µops	Unit	Latency	Reciprocal throughput	Remarks
MOVD	r32/64,(x)mm	1		3	1	
MOVD	m32/64,(x)mm	1	SA ST	2-3	1-2	
MOVD	(x)mm,r32/64			4	1	
MOVD	(x)mm,m32/64	1	LD	2-3	1	
MOVQ	(x)mm, (x)mm	1	MB	1	1	
MOVQ	(x)mm,m64	1	LD	2-3	1	
MOVQ	m64, (x)mm	1	SA ST	2-3	1-2	
MOVDQA	xmm, xmm	1	MB	1	1	
MOVDQA	xmm, m128	1	LD	2-3	1	
MOVDQA	m128, xmm	1	SA ST	2-3	1-2	
MOVDQU	m128, xmm	1	SA ST	2-3	1-2	
MOVDQU	xmm, m128	1	LD	2-3	1	
LDDQU	xmm, m128	1	LD	2-3	1	
MOVDQ2Q	mm, xmm	1	MB	1	1	
MOVQ2DQ	xmm,mm	1	MB	1	1	
MOVNTQ	m64,mm	3		~300	2	
MOVNTDQ	m128,xmm	3		~300	2	
PACKSSWB/DW PACKUSWB	(x)mm, (x)mm	1	MB	1	1	
PUNPCKH/LBW/WD/DQ	(x)mm, (x)mm	1	MB	1	1	
PUNPCKH/LQDQ	(x)mm, (x)mm	1	MB	1	1	
PSHUFB	(x)mm,(x)mm	1	MB	1	1	
PSHUFW	mm,mm,i	1	MB	1	1	
PSHUFL/HW	xmm,xmm,i	1	MB	1	1	
PSHUFD	xmm,xmm,i	1	MB	1	1	
PALIGNR	xmm, xmm,i	1	MB	1	1	
MASKMOVQ	mm,mm				1-3	
MASKMOVDQU	xmm,xmm				1-3	
PMOVMASKB	r32,(x)mm			3	1	
PEXTRW	r32 ,(x)mm,i			3	1	
PINSRW	(x)mm,r32,i			9	9	
Arithmetic instructions						
PADD/SUB(U)(S)B/W/D	(x)mm, (x)mm	1	MB	1	1	
PADDQ PSUBQ	(x)mm, (x)mm	1	MB	1	1	
PHADD(S)W PHSUB(S)W	(x)mm, (x)mm	3	MB	3	3	
PHADDD PHSUBD	(x)mm, (x)mm	3	MB	3	3	
PCMPEQ/GTB/W/D	(x)mm,(x)mm	1	MB	1	1	
PMULL/HW PMULHUW	(x)mm,(x)mm	1	MA	3	1	
PMULHSW	(x)mm,(x)mm	1	MA	3	1	
PMULUDQ	(x)mm,(x)mm	1	MA	3	1	
PMADDWD	(x)mm,(x)mm			4	2	
PMADDUBSW	(x)mm,(x)mm			10	8	
PSADB	(x)mm,(x)mm		MB	2	1	
PAVGB/W	(x)mm,(x)mm	1	MB	1	1	

PMIN/MAXUB	(x)mm,(x)mm	1	MB	1	1	
PMIN/MAXSW	(x)mm,(x)mm	1	MB	1	1	
PASB PASW PASD	(x)mm,(x)mm	1	MB	1	1	
PSIGNB PSIGNW PSIGND	(x)mm,(x)mm	1	MB	1	1	
Logic instructions						
PAND(N) POR PXOR	(x)mm,(x)mm	1	MB	1	1	
PSLL/RL/RAW/D/Q	(x)mm,(x)mm	1	MB	1	1	
PSLL/RL/RAW/D/Q	(x)xmm,i	1	MB	1	1	
PSLL/RLDQ	xmm,i	1	MB	1	1	
Other						
EMMS		1	MB		1	

11.4 Floating point XMM instructions

Move instructions	Operands	μops	Unit	Latency	Reciprocal throughput	Remarks
MOVAPS/D	xmm,xmm	1	MB	1	1	
MOVAPS/D	xmm,m128	1	LD	2-3	1	
MOVAPS/D	m128,xmm	1	SA ST	2-3	1-2	
MOVUPS/D	xmm,m128	1	LD	2-3	1	
MOVUPS/D	m128,xmm	1	SA ST	2-3	1-2	
MOVSS/D	xmm,xmm	1	MB	1	1	
MOVSS/D	xmm,m32/64	1	LD	2-3	1	
MOVSS/D	m32/64,xmm	1	SA ST	2-3	1-2	
MOVHPS/D	xmm,m64			6	1	
MOVLPS/D	xmm,m64			6	1	
MOVHPS/D	m64,xmm			6	1-2	
MOVLPS/D	m64,xmm			2	1-2	
MOVLHPS MOVHLPS	xmm,xmm	1	MB	1	1	
MOVMSKPS/D	r32,xmm			3	1	
MOVNTPS/D	m128,xmm			~300	2.5	
SHUFPS	xmm,xmm,i	1	MB	1	1	
SHUFPD	xmm,xmm,i	1	MB	1	1	
MOVDDUP	xmm,xmm	1	MB	1	1	
MOVSH/LDUP	xmm,xmm	1	MB	1	1	
UNPCKH/LPS	xmm,xmm	1	MB	1	1	
UNPCKH/LPD	xmm,xmm	1	MB	1	1	
Conversion						
CVTPD2PS	xmm,xmm			3-4		
CVTSD2SS	xmm,xmm			15		
CVTPS2PD	xmm,xmm			3-4		
CVTSS2SD	xmm,xmm			15		
CVTDQ2PS	xmm,xmm			3		
CVT(T) PS2DQ	xmm,xmm			2		
CVTDQ2PD	xmm,xmm			4		
CVT(T)PD2DQ	xmm,xmm			3		
CVTPD2PS	xmm,mm			4		
CVT(T)PS2PI	mm,xmm			3		
CVTPD2PD	xmm,mm			4		
CVT(T) PD2PI	mm,xmm			3		
CVTSI2SS	xmm,r32			5		
CVT(T)SS2SI	r32,xmm			4		
CVTSI2SD	xmm,r32			5		
CVT(T)SD2SI	r32,xmm			4		

Arithmetic						
ADDSS SUBSS	xmm,xmm	1	MBfadd	2-3	1	
ADDSD SUBSD	xmm,xmm	1	MBfadd	2-3	1	
ADDPS SUBPS	xmm,xmm	1	MBfadd	2-3	1	
ADDPD SUBPD	xmm,xmm	1	MBfadd	2-3	1	
ADDSUBPS	xmm,xmm	1	MBfadd	2-3	1	
ADDSUBPD	xmm,xmm	1	MBfadd	2-3	1	
HADDPS HSUBPS	xmm,xmm		MBfadd	5	3	
HADDPD HSUBPD	xmm,xmm		MBfadd	5	3	
MULSS	xmm,xmm	1	MA	3	1	
MULSD	xmm,xmm	1	MA	4	2	
MULPS	xmm,xmm		MA	3	1	
MULPD	xmm,xmm		MA	4	2	
DIVSS	xmm,xmm		MA	15-22	15-22	
DIVSD	xmm,xmm		MA	15-36	15-36	
DIVPS	xmm,xmm		MA	42-82	42-82	
DIVPD	xmm,xmm		MA	24-70	24-70	
RCPSS	xmm,xmm			5	5	
RCPPS	xmm,xmm			14	11	
CMPccSS/D	xmm,xmm	1	MBfadd	2	1	
CMPccPS/D	xmm,xmm	1	MBfadd	2	1	
COMISS/D UCOMISS/D	xmm,xmm			3	1	
MAXSS/D MINSS/D	xmm,xmm	1	MBfadd	2	1	
MAXPS/D MINPS/D	xmm,xmm	1	MBfadd	2	1	
Math						
SQRTSS	xmm,xmm		MA	33	33	
SQRTPS	xmm,xmm		MA	126	126	
SQRTSD	xmm,xmm		MA	62	62	
SQRTPD	xmm,xmm		MA	122	122	
RSQRTSS	xmm,xmm			5	5	
RSQRTPS	xmm,xmm			14	11	
Logic						
ANDPS/D	xmm,xmm	1	MB	1	1	
ANDNPS/D	xmm,xmm	1	MB	1	1	
ORPS/D	xmm,xmm	1	MB	1	1	
XORPS/D	xmm,xmm	1	MB	1	1	
Other						
LDMXCSR	m32			45	29	
STMXCSR	m32			13	13	
FXSAVE	m4096			208	208	
FXRSTOR	m4096			232	232	

11.5 VIA-specific instructions

Instruction	Conditions	Clock cycles, approximately
XSTORE	Data available	160-400 clock giving 8 bytes
XSTORE	No data available	50-80 clock giving 0 bytes
REP XSTORE	Quality factor = 0	4800 clock per 8 bytes
REP XSTORE	Quality factor > 0	19200 clock per 8 bytes
REP XCRYPTECB	128 bits key	44 clock per 16 bytes
REP XCRYPTECB	192 bits key	46 clock per 16 bytes
REP XCRYPTECB	256 bits key	48 clock per 16 bytes
REP XCRYPTCBC	128 bits key	54 clock per 16 bytes
REP XCRYPTCBC	192 bits key	59 clock per 16 bytes
REP XCRYPTCBC	256 bits key	63 clock per 16 bytes
REP XCRYPTCTR	128 bits key	43 clock per 16 bytes
REP XCRYPTCTR	192 bits key	46 clock per 16 bytes
REP XCRYPTCTR	256 bits key	48 clock per 16 bytes
REP XCRYPTCFB	128 bits key	54 clock per 16 bytes
REP XCRYPTCFB	192 bits key	59 clock per 16 bytes
REP XCRYPTCFB	256 bits key	63 clock per 16 bytes
REP XCRYPTOFB	128 bits key	54 clock per 16 bytes
REP XCRYPTOFB	192 bits key	59 clock per 16 bytes
REP XCRYPTOFB	256 bits key	63 clock per 16 bytes
REP XSHA1		3 clock per byte
REP XSHA256		4 clock per byte

12 List of instruction timings and μ op breakdown for VIA Nano 3000 series

Explanation of column headings:

Operands: i = immediate data, r = register, mm = 64 bit mmx register, xmm = 128 bit xmm register, (x)mm = mmx or xmm register, sr = segment register, m = memory, m32 = 32-bit memory operand, etc.

μ ops: The number of micro-operations from the decoder or ROM. Note that the VIA Nano 3000 processor has no reliable performance monitor counter for μ ops. Therefore the number of μ ops is not exact.

Port: Tells which execution port is used. Instructions that use the same port cannot execute simultaneously.

I1: Integer move, add, Boolean, shift, rotate, etc.

I2: Integer move, add, Boolean, shift, multiply (32 bit), jump

I12: Can use either I1 or I2, whichever is vacant first.

MA: Multiply, divide and square root on all operand types.

MB: Various Integer and floating point SIMD operations.

MBfadd: Floating point addition subunit under MB.

SA: Memory store address.

ST: Memory store.

LD: Memory load.

Latency: This is the delay that the instruction generates in a dependency chain. The numbers are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably. Floating point operands are presumed to be normal numbers. Denormal numbers, NAN's and infinity increase the delays very much, except in XMM move, shuffle and Boolean instructions. Floating point overflow, underflow, denormal or NAN results give a similar delay.

Note: There is an additional latency for moving data from one unit or subunit to another. A table of these latencies is given in manual 3: "The microarchitecture of Intel, AMD and VIA CPUs". These additional latencies are not included in the listings below where the source and destination operands are of the same type.

Reciprocal throughput: The average number of clock cycles per instruction for a series of independent instructions of the same kind in the same thread.

12.1 Integer instructions

	Operands	μ ops	Unit	Latency	Reciprocal throughput	Remarks
Move instructions						
MOV	r,r	1	I12	1	1/2	
MOV	r,i	1	I12	1	1/2	
MOV	r,m	1	LD	2	1	Latency 4 on pointer register
MOV	m,r	1	SA, ST	2	1.5	
MOV	m,i	1	SA, ST		1.5	
MOV	r,sr		I12		1/2	
MOV	m,sr				1.5	

MOV	sr,r			20	20	
MOV	sr,m			20	20	
MOVNTI	m,r		SA, ST	2	1.5	
MOVSX MOVZX	r,r	1	I12	1	1/2	
MOVSXD	r64,r32	1		1	1	
MOVSX MOVSXD	r,m	2	LD, I12	3	1	
MOVZX	r,m	1	LD	2	1	
CMOVcc	r,r	1	I12	1	1/2	
CMOVcc	r,m		LD, I12	5	1	
XCHG	r,r	3	I12	3	1.5	
XCHG	r,m			18	18	Implicit lock
XLAT	m	3	LD, I1	6	2	
PUSH	r	1	SA, ST		1-2	
PUSH	i	1	SA, ST		1-2	
PUSH	m		LD, SA, ST		2	
PUSH	sr				6	
PUSHF(D/Q)		3		2	2	
PUSHA(D)		9			15	Not in x64 mode
POP	r	2	LD		1.25	
POP	(E/R)SP				4	
POP	m	3			2	
POP	sr				11	
POPF(D/Q)		3			1	
POPA(D)		16			12	Not in x64 mode
LAHF		1	I1	1	1	
SAHF		1	I1	1	1	
SALC		2		10	6	Not in x64 mode
LEA	r,m	1	SA	1	1	Extra latency to other ports
BSWAP	r	1	I2	1	1	
LDS LES LFS LGS LSS	m	12		28	28	
PREFETCHNTA	m	1	LD		1	
PREFETCHT0/1/2	m	1	LD		1	
LFENCE MFENCE SFENCE					15	
Arithmetic instructions						
ADD SUB	r,r/i	1	I12	1	1/2	
ADD SUB	r,m	2	LD I12		1	
ADD SUB	m,r/i	3	LD I12 SA ST	5	2	
ADC SBB	r,r/i	1	I1	1	1	
ADC SBB	r,m	2	LD I1		1	
ADC SBB	m,r/i	3	LD I1 SA ST	5	2	
CMP	r,r/i	1	I12	1	1/2	
CMP	m,r/i	2	LD I12		1	
INC DEC NEG NOT	r	1	I12	1	1/2	
INC DEC NEG NOT	m	3	LD I12 SA ST	5		
AAA		12			37	Not in x64 mode
AAS		12			22	Not in x64 mode
DAA		14			22	Not in x64 mode
DAS		14			24	Not in x64 mode
AAD		7			24	Not in x64 mode
AAM		13			31	Not in x64 mode

MUL IMUL	r8	1	I2	2		
MUL IMUL	r16	3	I2	3		
MUL IMUL	r32	3	I2	3		
MUL IMUL	r64	3	MA	8	8	Extra latency to other ports
IMUL	r16,r16	1	I2	2	1	
IMUL	r32,r32	1	I2	2	1	
IMUL	r64,r64	1	MA	5	2	Extra latency to other ports
IMUL	r16,r16,i	1	I2	2	1	
IMUL	r32,r32,i	1	I2	2	1	
IMUL	r64,r64,i	1	MA	5	2	Extra latency to other ports
DIV	r8		MA	22-24	22-24	
DIV	r16		MA	24-28	24-28	
DIV	r32		MA	22-30	22-30	
DIV	r64		MA	145-162	145-162	
IDIV	r8		MA	21-24	21-24	
IDIV	r16		MA	24-28	24-28	
IDIV	r32		MA	18-26	18-26	
IDIV	r64		MA	182-200	182-200	
CBW CWDE CDQE		1	I2	1	1	
CWD CDQ CQO		1	I2	1	1	
Logic instructions						
AND OR XOR	r,r/i	1	I12	1	1/2	
AND OR XOR	r,m	2	LD I12		1	
AND OR XOR	m,r/i	3	LD I12 SA ST	5	2	
TEST	r,r/i	1	I12	1	1/2	
TEST	m,r/i	2	LD I12		1	
SHR SHL SAR	r,i/cl	1	I12	1	1/2	
ROR ROL	r,i/cl	1	I1	1	1	
RCR RCL	r,l	1	I1	1	1	
RCR RCL	r,i/cl	5+2n	I1	28+3n	28+3n	
SHLD SHRD	r16,r16,i/cl	2	I1	2	2	
SHLD SHRD	r32,r32,i/cl	2	I1	2	2	
SHLD	r64,r64,i/cl	16	I1	32	32	
SHRD	r64,r64,i/cl	23	I1	42	42	
BT	r,r/i	1	I1	1	1	
BT	m,r	6	I1		8	
BT	m,i	2	I1		1	
BTR BTS BTC	r,r/i	2	I1	2	2	
BTR BTS BTC	m,r	8	I1	10	10	
BTR BTS BTC	m,i	5	I1	8	8	
BSF BSR	r,r	2	I1	2	2	
SETcc	r8	1	I1	1	1	
SETcc	m	2			2	
CLC STC CMC		3	I1	3	3	
CLD STD		3	I1	3	3	
Control transfer instructions						
JMP	short/near	1	I2	3	3	8 if >2 jumps in 16 bytes block
JMP	far	14			50	Not in x64 mode
JMP	r	2	I2	3	3	8 if >2 jumps in 16 bytes block

JMP	m(near)	2		3	3	8 if >2 jumps in 16 bytes block
JMP	m(far)	17			42	
Conditional jump	short/near	1	12	1-3-8	1-3-8	1 if not jumping. 3 if jumping.
J(E/R)CXZ	short	2		1-3-8	1-3-8	8 if >2 jumps in 16 bytes block
LOOP	short	2		1-3-8	1-3-8	
LOOP(N)E	short	5		24	24	
CALL	near	2		3	3	8 if >2 jumps in 16 bytes block
CALL	far	17			58	Not in x64 mode
CALL	r	2		3	3	8 if >2 jumps in 16 bytes block
CALL	m(near)	3		4	3	8 if >2 jumps in 16 bytes block
CALL	m(far)	19			54	
RETN		3		3	3	8 if >2 jumps in 16 bytes block
RETN	i	4		3	3	8 if >2 jumps in 16 bytes block
RETF		20			49	
RETF	i	20			49	
BOUND	r,m	9			13	Not in x64 mode
INTO		3			7	Not in x64 mode
String instructions						
LODSB/W/D/Q		2			1	
REP LODSB/W/D/Q		3n			3n+27	
STOSB/W/D/Q		1			1-2	
REP STOSB/W/D/Q				Small: n+40, Big: 6-7 bytes per clock		
MOVSb/W/D/Q		3			2	
REP MOVSb/W/D/Q				Small: 2n+20, Big: 6-7 bytes per clock		
SCASB/W/D/Q		3			1	
REP SCASB				2.4n		
REP SCASW/D/Q				Small: 2n+31, Big: 5 bytes per clock		
CMPSB/W/D/Q		5			6	
REP CMPSB/W/D/Q				2.2n+30		
Other						
NOP (90)		0-1	I12	0	1/2	Sometimes fused
NOP (0F 1F mod000rm)		0-1	I12	0	1/2	
PAUSE		2			6	
ENTER	a,0	10			21	
ENTER	a,b				52+5b	
LEAVE		3		2	2	
CPUID				55-146		
RDTSC					37	
RDPMSR					40	

12.2 Floating point x87 instructions

	Operands	μops	Unit	Latency	Reciprocal throughput	Remarks
Move instructions						
FLD	r	1	MB	1	1	
FLD	m32/m64	2	LD MB	4	1	
FLD	m80	2	LD MB	4	1	
FBLD	m80	36		54	54	
FST(P)	r	1	MB	1	1	
FST(P)	m32/m64	3	MB SA ST	5	1-2	
FSTP	m80	3	MB SA ST	5	1-2	
FBSTP	m80	80		125	125	
FXCH	r	1	I2	0	1	
FILD	m16	3		7		
FILD	m32	2		5		
FILD	m64	2		5		
FIST(T)(P)	m16	3		6		
FIST(T)(P)	m32	3		5		
FIST(T)(P)	m64	3		5		
FLDZ FLD1		1	MB		1	
FLDPI FLDL2E etc.		3			10	
FCMOVcc	r	1	MB	2	2	
FNSTSW	AX	1			1	
FNSTSW	m16	3			2	
FLDCW	m16	5			8	
FNSTCW	m16	3			2	
FINCSTP FDECSTP		1	I2	0	1	
FFREE(P)		1	MB		1	
FNSAVE	m	122		319	319	
FRSTOR	m	115		196	196	
Arithmetic instructions						
FADD(P) FSUB(R)(P)	r/m	1	MB	2	1	
FMUL(P)	r/m	1	MA	4	2	
FDIV(R)(P)	r/m		MA	14-23	14-23	
FABS		1	MB	1	1	
FCHS		1	MB	1	1	
FCOM(P) FUCOM	r/m	1	MB		1	
FCOMPP FUCOMPP		1	MB		1	
FCOMI(P) FUCOMI(P)	r	1	MB	2	1	
FIADD FISUB(R)	m	3	MB		2	
FIMUL	m	3			4	
FIDIV(R)	m	3			16	
FICOM(P)	m	3			2	
FTST		1	MB	2	1	
FXAM		15		38	38	
FPREM				~130		
FPREM1				~130		

FRNDINT		11		27		
Math						
FSCALE		22		37		
EXTRACT		13		57		
FSQRT				73		Less at lower precision
FSIN FCOS				~150		
FSINCOS				270-360		
F2XM1				50-200		
FYL2X				~50		
FYL2XP1				~50		
FPTAN				300-370		
FPATAN				~180		
Other						
FNOP		1	MB		1	
WAIT		1	I12	0	1/2	
FNCLEX					59	
FNINIT					84	

12.3 Integer MMX and XMM instructions

Move instructions	Operands	μops	Unit	Latency	Reciprocal throughput	Remarks
MOVD	r32/64,(x)mm	1	MB	3	1	
MOVD	m32/64,(x)mm	1	SA ST	2	1-2	
MOVD	(x)mm,r32/64	1	I2	4	1	
MOVD	(x)mm,m32/64	1	LD	2	1	
MOVQ	(x)mm, (x)mm	1	MB	1	1	
MOVQ	(x)mm,m64	1	LD	2	1	
MOVQ	m64, (x)mm	1	SA ST	2	1-2	
MOVDQA	xmm, xmm	1	MB	1	1	
MOVDQA	xmm, m128	1	LD	2	1	
MOVDQA	m128, xmm	1	SA ST	2	1-2	
MOVDQU	m128, xmm	1	SA ST	2	1-2	
MOVDQU	xmm, m128	1	LD	2	1	
LDDQU	xmm, m128	1	LD	2	1	
MOVDQ2Q	mm, xmm	1	MB	1	1	
MOVQ2DQ	xmm,mm	1	MB	1	1	
MOVNTQ	m64,mm	2		~360	2	
MOVNTDQ	m128,xmm	2		~360	2	
MOVNTDQA	xmm,m128	1		2	1	
PACKSSWB/DW PACKUSWB	(x)mm, (x)mm	1	MB	1	1	
PACKUSDW	xmm,xmm	1	MB	1	1	
PUNPCKH/LBW/WD/DQ	(x)mm, (x)mm	1	MB	1	1	
PUNPCKH/LQDQ	(x)mm, (x)mm	1	MB	1	1	
PSHUFB	(x)mm,(x)mm	1	MB	1	1	
PSHUFW	mm,mm,i	1	MB	1	1	
PSHUFL/HW	xmm,xmm,i	1	MB	1	1	
PSHUFD	xmm,xmm,i	1	MB	1	1	
PBLENDVB	x,x,xmm0	1	MB	2	2	
PBLENDW	xmm,xmm,i	1	MB	1	1	
PALIGNR	xmm, xmm,i	1	MB	1	1	
MASKMOVQ	mm,mm				1-2	
MASKMOVDQU	xmm,xmm				1-2	
PMOVMskb	r32,(x)mm			3	1	
PEXTRW	r32 ,(x)mm,i	1	MB	3	1	
PEXTRB/D/Q	r32/64 ,xmm,i	1	MB	3	1	
PINSRW	(x)mm,r32,i	2	MB	5	1	
PINSRB/D/Q	xmm,r32/64,i	2	MB	5	1	
PMOVSX/ZX BW/BD/BQ/WD/WQ/DQ	xmm,xmm	1	MB	1	1	
Arithmetic instructions						
PADD/SUB(U)(S)B/W/D	(x)mm, (x)mm	1	MB	1	1	
PADDQ PSUBQ	(x)mm, (x)mm	1	MB	1	1	
PHADD(S)W PHSUB(S)W	(x)mm, (x)mm	3	MB	3	3	
PHADDD PHSUBD	(x)mm, (x)mm	3	MB	3	3	

PCMPEQ/GTB/W/D	(x)mm,(x)mm	1	MB	1	1	
PCMPEQQ	xmm,xmm	1	MB	1	1	
PMULL/HW PMULHUW	(x)mm,(x)mm	1	MA	3	1	
PMULHRSW	(x)mm,(x)mm	1	MA	3	1	
PMULLD	xmm,xmm	1	MA	3	1	
PMULUDQ	(x)mm,(x)mm	1	MA	3	1	
PMULDQ	xmm,xmm	1	MA	3	1	
PMADDWD	(x)mm,(x)mm	1	MA	4	2	
PMADDUBSW	(x)mm,(x)mm	7		10	8	
PSADBW	(x)mm,(x)mm	1	MB	2	1	
MPSADBW	xmm,xmm,i	1	MB	2	1	
PAVGB/W	(x)mm,(x)mm	1	MB	1	1	
PMIN/MAXSW	(x)mm,(x)mm	1	MB	1	1	
PMIN/MAXUB	(x)mm,(x)mm	1	MB	1	1	
PMIN/MAXSB/D	xmm,xmm	1	MB	1	1	
PMIN/MAXUW/D	xmm,xmm	1	MB	1	1	
PHMINPOSUW	xmm,xmm	1	MB	2	1	
PABSB PABSW PABSD	(x)mm,(x)mm	1	MB	1	1	
PSIGNB PSIGNW PSIGND	(x)mm,(x)mm	1	MB	1	1	
Logic instructions						
PAND(N) POR PXOR	(x)mm,(x)mm	1	MB	1	1	
PTEST	xmm,xmm	1	MB	3	1	
PSLL/RL/RAW/D/Q	(x)mm,(x)mm	1	MB	1	1	
PSLL/RL/RAW/D/Q	(x)xmm,i	1	MB	1	1	
PSLL/RLDQ	xmm,i	1	MB	1	1	
Other						
EMMS		1	MB		1	

12.4 Floating point XMM instructions

Move instructions	Operands	µops	Unit	Latency	Reciprocal throughput	Remarks
MOVAPS/D	xmm,xmm	1	MB	1	1	
MOVAPS/D	xmm,m128	1	LD	2	1	
MOVAPS/D	m128,xmm	1	SA ST	2	1	
MOVUPS/D	xmm,m128	1	LD	2	1	
MOVUPS/D	m128,xmm	2	SA ST	2	1	
MOVSS/D	xmm,xmm	1	MB	1	1	
MOVSS/D	xmm,m32/64	1	LD	2-3	1	
MOVSS/D	m32/64,xmm	2	SA ST	2-3	1-2	
MOVHPS/D	xmm,m64	2		6	1	
MOVLPS/D	xmm,m64	2		6	1	
MOVHPS/D	m64,xmm	3		6	1-2	
MOVLPS/D	m64,xmm	1		2	1-2	
MOVLHPS MOVHLPS	xmm,xmm	1		1	1	
MOVMSKPS/D	r32,xmm			3	1	
MOVNTPS/D	m128,xmm	2		~360	1-2	
SHUFPS	xmm,xmm,i	1	MB	1	1	
SHUFPD	xmm,xmm,i	1	MB	1	1	
MOVDDUP	xmm,xmm	1	MB	1	1	
MOVSH/LDUP	xmm,xmm	1	MB	1	1	
UNPCKH/LPS	xmm,xmm	1	MB	1	1	
UNPCKH/LPD	xmm,xmm	1	MB	1	1	
Conversion						
CVTPD2PS	xmm,xmm	2		5	2	
CVTSD2SS	xmm,xmm	1		2		
CVTPS2PD	xmm,xmm	2		5	1	
CVTSS2SD	xmm,xmm	1		2		
CVTDQ2PS	xmm,xmm	1	MB	3	1	
CVT(T) PS2DQ	xmm,xmm	1		2	1	
CVTDQ2PD	xmm,xmm	2		5	1	
CVT(T)PD2DQ	xmm,xmm			4	2	
CVTPI2PS	xmm,mm	2		5	2	
CVT(T)PS2PI	mm,xmm	1		4	1	
CVTPI2PD	xmm,mm	2		4	1	
CVT(T) PD2PI	mm,xmm	2		4	2	
CVTSI2SS	xmm,r32	2		5		
CVT(T)SS2SI	r32,xmm	1		4	1	
CVTSI2SD	xmm,r32	2		5		
CVT(T)SD2SI	r32,xmm	1		4	1	

Arithmetic						
ADDSS SUBSS	xmm,xmm	1	MBfadd	2	1	
ADDSD SUBSD	xmm,xmm	1	MBfadd	2	1	
ADDPS SUBPS	xmm,xmm	1	MBfadd	2	1	
ADDPD SUBPD	xmm,xmm	1	MBfadd	2	1	
ADDSUBPS	xmm,xmm	1	MBfadd	2	1	
ADDSUBPD	xmm,xmm	1	MBfadd	2	1	
HADDPS HSUBPS	xmm,xmm	3	MBfadd	5	3	
HADDPD HSUBPD	xmm,xmm	3	MBfadd	5	3	
MULSS	xmm,xmm	1	MA	3	1	
MULSD	xmm,xmm	1	MA	4	2	
MULPS	xmm,xmm	1	MA	3	1	
MULPD	xmm,xmm	1	MA	4	2	
DIVSS	xmm,xmm	1	MA	13	13	
DIVSD	xmm,xmm	1	MA	13-20	13-20	
DIVPS	xmm,xmm	1	MA	24	24	
DIVPD	xmm,xmm	1	MA	21-38	21-38	
RCPSS	xmm,xmm	1	MA	5	5	
RCPPS	xmm,xmm	3	MA	14	11	
CMPccSS/D	xmm,xmm	1	MBfadd	2	1	
CMPccPS/D	xmm,xmm	1	MBfadd	2	1	
COMISS/D UCOMISS/D	xmm,xmm	1	MBfadd	3	1	
MAXSS/D MINSS/D	xmm,xmm	1	MBfadd	2	1	
MAXPS/D MINPS/D	xmm,xmm	1	MBfadd	2	1	
Math						
SQRTSS	xmm,xmm	1	MA	33	33	
SQRTPS	xmm,xmm	1	MA	64	64	
SQRTSD	xmm,xmm	1	MA	62	62	
SQRTPD	xmm,xmm	1	MA	122	122	
RSQRTSS	xmm,xmm	1		5	5	
RSQRTPS	xmm,xmm	3		14	11	
Logic						
ANDPS/D	xmm,xmm	1	MB	1	1	
ANDNPS/D	xmm,xmm	1	MB	1	1	
ORPS/D	xmm,xmm	1	MB	1	1	
XORPS/D	xmm,xmm	1	MB	1	1	
Other						
LDMXCSR	m32				31	
STMXCSR	m32				13	
FXSAVE	m4096				97	
FXRSTOR	m4096				201	

12.5 VIA-specific instructions

Instruction	Conditions	Clock cycles, approximately
XSTORE	Data available	160-400 clock giving 8 bytes
XSTORE	No data available	50-80 clock giving 0 bytes
REP XSTORE	Quality factor = 0	1300 clock per 8 bytes
REP XSTORE	Quality factor > 0	5455 clock per 8 bytes
REP XCRYPTECB	128 bits key	15 clock per 16 bytes
REP XCRYPTECB	192 bits key	17 clock per 16 bytes
REP XCRYPTECB	256 bits key	18 clock per 16 bytes
REP XCRYPTCBC	128 bits key	29 clock per 16 bytes
REP XCRYPTCBC	192 bits key	33 clock per 16 bytes
REP XCRYPTCBC	256 bits key	37 clock per 16 bytes
REP XCRYPTCTR	128 bits key	23 clock per 16 bytes
REP XCRYPTCTR	192 bits key	26 clock per 16 bytes
REP XCRYPTCTR	256 bits key	27 clock per 16 bytes
REP XCRYPTCFB	128 bits key	29 clock per 16 bytes
REP XCRYPTCFB	192 bits key	33 clock per 16 bytes
REP XCRYPTCFB	256 bits key	37 clock per 16 bytes
REP XCRYPTOFB	128 bits key	29 clock per 16 bytes
REP XCRYPTOFB	192 bits key	33 clock per 16 bytes
REP XCRYPTOFB	256 bits key	37 clock per 16 bytes
REP XSHA1		5 clock per byte
REP XSHA256		5 clock per byte

13 Instruction timings and macro-operation breakdown for AMD K7

Explanation of column headings:

Instruction: Instruction name. cc means any condition code. For example, Jcc can be JB, JNE, etc.

Operands: i = immediate constant, r = any register, r32 = 32-bit register, etc., mm = 64 bit mmx register, xmm = 128 bit xmm register, sr = segment register, m = any memory operand including indirect operands, m64 means 64-bit memory operand, etc.

Ops: Number of macro-operations issued from instruction decoder to schedulers. Instructions with more than 2 macro-operations are vector-path instructions.

Latency: The number of clock cycles from the execution of an instruction begins to the next dependent instruction can begin. The numbers are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably. Floating point operands are presumed to be normal numbers. Denormal numbers, NAN's, infinity and exceptions increase the delays. The latency listed does not include the memory operand where the operand is listed as register or memory (r/m).

Reciprocal throughput: This is also called issue latency. This value indicates the average number of clock cycles from the execution of an instruction begins to a subsequent independent instruction of the same kind can begin to execute. A value of 1/3 indicates that the execution units can handle 3 instructions per clock cycle in one thread. However, the throughput may be limited by other bottlenecks in the pipeline.

Execution unit: Indicates which execution unit is used for the macro-operations. ALU means any of the three integer ALU's. ALU0_1 means that ALU0 and ALU1 are both used. AGU means any of the three integer address generation units. FADD means floating point adder unit. FMUL means floating point multiplier unit. FMISC means floating point store and miscellaneous unit. F/M means FADD or FMUL is used. FANY means any of the three floating point units can be used. Two macro-operations can execute simultaneously if they go to different execution units.

13.1 Integer instructions

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move instructions						
MOV	r,r	1	1	1/3	ALU	
MOV	r,i	1	1	1/3	ALU	
MOV	r8,m8	1	4	1/2	ALU, AGU	Any addressing mode. Add 1 clock if code
MOV	r16,m16	1	4	1/2	ALU, AGU	

MOV	r32,m32	1	3	1/2	AGU	segment base $\neq 0$
MOV	m8,r8H	1	8	1/2	AGU	AH, BH, CH, DH
MOV	m8,r8L	1	2	1/2	AGU	Any other 8-bit register
MOV	m16/32,r	1	2	1/2	AGU	Any addressing mode
MOV	m,i	1	2	1/2	AGU	
MOV	r,sr	1	2	1		
MOV	sr,r/m	6	9-13	8		
MOVZX, MOVZX	r,r	1	1	1/3	ALU	
MOVZX, MOVZX	r,m	1	4	1/2	ALU, AGU	
CMOVcc	r,r	1	1	1/3	ALU	
CMOVcc	r,m	1		1/2	ALU, AGU	
XCHG	r,r	3	2	1	ALU	
XCHG	r,m	3	16	16	ALU, AGU	Timing depends on hw
XLAT		2	5		ALU, AGU	
PUSH	r	1		1	ALU, AGU	
PUSH	i	1		1	ALU, AGU	
PUSH	m	2		1	ALU, AGU	
PUSH	sr	2		1	ALU, AGU	
PUSHF(D)		1		1	ALU, AGU	
PUSHA(D)		9		4	ALU, AGU	
POP	r	2		1	ALU, AGU	
POP	m	3		1	ALU, AGU	
POP	DS/ES/FS/GS	6		10	ALU, AGU	
POP	SS	9		18	ALU, AGU	
POPF(D)		2		1	ALU, AGU	
POPA(D)		9		4	ALU, AGU	
LEA	r16,[m]	2	3	1	AGU	Any address size
LEA	r32,[m]	1	2	1/3	AGU	Any address size
LAHF		4	3	2	ALU	
SAHF		2	2	2	ALU	
SALC		1	1	1	ALU	
LDS, LES, ...	r,m	10		9		
BSWAP	r	1	1	1/3	ALU	
Arithmetic instructions						
ADD, SUB	r,r/i	1	1	1/3	ALU	
ADD, SUB	r,m	1	1	1/2	ALU, AGU	
ADD, SUB	m,r	1	7	2.5	ALU, AGU	
ADC, SBB	r,r/i	1	1	1/3	ALU	
ADC, SBB	r,m	1	1	1/2	ALU, AGU	
ADC, SBB	m,r/i	1	7	2.5	ALU, AGU	
CMP	r,r/i	1	1	1/3	ALU	
CMP	r,m	1		1/2	ALU, AGU	
INC, DEC, NEG	r	1	1	1/3	ALU	
INC, DEC, NEG	m	1	7	3	ALU, AGU	
AAA, AAS		9	5	5	ALU	
DAA		12	6	6	ALU	
DAS		16	7	7	ALU	
AAD		4	5		ALU0	
AAM		31	13		ALU	
MUL, IMUL	r8/m8	3	3	2	ALU0	
MUL, IMUL	r16/m16	3	3	2	ALU0_1	latency ax=3, dx=4
MUL, IMUL	r32/m32	3	4	3	ALU0_1	
IMUL	r16,r16/m16	2	3	2	ALU0	
IMUL	r32,r32/m32	2	4	2.5	ALU0	
IMUL	r16,(r16),i	2	4	1	ALU0	
IMUL	r32,(r32),i	2	5	2	ALU0	
IMUL	r16,m16,i	3		2	ALU0	
IMUL	r32,m32,i	3		2	ALU0	
DIV	r8/m8	32	24	23	ALU	
DIV	r16/m16	47	24	23	ALU	

DIV	r32/m32	79	40	40	ALU	
IDIV	r8	41	17	17	ALU	
IDIV	r16	56	25	25	ALU	
IDIV	r32	88	41	41	ALU	
IDIV	m8	42	17	17	ALU	
IDIV	m16	57	25	25	ALU	
IDIV	m32	89	41	41	ALU	
CBW, CWDE		1	1	1/3	ALU	
CWD, CDQ		1	1	1/3	ALU	
Logic instructions						
AND, OR, XOR	r,r	1	1	1/3	ALU	
AND, OR, XOR	r,m	1	1	1/2	ALU, AGU	
AND, OR, XOR	m,r	1	7	2.5	ALU, AGU	
TEST	r,r	1	1	1/3	ALU	
TEST	r,m	1	1	1/2	ALU, AGU	
NOT	r	1	1	1/3	ALU	
NOT	m	1	7	2.5	ALU, AGU	
SHL, SHR, SAR	r,i/CL	1	1	1/3	ALU	
ROL, ROR	r,i/CL	1	1	1/3	ALU	
RCL, RCR	r,l	1	1	1/3	ALU	
RCL	r,i	9	4	4	ALU	
RCR	r,i	7	3	3	ALU	
RCL	r,CL	9	3	3	ALU	
RCR	r,CL	7	3	3	ALU	
SHL,SHR,SAR,ROL,ROR	m,i /CL	1	7	3	ALU, AGU	
RCL, RCR	m,l	1	7	4	ALU, AGU	
RCL	m,i	10	5	4	ALU, AGU	
RCR	m,i	9	8	4	ALU, AGU	
RCL	m,CL	9	6	4	ALU, AGU	
RCR	m,CL	8	7	3	ALU, AGU	
SHLD, SHRD	r,r,i	6	4	2	ALU	
SHLD, SHRD	r,r,cl	7	4	3	ALU	
SHLD, SHRD	m,r,i/CL	8	7	3	ALU, AGU	
BT	r,r/i	1	1	1/3	ALU	
BT	m,i	1		1/2	ALU, AGU	
BT	m,r	5		2	ALU, AGU	
BTC, BTR, BTS	r,r/i	2	2	1	ALU	
BTC	m,i	5	7	2	ALU, AGU	
BTR, BTS	m,i	4	7	2	ALU, AGU	
BTC, BTR, BTS	m,r	8	6	3	ALU, AGU	
BSF	r,r	19	7	7	ALU	
BSR	r,r	23	9	9	ALU	
BSF	r,m	20	8	8	ALU, AGU	
BSR	r,m	23	10	10	ALU, AGU	
SETcc	r	1	1	1/3	ALU	
SETcc	m	1		1/2	ALU, AGU	
CLC, STC		1		1/3	ALU	
CMC		1	1	1/3	ALU	
CLD		2		1	ALU	
STD		3		2	ALU	
Control transfer instructions						
JMP	short/near	1		2	ALU	
JMP	far	16-20	23-32			low values = real mode
JMP	r	1		2	ALU	
JMP	m(near)	1		2	ALU, AGU	
JMP	m(far)	17-21	25-33			low values = real mode
Jcc	short/near	1		1/3 - 2	ALU	recip. thrp. = 2 if jump
J(E)CXZ	short	2		1/3 - 2	ALU	recip. thrp. = 2 if jump
LOOP	short	7	3-4	3-4	ALU	

CALL	near	3	2	2	ALU	
CALL	far	16-22	23-32			low values = real mode
CALL	r	4	3	3	ALU	
CALL	m(near)	5	3	3	ALU, AGU	
CALL	m(far)	16-22	24-33			low values = real mode
RETN		2	3	3	ALU	
RETN	i	2	3	3	ALU	
RETF		15-23	24-35			low values = real mode
RETF	i	15-24	24-35			low values = real mode
IRET		32	81			real mode
INT	i	33	42			real mode
BOUND	m	6		2		values are for no jump
INTO		2		2		values are for no jump
String instructions						
LODS		4	2	2		
REP LODS		5	2	2		values are per count
STOS		4	2	2		
REP STOS		3	1	1		values are per count
MOVS		7	3	3		
REP MOVS		4	1-4	1-4		values are per count
SCAS		5	2	2		
REP SCAS		5	2	2		values are per count
CMPS		7	6	6		
REP CMPS		6	3-4	3-4		values are per count
Other						
NOP (90)		1	0	1/3	ALU	
NOP (0F 1F mod000rm)		1	0	1/3	ALU	
ENTER	i,0	12	12	12		
LEAVE		3		3		3 ops, 5 clk if 16 bit
CLI		8-9		5		
STI		16-17		27		
CPUID		19-28	44-74			
RDTSC		5		11		
RDPMSR		9		11		

13.2 Floating point x87 instructions

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move instructions						
FLD	r	1	2	1/2	FA/M	
FLD	m32/64	1	4	1/2	FANY	
FLD	m80	7	16	4		
FBLD	m80	30	41	39		
FST(P)	r	1	2	1/2	FA/M	
FST(P)	m32/64	1	3	1	FMISC	
FSTP	m80	10	7	5		
FBSTP	m80	260		188		
FXCH	r	1	0	0.4		
FILD	m	1	9	1	FMISC	
FIST(P)	m	1	7	1	FMISC, FA/M	
FLDZ, FLD1		1		1	FMISC	
FCMOVcc	st0,r	9	6	5	FMISC, FA/M	Low latency immediately after FCOMI
FFREE	r	1		1/3	FANY	
FINCSTP, FDECSTP		1	0	1/3	FANY	
FNSTSW	AX	2	6-12	12	FMISC, ALU	Low latency immediately after FCOM FTST
FSTSW	AX	3	6-12	12	FMISC, ALU	
FNSTSW	m16	2		8	FMISC, ALU	
FNSTCW	m16	3		1	FMISC, ALU	
FLDCW	m16	14		42	FMISC, ALU	faster if unchanged
Arithmetic instructions						
FADD(P),FSUB(R)(P)	r/m	1	4	1	FADD	
FIADD,FISUB(R)	m	2	4	1-2	FADD,FMISC	
FMUL(P)	r/m	1	4	1	FMUL	
FIMUL	m	2	4	2	FMUL,FMISC	
FDIV(R)(P)	r/m	1	11-25	8-22	FMUL	Low values are for round divisors
FIDIV(R)	m	2	12-26	9-23	FMUL,FMISC	
FABS, FCHS		1	2	1	FMUL	
FCOM(P), FUCOM(P)	r/m	1	2	1	FADD	
FCOMPP, FUCOMPP		1	2	1	FADD	
FCOMI(P)	r	1	3	1	FADD	
FICOM(P)	m	2		1	FADD, FMISC	
FTST		1	2	1	FADD	
FXAM		2		2	FMISC, ALU	
FRNDINT		5	10	3		
FPREM		1	7-10	8	FMUL	
FPREM1		1	8-11	8	FMUL	
Math						
FSQRT		1	35	12	FMUL	
FSIN		44	90-100			
FCOS		51	90-100			
FSINCOS		76	100-150			

FPTAN		46	100-200			
FPATAN		72	160-170			
FSCALE		5	8			
FXTRACT		7	11			
F2XM1		8	27			
FYL2X		49	126			
FYL2XP1		63	147			
Other						
FNOP		1	0	1/3	FANY	
(F)WAIT		1	0	1/3	ALU	
FNCLEX		7		24	FMISC	
FNINIT		25		92	FMISC	
FNSAVE		76		147		
FRSTOR		65		120		
FXSAVE		44		59		
FXRSTOR		85		87		

13.3 Integer MMX instructions

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move instructions						
MOVD	r32, mm	2	7	2	FMICS, ALU	
MOVD	mm, r32	2	9	2	FANY, ALU	
MOVD	mm,m32	1		1/2	FANY	
MOVD	m32, r	1		1	FMISC	
MOVQ	mm,mm	1	2	1/2	FA/M	
MOVQ	mm,m64	1		1/2	FANY	
MOVQ	m64,mm	1		1	FMISC	
MOVNTQ	m,mm	1		2	FMISC	
PACKSSWB/DW PACKUSWB	mm,r/m	1	2	2	FA/M	
PUNPCKH/LBW/WD	mm,r/m	1	2	2	FA/M	
PSHUFW	mm,mm,i	1	2	1/2	FA/M	
MASKMOVQ	mm,mm	32		24		
PMOVMKB	r32,mm	3		3	FADD	
PEXTRW	r32,mm,i	2	5	2	FMISC, ALU	
PINSRW	mm,r32,i	2	12	2	FA/M	
Arithmetic instructions						
PADDB/W/D PADDSB/W ADDUSB/W PSUBB/W/D PSUBSB/W PSUBUSB/W	mm,r/m	1	2	1/2	FA/M	
PCMPEQ/GT B/W/D	mm,r/m	1	2	1/2	FA/M	
PMULLW PMULHW PMULHUW	mm,r/m	1	3	1	FMUL	
PMADDWD	mm,r/m	1	3	1	FMUL	
PAVGB/W	mm,r/m	1	2	1/2	FA/M	
PMIN/MAX SW/UB	mm,r/m	1	2	1/2	FA/M	
PSADBW	mm,r/m	1	3	1	FADD	
Logic						
PAND PANDN POR PXOR	mm,r/m	1	2	1/2	FA/M	
PSLL/RLW/D/Q PSRAW/D	mm,i/mm/m	1	2	1/2	FA/M	
Other						
EMMS		1		1/3	FANY	

13.4 Floating point XMM instructions

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move instructions						
MOVAPS	r,r	2	2	1	FA/M	
MOVAPS	r,m	2		2	FMISC	
MOVAPS	m,r	2		2	FMISC	
MOVUPS	r,r	2	2	1	FA/M	
MOVUPS	r,m	5		2		
MOVUPS	m,r	5		2		
MOVSS	r,r	1	2	1	FA/M	
MOVSS	r,m	2	4	1	FANY FMISC	
MOVSS	m,r	1	3	1	FMISC	
MOVHLPs, MOVLHPS	r,r	1	2	1/2	FA/M	
MOVHPS, MOVLPS	r,m	1		1/2	FMISC	
MOVHPS, MOVLPS	m,r	1		1	FMISC	
MOVNTPS	m,r	2		4	FMISC	
MOVMSKPS	r32,r	3		2	FADD	
SHUFPS	r,r/m,i	3	3	3	FMUL	
UNPCK H/L PS	r,r/m	2	3	3	FMUL	
Conversion						
CVTPI2PS	xmm,mm	1	4		FMISC	
CVT(T)PS2PI	mm,xmm	1	6		FMISC	
CVTSI2SS	xmm,r32	4		10	FMISC	
CVT(T)SS2SI	r32,xmm	2		3	FMISC	
Arithmetic						
ADDSS SUBSS	r,r/m	1	4	1	FADD	
ADDPS SUBPS	r,r/m	2	4	2	FADD	
MULSS	r,r/m	1	4	1	FMUL	
MULPS	r,r/m	2	4	2	FMUL	
DIVSS	r,r/m	1	11-16	8-13	FMUL	Low values are for round divisors, e.g. powers of 2.
DIVPS	r,r/m	2	18-30	18-30	FMUL	
RCPSS	r,r/m	1	3	1	FMUL	
RCPPS	r,r/m	2	3	2	FMUL	
MAXSS MINSS	r,r/m	1	2	1	FADD	
MAXPS MINPS	r,r/m	2	2	2	FADD	
CMPccSS	r,r/m	1	2	1	FADD	
CMPccPS	r,r/m	2	2	2	FADD	
COMISS UCOMISS	r,r/m	1	2	1	FADD	
Logic						
ANDPS/D ANDNPS/D ORPS/D XORPS/D	r,r/m	2	2	2	FMUL	
Math						
SQRTSS	r,r/m	1	19	16	FMUL	

SQRTPS	r,r/m	2	36	36	FMUL	
RSQRTSS	r,r/m	1	3	1	FMUL	
RSQRTPS	r,r/m	2	3	2	FMUL	
Other						
LDMXCSR	m	8		9		
STMXCSR	m	3		10		

13.5 3DNow instructions

These instructions are not available on Intel processors

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move and convert instructions						
PREFETCH(W)	m	1		1/2	AGU	
PF2ID	mm,mm	1	5	1	FMISC	
PI2FD	mm,mm	1	5	1	FMISC	
PF2IW	mm,mm	1	5	1	FMISC	3DNow extension
PI2FW	mm,mm	1	5	1	FMISC	3DNow extension
PSWAPD	mm,mm	1	2	1/2	FA/M	3DNow extension
Integer instructions						
PAVGUSB	mm,mm	1	2	1/2	FA/M	
PMULHRW	mm,mm	1	3	1	FMUL	
Floating point instructions						
PFADD/SUB/SUBR	mm,mm	1	4	1	FADD	
PFCMPEQ/GE/GT	mm,mm	1	2	1	FADD	
PFMAX/MIN	mm,mm	1	2	1	FADD	
PFMUL	mm,mm	1	4	1	FMUL	
PFACC	mm,mm	1	4	1	FADD	
PFNACC, PFPNACC	mm,mm	1	4	1	FADD	3DNow extension
PFRCP	mm,mm	1	3	1	FMUL	
PFRCPIT1/2	mm,mm	1	4	1	FMUL	
PFRSQRT	mm,mm	1	3	1	FMUL	
PFRSQIT1	mm,mm	1	4	1	FMUL	
Other						
FEMMS	mm,mm	1		1/3	FANY	

14 Instruction timings and macro-operation breakdown for AMD K8

Explanation of column headings:

Instruction: Instruction name. cc means any condition code. For example, Jcc can be JB, JNE, etc.

Operands: i = immediate constant, r = any register, r32 = 32-bit register, etc., mm = 64 bit mmx register, xmm = 128 bit xmm register, sr = segment register, m = any memory operand including indirect operands, m64 means 64-bit memory operand, etc.

Ops: Number of macro-operations issued from instruction decoder to schedulers. Instructions with more than 2 macro-operations are vector-path instructions.

Latency: The number of clock cycles from the execution of an instruction begins to the next dependent instruction can begin. The numbers are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably. Floating point operands are presumed to be normal numbers. Denormal numbers, NAN's, infinity and exceptions increase the delays. The latency listed does not include the memory operand where the operand is listed as register or memory (r/m).

Reciprocal throughput: This is also called issue latency. This value indicates the average number of clock cycles from the execution of an instruction begins to a subsequent independent instruction of the same kind can begin to execute. A value of 1/3 indicates that the execution units can handle 3 instructions per clock cycle in one thread. However, the throughput may be limited by other bottlenecks in the pipeline.

Execution unit: Indicates which execution unit is used for the macro-operations. ALU means any of the three integer ALU's. ALU0_1 means that ALU0 and ALU1 are both used. AGU means any of the three integer address generation units. FADD means floating point adder unit. FMUL means floating point multiplier unit. FMISC means floating point store and miscellaneous unit. F/M means FADD or FMUL is used. FANY means any of the three floating point units can be used. Two macro-operations can execute simultaneously if they go to different execution units.

14.1 Integer instructions

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move instructions						
MOV	r,r	1	1	1/3	ALU	
MOV	r,i	1	1	1/3	ALU	
MOV	r8,m8	1	4	1/2	ALU, AGU	Any addressing mode. Add 1 clock if code
MOV	r16,m16	1	4	1/2	ALU, AGU	

MOV	r32,m32	1	3	1/2	AGU	segment base $\neq 0$
MOV	r64,m64	1	3	1/2	AGU	
MOV	m8,r8H	1	8	1/2	AGU	AH, BH, CH, DH
MOV	m8,r8L	1	3	1/2	AGU	Any other 8-bit register
MOV	m16/32/64,r	1	3	1/2	AGU	Any addressing mode
MOV	m,i	1	3	1/2	AGU	
MOV	m64,i32	1	3	1/2	AGU	
MOV	r,sr	1	2	1/2-1		
MOV	sr,r/m	6	9-13	8		
MOVNTI	m,r	1		2-3	AGU	
MOVZX, MOVZX	r,r	1	1	1/3	ALU	
MOVZX, MOVZX	r,m	1	4	1/2	ALU, AGU	
MOVSXD	r64,r32	1	1	1/3	ALU	
MOVSXD	r64,m32	1		1/2	ALU, AGU	
CMOVcc	r,r	1	1	1/3	ALU	
CMOVcc	r,m	1		1/2	ALU, AGU	
XCHG	r,r	3	2	1	ALU	
XCHG	r,m	3	16	16	ALU, AGU	Timing depends on hw
XLAT		2	5		ALU, AGU	
PUSH	r	1	1	1	ALU, AGU	
PUSH	i	1	1	1	ALU, AGU	
PUSH	m	2	1	1	ALU, AGU	
PUSH	sr	2	1	1	ALU, AGU	
PUSHF(D/Q)		5	2	2	ALU, AGU	
PUSHA(D)		9	4	4	ALU, AGU	
POP	r	2	1	1	ALU, AGU	
POP	m	3	1	1	ALU, AGU	
POP	DS/ES/FS/GS	4-6	8	8	ALU, AGU	
POP	SS	7-9	28	28	ALU, AGU	
POPF(D/Q)		25	10	10	ALU, AGU	
POPA(D)		9	4	4	ALU, AGU	
LEA	r16,[m]	2	3	1	AGU	Any address size
LEA	r32,[m]	1	2	1/3	AGU	Any address size
LEA	r64,[m]	1	2	1/3	AGU	Any address size
LAHF		4	3	2	ALU	
SAHF		1	1	1/3	ALU	
SALC		1	1	1/3	ALU	
LDS, LES, ...	r,m	10		9		
BSWAP	r	1	1	1/3	ALU	
PREFETCHCNTA	m	1		1/2	AGU	
PREFETCHT0/1/2	m	1		1/2	AGU	
SFENCE		6		8		
LFENCE		1		5		
MFENCE		7		16		
IN	r,i/DX	270				
OUT	i/DX,r	300				
Arithmetic instructions						
ADD, SUB	r,r/i	1	1	1/3	ALU	
ADD, SUB	r,m	1	1	1/2	ALU, AGU	
ADD, SUB	m,r	1	7	2.5	ALU, AGU	
ADC, SBB	r,r/i	1	1	1/3	ALU	
ADC, SBB	r,m	1	1	1/2	ALU, AGU	
ADC, SBB	m,r/i	1	7	2.5	ALU, AGU	
CMP	r,r/i	1	1	1/3	ALU	
CMP	r,m	1		1/2	ALU, AGU	
INC, DEC, NEG	r	1	1	1/3	ALU	
INC, DEC, NEG	m	1	7	3	ALU, AGU	
AAA, AAS		9	5	5	ALU	
DAA		12	6	6	ALU	
DAS		16	7	7	ALU	

AAD		4	5		ALU0	
AAM		31	13		ALU	
MUL, IMUL	r8/m8	1	3	1	ALU0	
MUL, IMUL	r16/m16	3	3-4	2	ALU0_1	latency ax=3, dx=4
MUL, IMUL	r32/m32	2	3	1	ALU0_1	
MUL, IMUL	r64/m64	2	4-5	2	ALU0_1	latency rax=4, rdx=5
IMUL	r16,r16/m16	1	3	1	ALU0	
IMUL	r32,r32/m32	1	3	1	ALU0	
IMUL	r64,r64/m64	1	4	2	ALU0_1	
IMUL	r16,(r16),i	2	4	1	ALU0	
IMUL	r32,(r32),i	1	3	1	ALU0	
IMUL	r64,(r64),i	1	4	2	ALU0	
IMUL	r16,m16,i	3		2	ALU0	
IMUL	r32,m32,i	3		2	ALU0	
IMUL	r64,m64,i	3		2	ALU0_1	
DIV	r8/m8	31	15	15	ALU	
DIV	r16/m16	46	23	23	ALU	
DIV	r32/m32	78	39	39	ALU	
DIV	r64/m64	143	71	71	ALU	
IDIV	r8	40	17	17	ALU	
IDIV	r16	55	25	25	ALU	
IDIV	r32	87	41	41	ALU	
IDIV	r64	152	73	73	ALU	
IDIV	m8	41	17	17	ALU	
IDIV	m16	56	25	25	ALU	
IDIV	m32	88	41	41	ALU	
IDIV	m64	153	73	73	ALU	
CBW, CWDE, CDQE		1	1	1/3	ALU	
CWD, CDQ, CQO		1	1	1/3	ALU	
Logic instructions						
AND, OR, XOR	r,r	1	1	1/3	ALU	
AND, OR, XOR	r,m	1	1	1/2	ALU, AGU	
AND, OR, XOR	m,r	1	7	2.5	ALU, AGU	
TEST	r,r	1	1	1/3	ALU	
TEST	r,m	1	1	1/2	ALU, AGU	
NOT	r	1	1	1/3	ALU	
NOT	m	1	7	2.5	ALU, AGU	
SHL, SHR, SAR	r,i/CL	1	1	1/3	ALU	
ROL, ROR	r,i/CL	1	1	1/3	ALU	
RCL, RCR	r,l	1	1	1/3	ALU	
RCL	r,i	9	3	3	ALU	
RCR	r,i	7	3	3	ALU	
RCL	r,CL	9	4	4	ALU	
RCR	r,CL	7	3	3	ALU	
SHL,SHR,SAR,ROL,ROR	m,i /CL	1	7	3	ALU, AGU	
RCL, RCR	m,l	1	7	4	ALU, AGU	
RCL	m,i	10	9	4	ALU, AGU	
RCR	m,i	9	8	4	ALU, AGU	
RCL	m,CL	9	7	4	ALU, AGU	
RCR	m,CL	8	8	3	ALU, AGU	
SHLD, SHRD	r,r,i	6	3	3	ALU	
SHLD, SHRD	r,r,cl	7	3	3	ALU	
SHLD, SHRD	m,r,i/CL	8	6	3	ALU, AGU	
BT	r,r/i	1	1	1/3	ALU	
BT	m,i	1		1/2	ALU, AGU	
BT	m,r	5		2	ALU, AGU	
BTC, BTR, BTS	r,r/i	2	2	1	ALU	
BTC	m,i	5	7	2	ALU, AGU	
BTR, BTS	m,i	4	7	2	ALU, AGU	
BTC	m,r	8	5	5	ALU, AGU	

BTR, BTS	m,r	8	8	3	ALU, AGU	
BSF	r16/32,r	21	8	8	ALU	
BSF	r64,r	22	9	9	ALU	
BSR	r,r	28	10	10	ALU	
BSF	r16,m	20	8	8	ALU, AGU	
BSF	r32,m	22	9	9	ALU, AGU	
BSF	r64,m	25	10	10	ALU, AGU	
BSR	r,m	28	10	10	ALU, AGU	
SETcc	r	1	1	1/3	ALU	
SETcc	m	1		1/2	ALU, AGU	
CLC, STC		1		1/3	ALU	
CMC		1	1	1/3	ALU	
CLD		1		1/3	ALU	
STD		2		1/3	ALU	
Control transfer instructions						
JMP	short/near	1		2	ALU	
JMP	far	16-20	23-32			low values = real mode
JMP	r	1		2	ALU	
JMP	m(near)	1		2	ALU, AGU	
JMP	m(far)	17-21	25-33			low values = real mode
Jcc	short/near	1		1/3 - 2	ALU	recip. thrp.= 2 if jump
J(E/R)CXZ	short	2		1/3 - 2	ALU	recip. thrp.= 2 if jump
LOOP	short	7	3-4	3-4	ALU	
CALL	near	3	2	2	ALU	
CALL	far	16-22	23-32			low values = real mode
CALL	r	4	3	3	ALU	
CALL	m(near)	5	3	3	ALU, AGU	
CALL	m(far)	16-22	24-33			low values = real mode
RETN		2	3	3	ALU	
RETN	i	2	3	3	ALU	
RETF		15-23	24-35			low values = real mode
RETF	i	15-24	24-35			low values = real mode
IRET		32	81			real mode
INT	i	33	42			real mode
BOUND	m	6		2		values are for no jump
INTO		2		2		values are for no jump
String instructions						
LODS		4	2	2		
REP LODS		5	2	2		values are per count
STOS		4	2	2		
REP STOS		1.5 - 2	0.5 - 1	0.5 - 1		values are per count
MOVS		7	3	3		
REP MOVS		3	1-2	1-2		values are per count
SCAS		5	2	2		
REP SCAS		5	2	2		values are per count
CMPS		2	3	3		
REP CMPS		6	2	2		values are per count
Other						
NOP (90)		1	0	1/3	ALU	
NOP (0F 1F mod000rm)		1	0	1/3	ALU	
ENTER	i,0	12	12	12		
LEAVE		2		3		3 ops, 5 clk if 16 bit
CLI		8-9		5		
STI		16-17		27		
CPUID		22-50	47-164			
RDTSC		6	10	7		
RDPMC		9	12	7		

14.2 Floating point x87 instructions

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move instructions						
FLD	r	1	2	1/2	FA/M	
FLD	m32/64	1	4	1/2	FANY	
FLD	m80	7	16	4		
FBLD	m80	30	41	39		
FST(P)	r	1	2	1/2	FA/M	
FST(P)	m32/64	1	3	1	FMISC	
FSTP	m80	10	7	5		
FBSTP	m80	260	173	160		
FXCH	r	1	0	0.4		
FILD	m	1	9	1	FMISC	
FIST(P)	m	1	7	1	FMISC, FA/M	
FLDZ, FLD1		1		1	FMISC	
FCMOVcc	st0,r	9	4-15	4	FMISC, FA/M	Low latency immediately after FCOMI
FFREE	r	1		2	FANY	
FINCSTP, FDECSTP		1	0	1/3	FANY	
FNSTSW	AX	2	6-12	12	FMISC, ALU	Low latency immediately after FCOM FTST
FSTSW	AX	3	6-12	12	FMISC, ALU	
FNSTSW	m16	2		8	FMISC, ALU	
FNSTCW	m16	3		1	FMISC, ALU	
FLDCW	m16	18		50	FMISC, ALU	faster if unchanged
Arithmetic instructions						
FADD(P),FSUB(R)(P)	r/m	1	4	1	FADD	
FIADD,FISUB(R)	m	2	4	1-2	FADD,FMISC	
FMUL(P)	r/m	1	4	1	FMUL	
FIMUL	m	2	4	2	FMUL,FMISC	
FDIV(R)(P)	r/m	1	11-25	8-22	FMUL	Low values are for round divisors
FIDIV(R)	m	2	12-26	9-23	FMUL,FMISC	
FABS, FCHS		1	2	1	FMUL	
FCOM(P), FUCOM(P)	r/m	1	2	1	FADD	
FCOMPP, FUCOMPP		1	2	1	FADD	
FCOMI(P)	r	1	3	1	FADD	
FICOM(P)	m	2		1	FADD, FMISC	
FTST		1	2	1	FADD	
FXAM		2		1	FMISC, ALU	
FRNDINT		5	10	3		
FPREM		1	7-10	8	FMUL	
FPREM1		1	8-11	8	FMUL	
Math						
FSQRT		1	27	12	FMUL	
FLDPI, etc.		1		1	FMISC	
FSIN		66	140-190			
FCOS		73	150-190			

FSINCOS		98	170-200			
FPTAN		67	150-180			
FPATAN		97	217			
FSCALE		5	8			
FXTRACT		7	12	7		
F2XM1		53	126			
FYL2X		72	179			
FYL2XP1		75	175			
Other						
FNOP		1	0	1/3	FANY	
(F)WAIT		1	0	1/3	ALU	
FNCLEX		8		27	FMISC	
FNINIT		26		100	FMISC	
FNSAVE		77		171		
FRSTOR		70		136		
FXSAVE		61		56		
FXRSTOR		101		95		

14.3 Integer MMX and XMM instructions

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move instructions						
MOVD	r32, mm	2	4	2	FMISC, ALU	
MOVD	mm, r32	2	9	2	FANY, ALU	
MOVD	mm, m32	1		1/2	FANY	
MOVD	r32, xmm	3	2	2	FMISC, ALU	
MOVD	xmm, r32	3	3	2		
MOVD	xmm, m32	2		1	FANY	
MOVD	m32, r	1		1	FMISC	
MOVD (MOVQ)	r64, mm/xmm	2	4	2	FMISC, ALU	Moves 64 bits. Name of instruction differs
MOVD (MOVQ)	mm, r64	2	9	2	FANY, ALU	
MOVD (MOVQ)	xmm, r64	3	9	2	FANY, ALU	
MOVQ	mm, mm	1	2	1/2	FA/M	
MOVQ	xmm, xmm	2	2	1	FA/M, FMISC	
MOVQ	mm, m64	1		1/2	FANY	
MOVQ	xmm, m64	2		1	FANY, FMISC	
MOVQ	m64, mm/xmm	1		1	FMISC	
MOVDQA	xmm, xmm	2	2	1	FA/M	
MOVDQA	xmm, m	2		2	FMISC	
MOVDQA	m, xmm	2		2	FMISC	
MOVDQU	xmm, m	4		2		
MOVDQU	m, xmm	5		2		
MOVDQ2Q	mm, xmm	1	2	1/2	FA/M	
MOVQ2DQ	xmm, mm	2	2	1	FA/M, FMISC	
MOVNTQ	m, mm	1		2	FMISC	
MOVNTDQ	m, xmm	2		3	FMISC	
PACKSSWB/DW PACKUSWB	mm, r/m	1	2	2	FA/M	
PACKSSWB/DW PACKUSWB	xmm, r/m	3	3	2	FA/M	
PUNPCKH/LBW/WD/DQ	mm, r/m	1	2	2	FA/M	
PUNPCKH/LBW/WD/DQ	xmm, r/m	2	2	2	FA/M	
PUNPCKHQDQ	xmm, r/m	2	2	1	FA/M	
PUNPCKLQDQ	xmm, r/m	1	2	1/2	FA/M	
PSHUFD	xmm, xmm, i	3	3	1.5	FA/M	
PSHUFW	mm, mm, i	1	2	1/2	FA/M	
PSHUFL/HW	xmm, xmm, i	2	2	1	FA/M	
MASKMOVQ	mm, mm	32		13		
MASKMOVDQU	xmm, xmm	64		26		
PMOVBMSKB	r32, mm/xmm	1	2	1	FADD	
PEXTRW	r32, mm/xmm, i	2	5	2	FMISC, ALU	
PINSRW	mm, r32, i	2	12	2	FA/M	
PINSRW	xmm, r32, i	3	12	3	FA/M	
Arithmetic instructions						
PADDB/W/D/Q PADDSB/W ADDUSB/W PSUBB/W/D/Q PSUBSB/W PSUBUSB/W	mm, r/m	1	2	1/2	FA/M	

PADDB/W/D/Q PADDSB/W ADDUSB/W PSUBB/W/D/Q PSUBSB/W PSUBUSB/W	xmm,r/m	2	2	1	FA/M	
PCMPEQ/GT B/W/D	mm,r/m	1	2	1/2	FA/M	
PCMPEQ/GT B/W/D	xmm,r/m	2	2	1	FA/M	
PMULLW PMULHW PMULHUW PMULUDQ	mm,r/m	1	3	1	FMUL	
PMULLW PMULHW PMULHUW PMULUDQ	xmm,r/m	2	3	2	FMUL	
PMADDWD	mm,r/m	1	3	1	FMUL	
PMADDWD	xmm,r/m	2	3	2	FMUL	
PAVGB/W	mm,r/m	1	2	1/2	FA/M	
PAVGB/W	xmm,r/m	2	2	1	FA/M	
PMIN/MAX SW/UB	mm,r/m	1	2	1/2	FA/M	
PMIN/MAX SW/UB	xmm,r/m	2	2	1	FA/M	
PSADBW	mm,r/m	1	3	1	FADD	
PSADBW	xmm,r/m	2	3	2	FADD	
Logic						
PAND PANDN POR PXOR	mm,r/m	1	2	1/2	FA/M	
PAND PANDN POR PXOR	xmm,r/m	2	2	1	FA/M	
PSLL/RL W/D/Q PSRAW/D	mm,i/mm/m	1	2	1/2	FA/M	
PSLL/RL W/D/Q PSRAW/D	xmm,i/xmm/m	2	2	1	FA/M	
PSLLDQ, PSRLDQ	xmm,i	2	2	1	FA/M	
Other						
EMMS		1		1/3	FANY	

14.4 Floating point XMM instructions

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move instructions						
MOVAPS/D	r,r	2	2	1	FA/M	
MOVAPS/D	r,m	2		2	FMISC	
MOVAPS/D	m,r	2		2	FMISC	
MOVUPS/D	r,r	2	2	1	FA/M	
MOVUPS/D	r,m	4		2		
MOVUPS/D	m,r	5		2		
MOVSS/D	r,r	1	2	1	FA/M	
MOVSS/D	r,m	2	4	1	FANY FMISC	
MOVSS/D	m,r	1	3	1	FMISC	
MOVHLPs, MOVLHPS	r,r	1	2	1/2	FA/M	
MOVHPS/D, MOVLPS/D	r,m	1		1	FMISC	
MOVHPS/D, MOVLPS/D	m,r	1		1	FMISC	
MOVDDUP g)	r,r	2	2	1		
MOVSH/LDUP g)	r,r	2	2	2		
MOVNTPS/D	m,r	2		3	FMISC	
MOVMSKPS/D	r32,r	1	8	1	FADD	
SHUFPS/D	r,r/m,i	3	3	2	FMUL	
UNPCK H/L PS/D	r,r/m	2	3	3	FMUL	
Conversion						
CVTQPS2PD	r,r/m	2	4	2	FMISC	
CVTPD2PS	r,r/m	4	8	3	FMISC	
CVTSD2SS	r,r/m	3	8	8	FMISC	
CVTSS2SD	r,r/m	1	2	1	FMISC	
CVTDQ2PS	r,r/m	2	5	2	FMISC	
CVTDQ2PD	r,r/m	2	5	2	FMISC	
CVT(T)PS2DQ	r,r/m	2	5	2	FMISC	
CVT(T)PD2DQ	r,r/m	4	8	3	FMISC	
CVTPi2PS	xmm,mm	1	4	1	FMISC	
CVTPi2PD	xmm,mm	2	5	2	FMISC	
CVT(T)PS2Pi	mm,xmm	1	6	1	FMISC	
CVT(T)PD2Pi	mm,xmm	3	8	2	FMISC	
CVTSi2SS	xmm,r32	3	14	2	FMISC	
CVTSi2SD	xmm,r32	2	12	2	FMISC	
CVT(T)SD2Si	r32,xmm	2	10	2	FMISC	
CVT(T)SS2Si	r32,xmm	2	9	2	FMISC	
Arithmetic						
ADDSS/D SUBSS/D	r,r/m	1	4	1	FADD	
ADDPS/D SUBPS/D	r,r/m	2	4	2	FADD	
HADDPS/D HSUBPS/D g)	r,r/m	2	4	2	FADD	
MULSS/D	r,r/m	1	4	1	FMUL	
MULPS/D	r,r/m	2	4	2	FMUL	
DIVSS	r,r/m	1	11-16	8-13	FMUL	Low values are for round divisors, e.g.
DIVPS	r,r/m	2	18-30	18-30	FMUL	

DIVSD	r,r/m	1	11-20	8-17	FMUL	powers of 2.
DIVPD	r,r/m	2	16-34	16-34	FMUL	
RCPSS	r,r/m	1	3	1	FMUL	
RCPPS	r,r/m	2	3	2	FMUL	
MAXSS/D MINSS/D	r,r/m	1	2	1	FADD	
MAXPS/D MINPS/D	r,r/m	2	2	2	FADD	
CMPccSS/D	r,r/m	1	2	1	FADD	
CMPccPS/D	r,r/m	2	2	2	FADD	
COMISS/D UCOMISS/D	r,r/m	1	2	1	FADD	
Logic						
ANDPS/D ANDNPS/D ORPS/D XORPS/D	r,r/m	2	2	2	FMUL	
Math						
SQRTSS	r,r/m	1	19	16	FMUL	
SQRTPS	r,r/m	2	36	36	FMUL	
SQRTSD	r,r/m	1	27	24	FMUL	
SQRTPD	r,r/m	2	48	48	FMUL	
RSQRTSS	r,r/m	1	3	1	FMUL	
RSQRTPS	r,r/m	2	3	2	FMUL	
Other						
LDMXCSR	m	8		9		
STMXCSR	m	3		10		

g) SSE3 instruction set.

14.5 3DNow instructions

These instructions are not available on Intel processors

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move and convert instructions						
PREFETCH(W)	m	1		1/2	AGU	
PF2ID	mm,mm	1	5	1	FMISC	
PI2FD	mm,mm	1	5	1	FMISC	
PF2IW	mm,mm	1	5	1	FMISC	3DNow extension
PI2FW	mm,mm	1	5	1	FMISC	3DNow extension
PSWAPD	mm,mm	1	2	1/2	FA/M	3DNow extension
Integer instructions						
PAVGUSB	mm,mm	1	2	1/2	FA/M	
PMULHRW	mm,mm	1	3	1	FMUL	
Floating point instructions						
PFADD/SUB/SUBR	mm,mm	1	4	1	FADD	
PFCMPEQ/GE/GT	mm,mm	1	2	1	FADD	
PFPMAX/MIN	mm,mm	1	2	1	FADD	
PFMUL	mm,mm	1	4	1	FMUL	
PFACC	mm,mm	1	4	1	FADD	

PFNACC, PFPNACC	mm,mm	1	4	1	FADD	3DNow extension
PFRCP	mm,mm	1	3	1	FMUL	
PFRCPIT1/2	mm,mm	1	4	1	FMUL	
PFRSQRT	mm,mm	1	3	1	FMUL	
PFRSQIT1	mm,mm	1	4	1	FMUL	
Other						
FEMMS	mm,mm	1		1/3	FANY	

15 Instruction timings and macro-operation breakdown for AMD K10

Explanation of column headings:

Instruction: Instruction name. cc means any condition code. For example, Jcc can be JB, JNE, etc.

Operands: i = immediate constant, r = any register, r32 = 32-bit register, etc., mm = 64 bit mmx register, xmm = 128 bit xmm register, sr = segment register, m = any memory operand including indirect operands, m64 means 64-bit memory operand, etc.

Ops: Number of macro-operations issued from instruction decoder to schedulers. Instructions with more than 2 macro-operations are vector-path instructions.

Latency: The number of clock cycles from the execution of an instruction begins to the next dependent instruction can begin. The numbers are minimum values. Cache misses, misalignment, and exceptions may increase the clock counts considerably. Floating point operands are presumed to be normal numbers. Denormal numbers, NAN's, infinity and exceptions increase the delays. The latency listed does not include the memory operand where the operand is listed as register or memory (r/m).

Reciprocal throughput: This is also called issue latency. This value indicates the average number of clock cycles from the execution of an instruction begins to a subsequent independent instruction of the same kind can begin to execute. A value of 1/3 indicates that the execution units can handle 3 instructions per clock cycle in one thread. However, the throughput may be limited by other bottlenecks in the pipeline.

Execution unit: Indicates which execution unit is used for the macro-operations. ALU means any of the three integer ALU's. ALU0_1 means that ALU0 and ALU1 are both used. AGU means any of the three integer address generation units. FADD means floating point adder unit. FMUL means floating point multiplier unit. FMISC means floating point store and miscellaneous unit. FA/M means FADD or FMUL is used. FANY means any of the three floating point units can be used. Two macro-operations can execute simultaneously if they go to different execution units.

Thank you to Xucheng Tang for doing the measurements on the K10.

15.1 Integer instructions

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move instructions						
MOV	r,r	1	1	1/3	ALU	
MOV	r,i	1	1	1/3	ALU	
MOV	r8,m8	1	4	1/2	ALU, AGU	Any addressing mode.

MOV	r16,m16	1	4	1/2	ALU, AGU	Add 1 clock if code segment base $\neq 0$
MOV	r32,m32	1	3	1/2	AGU	
MOV	r64,m64	1	3	1/2	AGU	
MOV	m8,r8H	1	?	1/2	AGU	AH, BH, CH, DH
MOV	m8,r8L	1	3	1/2	AGU	Any other 8-bit register
MOV	m16/32/64,r	1	3	1/2	AGU	Any addressing mode
MOV	m,i	1	3	1/2	AGU	
MOV	m64,i32	1	3	1/2	AGU	
MOV	r,sr	1	3-4	1/2		
MOV	sr,r/m	6	8-26	8		from AMD manual
MOVNTI	m,r	1		1	AGU	
MOVZX, MOVSX	r,r	1	1	1/3	ALU	
MOVZX, MOVSX	r,m	1	4	1/2	ALU, AGU	
MOVSXD	r64,r32	1	1	1/3	ALU	
MOVSXD	r64,m32	1	4	1/2	ALU, AGU	
CMOVcc	r,r	1	1	1/3	ALU	
CMOVcc	r,m	1	4	1/2	ALU, AGU	
XCHG	r,r	2	1	1	ALU	
XCHG	r,m	2	21	19	ALU, AGU	Timing depends on hw
XLAT		2	5	5	ALU, AGU	
PUSH	r	1		1/2	ALU, AGU	
PUSH	i	1		1/2	ALU, AGU	
PUSH	m	2		1	ALU, AGU	
PUSH	sr	2		1	ALU, AGU	
PUSHF(D/Q)		9		3	ALU, AGU	
PUSHA(D)		9	6	6	ALU, AGU	
POP	r	1		1/2	ALU, AGU	
POP	m	3	3	1	ALU, AGU	
POP	DS/ES/FS/GS	6	10	8	ALU, AGU	
POP	SS	10	26	16	ALU, AGU	
POPF(D/Q)		28	16	11	ALU, AGU	
POPA(D)		9	6	6	ALU, AGU	
LEA	r16,[m]	2	3	1	ALU, AGU	Any address size
LEA	r32/64,[m]	1	1	1/3	ALU	≤ 2 source operands
LEA	r32/64,[m]	1	2	1/3	AGU	W. scale or 3 operands
LAHF		4	3	2	ALU	
SAHF		1	1	1/3	ALU	
SALC		1	1	1	ALU	
LDS, LES, ...	r,m	10		10		
BSWAP	r	1	1	1/3	ALU	
PREFETCHCNTA	m	1		1/2	AGU	
PREFETCHT0/1/2	m	1		1/2	AGU	
SFENCE		6		8		
LFENCE		1		1		
MFENCE		4		33		
IN	r,i/DX	~270				
OUT	i/DX,r	~300				
Arithmetic instructions						
ADD, SUB	r,r/i	1	1	1/3	ALU	
ADD, SUB	r,m	1		1/2	ALU, AGU	
ADD, SUB	m,r	1	4	1	ALU, AGU	
ADC, SBB	r,r/i	1	1	1/3	ALU	
ADC, SBB	r,m	1		1/2	ALU, AGU	
ADC, SBB	m,r/i	1	4	1	ALU, AGU	
CMP	r,r/i	1	1	1/3	ALU	
CMP	r,m	1		1/2	ALU, AGU	
INC, DEC, NEG	r	1	1	1/3	ALU	
INC, DEC, NEG	m	1	7	2	ALU, AGU	
AAA, AAS		9	5	5	ALU	
DAA		12	6	6	ALU	

DAS		16	7	7	ALU	
AAD		4	5	5	ALU0	
AAM		30	13	13	ALU	
MUL, IMUL	r8/m8	1	3	1	ALU0	
MUL, IMUL	r16/m16	3	3	2	ALU0_1	latency ax=3, dx=4
MUL, IMUL	r32/m32	2	3	1	ALU0_1	
MUL, IMUL	r64/m64	2	4	2	ALU0_1	latency rax=4, rdx=5
IMUL	r16,r16/m16	1	3	1	ALU0	
IMUL	r32,r32/m32	1	3	1	ALU0	
IMUL	r64,r64/m64	1	4	2	ALU0_1	
IMUL	r16,(r16),i	2	4	1	ALU0	
IMUL	r32,(r32),i	1	3	1	ALU0	
IMUL	r64,(r64),i	1	4	2	ALU0	
IMUL	r16,m16,i	3		2	ALU0	
IMUL	r32,m32,i	3		2	ALU0	
IMUL	r64,m64,i	3		2	ALU0_1	
DIV	r8/m8		17	17	ALU	
IDIV	r8		19	19	ALU	
IDIV	m8		22	22	ALU	
DIV	r16/m16		15-30	15-30	ALU	Depends on number of significant bits in absolute value of dividend. See AMD software optimization guide.
DIV	r32/m32		15-46	15-46	ALU	
DIV	r64/m64		15-78	15-78	ALU	
IDIV	r16/m16		24-39	24-39	ALU	
IDIV	r32/m32		24-55	24-55	ALU	
IDIV	r64/m64		24-87	24-87	ALU	
CBW, CWDE, CDQE		1	1	1/3	ALU	
CWD, CDQ, CQO		1	1	1/3	ALU	
Logic instructions						
AND, OR, XOR	r,r	1	1	1/3	ALU	
AND, OR, XOR	r,m	1		1/2	ALU, AGU	
AND, OR, XOR	m,r	1	4	1	ALU, AGU	
TEST	r,r	1	1	1/3	ALU	
TEST	r,m	1		1/2	ALU, AGU	
NOT	r	1	1	1/3	ALU	
NOT	m	1	7	1	ALU, AGU	
SHL, SHR, SAR	r,i/CL	1	1	1/3	ALU	
ROL, ROR	r,i/CL	1	1	1/3	ALU	
RCL, RCR	r,l	1	1	1	ALU	
RCL	r,i	9	3	3	ALU	
RCR	r,i	7	3	3	ALU	
RCL	r,CL	9	4	4	ALU	
RCR	r,CL	7	3	3	ALU	
SHL,SHR,SAR,ROL,ROR	m,i /CL	1	7	1	ALU, AGU	
RCL, RCR	m,l	1	7	1	ALU, AGU	
RCL	m,i	10	7	5	ALU, AGU	
RCR	m,i	9	7	6	ALU, AGU	
RCL	m,CL	9	8	6	ALU, AGU	
RCR	m,CL	8	7	5	ALU, AGU	
SHLD, SHRD	r,r,i	6	3	2	ALU	
SHLD, SHRD	r,r,cl	7	3	3	ALU	
SHLD, SHRD	m,r,i/CL	8	7.5	6	ALU, AGU	
BT	r,r/i	1	1	1/3	ALU	
BT	m,i	1		1/2	ALU, AGU	
BT	m,r	5	7	2	ALU, AGU	
BTC, BTR, BTS	r,r/i	2	2	1/3	ALU	
BTC	m,i	5	9	1.5	ALU, AGU	
BTR, BTS	m,i	4	9	1.5	ALU, AGU	
BTC	m,r	8	8	10	ALU, AGU	
BTR, BTS	m,r	8	8	7	ALU, AGU	
BSF	r,r	6	4	3	ALU	

BSR	r,r	7	4	3	ALU	
BSF	r,m	7	7	3	ALU, AGU	
BSR	r,m	8	7	3	ALU, AGU	
POPCNT	r,r/m	1	2	1	ALU	SSE4.A/SSE4.2
LZCNT	r,r/m	1	2	1	ALU	SSE4.A, AMD only
SETcc	r	1	1	1/3	ALU	
SETcc	m	1		1/2	ALU, AGU	
CLC, STC		1		1/3	ALU	
CMC		1	1	1/3	ALU	
CLD		1		1/3	ALU	
STD		2		2/3	ALU	
Control transfer instructions						
JMP	short/near	1		2	ALU	
JMP	far	16-20	23-32			low values = real mode
JMP	r	1		2	ALU	
JMP	m(near)	1		2	ALU, AGU	
JMP	m(far)	17-21	25-33			low values = real mode
Jcc	short/near	1		1/3 - 2	ALU	recip. thrp. = 2 if jump
J(E/R)CXZ	short	2		2/3 - 2	ALU	recip. thrp. = 2 if jump
LOOP	short	7		3	ALU	
CALL	near	3	2	2	ALU	
CALL	far	16-22	23-32			low values = real mode
CALL	r	4	3	3	ALU	
CALL	m(near)	5	3	3	ALU, AGU	
CALL	m(far)	16-22	24-33			low values = real mode
RETN		2	3	3	ALU	
RETN	i	2	3	3	ALU	
RETF		15-23	24-35			low values = real mode
RETF	i	15-24	24-35			low values = real mode
IRET		32	81			real mode
INT	i	33	42			real mode
BOUND	m	6		2		values are for no jump
INTO		2		2		values are for no jump
String instructions						
LODS		4	2	2		
REP LODS		5	2	2		values are per count
STOS		4	2	2		
REP STOS		2	1	1		values are per count
MOVS		7	3	3		
REP MOVS		3	1	1		values are per count
SCAS		5	2	2		
REP SCAS		5	2	2		values are per count
CMPS		7	3	3		
REP CMPS		3	1	1		values are per count
Other						
NOP (90)		1	0	1/3	ALU	
NOP (0F 1F mod000rm)		1	0	1/3	ALU	
ENTER	i,0	12		12		
LEAVE		2		3		3 ops, 5 clk if 16 bit
CLI		8-9		5		
STI		16-17		27		
CPUID		22-50	47-164			
RDTSC		30		67		
RDPNC		13		5		

15.2 Floating point x87 instructions

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move instructions						
FLD	r	1	2	1/2	FA/M	
FLD	m32/64	1	4	1/2	FANY	
FLD	m80	7	13	4		
FBLD	m80	20	94	30		
FST(P)	r	1	2	1/2	FA/M	
FST(P)	m32/64	1	2	1	FMISC	
FSTP	m80	10	8	7		
FBSTP	m80	218	167	163		
FXCH	r	1	0	1/3		
FILD	m	1	6	1	FMISC	
FIST(P)	m	1	4	1	FMISC	
FLDZ, FLD1		1		1	FMISC	
FCMOVcc	st0,r	9			FMISC, FA/M	Low latency immediately after FCOMI
FFREE	r	1		1/3	FANY	
FINCSTP, FDECSTP		1	0	1/3	FANY	
FNSTSW	AX	2		16	FMISC, ALU	Low latency immediately after FCOM FTST
FSTSW	AX	3		14	FMISC, ALU	
FNSTSW	m16	2		9	FMISC, ALU	
FNSTCW	m16	3		2	FMISC, ALU	
FLDCW	m16	12		14	FMISC, ALU	faster if unchanged
Arithmetic instructions						
FADD(P),FSUB(R)(P)	r/m	1	4	1	FADD	
FIADD,FISUB(R)	m	2		4	FADD,FMISC	
FMUL(P)	r/m	1	4	1	FMUL	
FIMUL	m	2		4	FMUL,FMISC	
FDIV(R)(P)	r/m	1	?	24	FMUL	
FIDIV(R)	m	2	31	24	FMUL,FMISC	
FABS, FCHS		1	2	2	FMUL	
FCOM(P), FUCOM(P)	r/m	1		1	FADD	
FCOMPP, FUCOMPP		1		1	FADD	
FCOMI(P)	r	1		1	FADD	
FICOM(P)	m	2		1	FADD, FMISC	
FTST		1		1	FADD	
FXAM		2		1	FMISC, ALU	
FRNDINT		6		37		
FPREM		1		7	FMUL	
FPREM1		1		7	FMUL	
Math						
FSQRT		1	35	35	FMUL	
FLDPI, etc.		1		1	FMISC	
FSIN		45	~51?			
FCOS		51	~90?			

FSINCOS		76	~125?			
FPTAN		45	~119			
FPATAN		9	151?	45?		
FSCALE		5	9	29		
FXTRACT		11	9	41		
F2XM1		8	65	30?		
FYL2X		8	13	30?		
FYL2XP1		12	114	44?		
Other						
FNOP		1	0	1/3	FANY	
(F)WAIT		1	0	1/3	ALU	
FNCLEX		8		28	FMISC	
FNINIT		26		103	FMISC	
FNSAVE	m	77	162	149		
FRSTOR	m	70	133	149		
FXSAVE	m	61	63	58		
FXRSTOR	m	85	89	79		

15.3 Integer MMX and XMM instructions

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move instructions						
MOVD	r32, mm	1	3	1	FADD	
MOVD	mm, r32	2	6	3		
MOVD	mm,m32	1	4	1/2	FANY	
MOVD	r32, xmm	1	3	1	FADD	
MOVD	xmm, r32	2	6	3		
MOVD	xmm,m32	1	2	1/2		
MOVD	m32,mm/xmm	1	2	1	FMISC	
MOVD (MOVQ)	r64,mm/xmm	1	3	1	FADD	Moves 64 bits. Name of instruction differs
MOVD (MOVQ)	mm,r64	2	6	3		
MOVD (MOVQ)	xmm,r64	2	6	3	FMUL, ALU	
MOVQ	mm,mm	1	2	1/2	FA/M	
MOVQ	xmm,xmm	1	2.5	1/3	FANY	
MOVQ	mm,m64	1	4	1/2	FANY	
MOVQ	xmm,m64	1	2	1/2	?	
MOVQ	m64,mm/xmm	1	2	1	FMISC	
MOVDQA	xmm,xmm	1	2.5	1/3	FANY	
MOVDQA	xmm,m	1	2	1/2	?	
MOVDQA	m,xmm	2	2	1	FMUL,FMISC	
MOVDQU	xmm,m	1	2	1/2		
MOVDQU	m,xmm	3	3	2		
MOVDQ2Q	mm,xmm	1	2	1/3	FANY	
MOVQ2DQ	xmm,mm	1	2	1/3	FANY	
MOVNTQ	m,mm	1		1	FMISC	
MOVNTDQ	m,xmm	2		1	FMUL,FMISC	
PACKSSWB/DW PACKUSWB	mm,r/m	1	2	1/2	FA/M	
PACKSSWB/DW PACKUSWB	xmm,r/m	1	3	1/2	FA/M	
PUNPCKH/LBW/WD/DQ	mm,r/m	1	2	1/2	FA/M	
PUNPCKH/LBW/WD/DQ	xmm,r/m	1	3	1/2	FA/M	
PUNPCKHQDQ	xmm,r/m	1	3	1/2	FA/M	
PUNPCKLQDQ	xmm,r/m	1	3	1/2	FA/M	
PSHUFD	xmm,xmm,i	1	3	1/2	FA/M	
PSHUFW	mm,mm,i	1	2	1/2	FA/M	
PSHUFL/HW	xmm,xmm,i	1	2	1/2	FA/M	
MASKMOVQ	mm,mm	32		13		
MASKMOVDQU	xmm,xmm	64		24		
PMOVBMSKB	r32,mm/xmm	1	3	1	FADD	
PEXTRW	r32,mm/xmm,i	2	6	1		
PINSRW	mm/xmm,r32,i	2	9	3	FA/M	
INSERTQ	xmm,xmm	3	6	2	FA/M	SSE4.A, AMD only
INSERTQ	xmm,xmm,i,i	3	6	2	FA/M	SSE4.A, AMD only
EXTRQ	xmm,xmm	1	2	1/2	FA/M	SSE4.A, AMD only
EXTRQ	xmm,xmm,i,i	1	2	1/2	FA/M	SSE4.A, AMD only

Arithmetic instructions						
PADDB/W/D/Q PADDSB/W ADDUSB/W PSUBB/W/D/Q PSUBSB/W PSUBUSB/W	mm/xmm,r/m	1	2	1/2	FA/M	
PCMPEQ/GT B/W/D	mm/xmm,r/m	1	2	1/2	FA/M	
PMULLW PMULHW PMULHUW PMULUDQ	mm/xmm,r/m	1	3	1	FMUL	
PMADDWD	mm/xmm,r/m	1	3	1	FMUL	
PAVGB/W	mm/xmm,r/m	1	2	1/2	FA/M	
PMIN/MAX SW/UB	mm/xmm,r/m	1	2	1/2	FA/M	
PSADBW	mm/xmm,r/m	1	3	1	FADD	
Logic						
PAND PANDN POR PXOR	mm/xmm,r/m	1	2	1/2	FA/M	
PSLL/RL W/D/Q PSRAW/D	mm,i/mm/m	1	2	1/2	FA/M	
PSLL/RL W/D/Q PSRAW/D	xmm,i/xmm/m	1	3	1/2	FA/M	
PSLLDQ, PSRLDQ	xmm,i	1	3	1/2	FA/M	
Other						
EMMS		1		1/3	FANY	

15.4 Floating point XMM instructions

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move instructions						
MOVAPS/D	r,r	1	2.5	1/2	FANY	
MOVAPS/D	r,m	1	2	1/2	?	
MOVAPS/D	m,r	2	2	1	FMUL,FMISC	
MOVUPS/D	r,r	1	2.5	1/2	FANY	
MOVUPS/D	r,m	1	2	1/2	?	
MOVUPS/D	m,r	3	3	2	FMISC	
MOVSS/D	r,r	1	2	1/2	FA/M	
MOVSS/D	r,m	1	2	1/2	?	
MOVSS/D	m,r	1	2	1	FMISC	
MOVHLPs, MOVLHPS	r,r	1	3	1/2	FA/M	
MOVHPS/D, MOVLPS/D	r,m	1	4	1/2	FA/M	
MOVHPS/D, MOVLPS/D	m,r	1		1	FMISC	
MOVNTPS/D	m,r	2		3	FMUL,FMISC	
MOVNTSS/D	m,r	1		1	FMISC	SSE4.A, AMD only
MOVMSKPS/D	r32,r	1	3	1	FADD	
SHUFPS/D	r,r/m,i	1	3	1/2	FA/M	
UNPCK H/L PS/D	r,r/m	1	3	1/2	FA/M	
Conversion						
CVTTPS2PD	r,r/m	1	2	1	FMISC	
CVTPD2PS	r,r/m	2	7	1		
CVTSD2SS	r,r/m	3	8	2		
CVTSS2SD	r,r/m	3	7	2		
CVTDQ2PS	r,r/m	1	4	1	FMISC	
CVTDQ2PD	r,r/m	1	4	1	FMISC	
CVT(T)PS2DQ	r,r/m	1	4	1	FMISC	
CVT(T)PD2DQ	r,r/m	2	7	1		
CVTP12PS	xmm,mm	2	7	1		
CVTP12PD	xmm,mm	1	4	1	FMISC	
CVT(T)PS2PI	mm,xmm	1	4	1	FMISC	
CVT(T)PD2PI	mm,xmm	2	7	1		
CVTSI2SS	xmm,r32	3	14	3		
CVTSI2SD	xmm,r32	3	14	3		
CVT(T)SD2SI	r32,xmm	2	8	1	FADD,FMISC	
CVT(T)SS2SI	r32,xmm	2	8	1	FADD,FMISC	
Arithmetic						
ADDSS/D SUBSS/D	r,r/m	1	4	1	FADD	
ADDPS/D SUBPS/D	r,r/m	1	4	1	FADD	
MULSS/D	r,r/m	1	4	1	FMUL	
MULPS/D	r,r/m	1	4	1	FMUL	
DIVSS	r,r/m	1	16	13	FMUL	
DIVPS	r,r/m	1	18	15	FMUL	
DIVSD	r,r/m	1	20	17	FMUL	
DIVPD	r,r/m	1	20	17	FMUL	

RCPSS RCPPS	r,r/m	1	3	1	FMUL	
MAXSS/D MINSS/D	r,r/m	1	2	1	FADD	
MAXPS/D MINPS/D	r,r/m	1	2	1	FADD	
CMPccSS/D	r,r/m	1	2	1	FADD	
CMPccPS/D	r,r/m	1	2	1	FADD	
COMISS/D UCOMISS/D	r,r/m	1		1	FADD	
Logic						
ANDPS/D ANDNPS/D ORPS/D XORPS/D	r,r/m	1	2	1/2	FA/M	
Math						
SQRTSS	r,r/m	1	19	16	FMUL	
SQRTPS	r,r/m	1	21	18	FMUL	
SQRTSD	r,r/m	1	27	24	FMUL	
SQRTPD	r,r/m	1	27	24	FMUL	
RSQRTSS	r,r/m	1	3	1	FMUL	
RSQRTPS	r,r/m	1	3	1	FMUL	
Other						
LDMXCSR	m	12	12	10		
STMXCSR	m	3	12	11		

15.5 3DNow instructions

These instructions are not available on Intel processors

Instruction	Operands	Ops	Latency	Reciprocal throughput	Execution unit	Notes
Move and convert instructions						
PREFETCH(W)	m	1		1/2	AGU	
PF2ID	mm,mm	1	5	1	FMISC	
PI2FD	mm,mm	1	5	1	FMISC	
PF2IW	mm,mm	1	5	1	FMISC	3DNow extension
PI2FW	mm,mm	1	5	1	FMISC	3DNow extension
PSWAPD	mm,mm	1	2	1/2	FA/M	3DNow extension
Integer instructions						
PAVGUSB	mm,mm	1	2	1/2	FA/M	
PMULHRW	mm,mm	1	3	1	FMUL	
Floating point instructions						
PFADD/SUB/SUBR	mm,mm	1	4	1	FADD	
PFCMPEQ/GE/GT	mm,mm	1	2	1	FADD	
PFMAX/MIN	mm,mm	1	2	1	FADD	
PFMUL	mm,mm	1	4	1	FMUL	
PFACC	mm,mm	1	4	1	FADD	
PFNACC, PFPNACC	mm,mm	1	4	1	FADD	3DNow extension
PFRCP	mm,mm	1	3	1	FMUL	
PFRCPIT1/2	mm,mm	1	4	1	FMUL	
PFRSQRT	mm,mm	1	3	1	FMUL	
PFRSQIT1	mm,mm	1	4	1	FMUL	

Other						
FEMMS	mm,mm	1		1/3	FANY	

Instruction set compatibility table

The following table lists which instruction sets are supported on which microprocessors. This is intended as an aid in deciding which instruction sets to use and whether to add support for older microprocessors. The different instruction sets are explained below.

Processor	Introduction year	80186	CPUID	PPro	MMX	SSE	SSE2	SSE3	Suppl. SSE3	SSE4.1	SSE4.2	32 bit	64 bit
Intel processors													
8086, 8088	1978												
80186	1982	x											
80286	1982	x											
80386	1985	x											
80486	1989	x	s										
Pentium	1993	x	x									x	
Pentium Pro	1995	x	x	x								x	
Pentium MMX	1997	x	x		x							x	
Pentium II	1997	x	x	x	x							x	
Pentium III	1999	x	x	x	x	x						x	
Pentium 4	2000	x	x	x	x	x	x					x	
Pentium 4 w. EM64T	2004	x	x	x	x	x	x	x				x	x
Pentium D	2005	x	x	x	x	x	x	x				x	x
Pentium Extreme ed.	2005	x	x	x	x	x	x	x				x	x
Celeron	1998	x	x	x	x	s	s					x	
Xeon	1998	x	x	x	x	s	s					x	
Pentium M	2003	x	x	x	x	x	x					x	
Core Solo	2006	x	x	x	x	x	x	x				x	
Core Duo	2006	x	x	x	x	x	x	x				x	
Core 2, 65 nm	2006	x	x	x	x	x	x	x	x			x	x
Core 2, 45 nm	2007	x	x	x	x	x	x	x	x	x		x	x
Core i7	2008	x	x	x	x	x	x	x	x	x	x	x	x

x = supported, s = supported in some versions.

Processor	Introduction year	80186	CPUID	PPro	MMX	SSE	SSE2	SSE3	Suppl. SSE3	3DNow	3DNowE	32 bit	64 bit
AMD processors													
Am286	1986?	x											
Am386	1991	x										x	
Am486	1993	x	s									x	
K5	1996	x	x									x	
K6	1997	x	x		x					s		x	
Athlon	1999	x	x	x	x	s				x	x	x	
Duron	2000	x	x	x	x	x				x	x	x	

Processor	Introduction year	SSE2	SSE3	Suppl. SSE3	SSE4.1/SSE4.2	AMD SSE4A	AMD XOP	32 bit	64 bit
AMD processors									
Sempron, K7	2004	s	s					x	s
Athlon 64, K8	2003	x	s					x	x
Opteron, K8	2003	x	s					x	x
K10	2007	x	x			x		x	x
?	2011	x	x	x	x	x	x	x	x

15.6 Explanation of instruction sets

The availability of a particular instruction set should be tested with the [CPUID](#) instruction, if available. The different instruction sets are explained below.

x86

This is the name of the common instruction set, supported by all processors in this lineage.

80186

This is the first extension to the x86 instruction set. New integer instructions: [PUSH i](#), [PUSHA](#), [POPA](#), [IMUL r, r, i](#), [BOUND](#), [ENTER](#), [LEAVE](#), shifts and rotates by immediate $\neq 1$.

80286

System instructions for 16-bit protected mode.

80386

The eight general purpose registers are extended from 16 to 32 bits. 32-bit addressing. 32-bit protected mode. Scaled index addressing. [MOVZX](#), [MOVSX](#), [IMUL r, r](#), [SHLD](#), [SHRD](#), [BT](#), [BTR](#), [BTS](#), [BTC](#), [BSF](#), [BSR](#), [SETcc](#).

80486

[BSWAP](#). Later versions have [CPUID](#).

x87

This is the floating point instruction set. Supported in 8086/8088 and later processors when a 8087 or later coprocessor is present. Some 486 processors and all processors since Pentium/K5 have built-in support for floating point instructions without the need for a coprocessor.

80287

[FSTSW AX](#).

80387

[FPREM1](#), [FSIN](#), [FCOS](#), [FSINCOS](#).

Pentium

[RDTSC](#), [RDPMC](#).

PPro

Conditional move ([CMOV](#), [FCMOV](#)) and fast floating point compare ([FCOMI](#)) instructions introduced in Pentium Pro. These instructions are not supported in Pentium MMX, but are supported in all processors with SSE and later.

MMX

Integer vector instructions with packed 8, 16 and 32-bit integers in the 64-bit MMX registers [MM0](#) - [MM7](#), which are aliased upon the floating point stack registers [ST\(0\)](#) - [ST\(7\)](#).

SSE

Single precision floating point scalar and vector instructions in the new 128-bit XMM registers [XMM0](#) - [XMM7](#). [PREFETCH](#), [SFENCE](#), [FXSAVE](#), [FXRSTOR](#), [MOVNTQ](#), [MOVNTPS](#). The use of XMM registers requires operating system support.

SSE2

Double precision floating point scalar and vector instructions in the 128-bit XMM registers [XMM0](#) - [XMM7](#). 64-bit integer arithmetics in the MMX registers. Integer vector instructions with packed 8, 16, 32 and 64-bit integers in the XMM registers. [MOVNTI](#), [MOVNTPD](#), [PAUSE](#), [LFENCE](#), [MFENCE](#).

SSE3

[FISTTP](#), [LDDQU](#), [MOVDDUP](#), [MOVSHDUP](#), [MOVSLDUP](#), [ADDSUBPS](#), [ADDSUPPD](#), [HADDPS](#), [HADDPD](#), [HSUBPS](#), [HSUBPD](#).

Supplementary SSE3

[PSHUFB](#), [PHADDW](#), [PHADDSW](#), [PHADDQ](#), [PMADDUBSW](#), [PHSUBW](#), [PHSUBSW](#), [PHSUBD](#), [PSIGNB](#), [PSIGNW](#), [PSIGND](#), [PMULHRSW](#), [PABSB](#), [PABSW](#), [PABSD](#), [PALIGNR](#).

MONITOR

The instructions [MONITOR](#) and [MWAIT](#) are available in some Intel and AMD multiprocessor CPUs with SSE3.

SSE4.1

[BLENDPD](#), [BLENDPS](#), [BLENDVPD](#), [BLENDVPS](#), [DPPD](#), [DPPS](#), [EXTRACTPS](#), [INSERTPS](#), [MOVNTDQA](#), [MPSADBW](#), [PACKUSDW](#), [PBLENDVB](#), [PBLENDW](#), [PCMPEQQ](#), [PEXTRB](#), [PEXTRD](#), [PEXTRQ](#), [PEXTRW](#), [PHMINPOSUW](#), [PINSRB](#), [PINSRD](#), [PINSRQ](#), [PMAXSB](#), [PMAXSD](#), [PMAXUD](#), [PMAXUW](#), [PMINSB](#), [PMINSW](#), [PMINUD](#), [PMINUW](#), [PMOVSXBD](#), [PMOVSXBQ](#), [PMOVSXBW](#), [PMOVSXWD](#), [PMOVSXWQ](#), [PMOVSXDQ](#), [PMOVZXBQ](#), [PMOVZXBW](#), [PMOVZXWD](#), [PMPVZXWQ](#), [PMOVZXDQ](#), [PMULDQ](#), [PMULLD](#), [PTEST](#), [ROUNDPD](#), [ROUNDPS](#), [ROUNDSD](#), [ROUNDSS](#).

SSE4.2 (Intel and future AMD processors)

[CRC32](#), [PCMPESTRI](#), [PCMPESTRM](#), [PCMPISTRI](#), [PCMPISTRM](#), [PCMPGTQ](#), [POPCNT](#).

AES (Future Intel and AMD)

[AESDEC](#), [AESDECLAST](#), [AESENC](#), [AESENCLAST](#), [AESIMC](#), [AESKEYGENASSIST](#).

CLMUL (Future Intel and AMD)

[PCLMULQDQ](#).

AVX (Future Intel and AMD)

The 128-bit XMM registers are extended to 256-bit YMM registers with room for further extension in the future. The use of YMM registers requires operating system support.

Almost all previous XMM instructions now have two versions: with and without zero-extension into the full YMM register. The zero-extension versions have three operands in most cases. New instructions in AVX: [VBROADCASTSS](#), [VBROADCASTSD](#), [VEXTRACTF128](#), [VINSETRF128](#), [VLDMXCSR](#), [VMASKMOVPS](#), [VMASKMOVPD](#), [VPERMILPD](#), [VPERMIL2PD](#), [VPERMILPS](#), [VPERMIL2PS](#), [VPERM2F128](#), [VSTMXCSR](#), [VZEROALL](#), [VZERoupper](#).

FMA(3) (Future Intel and perhaps AMD)

Fused multiply and add instructions: [VFMADDxxxPD](#), [VFMADDxxxPS](#), [VFMADDxxxSD](#), [VFMADDxxxSS](#), [VFMADDSUBxxxPD](#), [VFMADDSUBxxxPS](#), [VFMSUBADDxxxPD](#), [VFMSUBADDxxxPS](#), [VFMSUBxxxPD](#), [VFMSUBxxxPS](#), [VFMSUBxxxSD](#), [VFMSUBxxxSS](#), [VFNMADDxxxPD](#), [VFNMADDxxxPS](#), [VFNMADDxxxSD](#), [VFNMADDxxxSS](#), [VFNMSUBxxxPD](#), [VFNMSUBxxxPS](#), [VFNMSUBxxxSD](#), [VFNMSUBxxxSS](#).

FMA4 (Future AMD)

Same as Intel FMA, but currently specified with 4 different operands according to a preliminary Intel specification, while Intel's FMA specification has later been changed to allow only 3 different operands (FMA3). Compatibility between Intel and AMD is currently uncertain.

3DNow (AMD only)

Single precision floating point vector instructions in the 64-bit MMX registers. Only available on AMD processors. The 3DNow instructions are: [FEMMS](#), [PAVGUSB](#), [PF2ID](#), [PFACC](#), [PFADD](#), [PFCMPEQ/GT/GE](#), [PFMAX](#), [PFMIN](#), [PFRCP/IT1/IT2](#), [PFRSQRT/IT1](#), [PFSUB](#), [PFSUBR](#), [PI2FD](#), [PMULHRW](#), [PREFETCH/W](#).

3DNowE (AMD only)

[PF2IW](#), [PFNACC](#), [PFPNACC](#), [PI2FW](#), [PSWAPD](#).

SSE4.a (AMD only)

[EXTRQ](#), [INSRTQ](#), [LZCNT](#), [MOVNTSD](#), [MOVNTSS](#), [POPCNT](#). ([POPCNT](#) shared with Intel SSE4.2).

XOP (AMD only. Future)

[VCVTPH2PS](#), [VCVTPS2PH](#), [VFRCZPD](#), [VFRCZPS](#), [VFRCZSD](#), [VFRCZSS](#), [VPCMOV](#), [VPCOMB](#), [VPCOMD](#), [VPCOMQ](#), [PCOMW](#), [VPCOMUB](#), [VPCOMUD](#), [VPCOMUQ](#), [VPCOMUW](#), [VPHADDBD](#), [VPHADDBQ](#), [VPHADDBW](#), [VPHADDDQ](#), [VPHADDUBD](#), [VPHADDUBQ](#), [VPHADDUBW](#), [VPHADDUDQ](#), [VPHADDUWD](#), [VPHADDUWQ](#), [VPHADDWD](#), [VPHADDWQ](#), [VPHSUBBW](#), [VPHSUBDQ](#), [VPHSUBWD](#), [VPMACSD](#), [VPMACSDQH](#), [VPMACSDQL](#), [VPMACSSD](#), [VPMACSSDQH](#), [VPMACSSDQL](#), [VPMACSSWD](#), [VPMACSSW](#), [VPMACSWD](#), [VPMACSWW](#), [VPMADCSSWD](#), [VPMADCSDW](#), [VPPERF](#), [VPROTB](#), [VPROTD](#), [VPROTQ](#), [VPROTW](#), [VPSHAB](#), [VPSHAD](#), [VPSHAQ](#), [VPSHAW](#), [VPSHLB](#), [VPSHLD](#), [VPSHLQ](#), [VPSHLW](#).

CVT16 (AMD and Intel. Future)

[VCVTPH2PS](#), [VCVTPS2PH](#).

64 bit

This instruction set is called x86-64, x64, AMD64 or EM64T. It defines a new 64-bit mode with 64-bit addressing and the following extensions: The general purpose registers are extended to 64 bits, and the number of general purpose registers is extended from eight to sixteen. The number of [XMM](#) registers is also extended from eight to sixteen, but the number of [MMX](#) and [ST](#) registers is still eight. Data can be addressed relative to the instruction pointer. There is no way to get access to these extensions in 32-bit mode.

Instructions not available in 64 bit mode

The following instructions are not available in 64-bit mode: [PUSHA](#), [POPA](#), [BOUND](#), [INTO](#), BCD instructions: [AAA](#), [AAS](#), [DAA](#), [DAS](#), [AAD](#), [AAM](#), undocumented instructions ([SALC](#), [ICEBP](#), 82H alias for 80H opcode), [SYSENTER](#), [SYSEXIT](#), [ARPL](#). On some early Intel processors, [LAHF](#) and [SAHF](#) are not available in 64 bit mode. Increment and decrement register instructions cannot be coded in the short one-byte opcode form because these codes have been reassigned as REX prefixes.

Most instructions that involve segmentation are not available in 64 bit mode. Direct far jumps and calls are not allowed, but indirect far jumps, indirect far calls and far returns are allowed. These are used in system code for switching mode. Segment registers [DS](#), [ES](#), and [SS](#) cannot be used. [PUSH CS](#), [PUSH DS](#), [PUSH ES](#), [PUSH SS](#), [POP DS](#), [POP ES](#), [POP SS](#), [LDS](#) and [LES](#) instructions are not allowed. [CS](#), [DS](#), [ES](#) and [SS](#) prefixes are allowed but ignored. The [FS](#) and [GS](#) segments and segment prefixes are available in 64 bit mode and are used for addressing thread environment blocks and processor environment blocks.

16 Comparison of the different microprocessors

The following table summarizes some important differences between different microprocessors.

	P1	PMMX	PPro	P2	P3	P4	P4E	PM	Core2	Core i7	AMDK8	AMD K10
code cache, kb	8	16	8	16	16	≈ 64	≈ 78	32	32	32	64	64
code cache associativity, ways	2	4	4	4	4	4	8	8	8	4	2	2
data cache, kb	8	16	8	16	16	8	8-16	32	32	32	64	64
data cache associativity, ways	2	4	2	4	4	4	8	8	8	8	2	2
data cache line size	32	32	32	32	32	64	64	64	64	64	64	64
built-in level 2 cache, kb	0	0	0-512	0-512	128-512	128-512	256-2048	512-2048	2-6MB	256	512-1024	512
level 2 cache associativity, ways	0	0	4	4	8	8	8	8	16-24	8	16	16
level 2 cache bus size, bits	0	0	64	64	256	256	256	256	256		64	128
level 3 cache size	0	0	0	0	0	0	0	0	0	8MB	0	2 MB
branch target buffer entries	256	256	512	512	512	4096	4096	2048	2048	?	2048	2048
return stack buffer size	0	4	16	16	16	16	16	16	16	16	12	24
out of order execution	no	no	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes
branch prediction	poor	good	good	good	good	good	good	good	good	good	good	good
branch misprediction penalty	3-4	4-5	10-20	10-20	10-20	≥ 24	≥ 24	13	15	17	12	12
partial register stall	0	0	5	5	5	0	0	1-5	1-6	1-6	0	0
FMUL latency	3	3	5	5	5	6-7	7-8	5	5	5	4	4
IMUL latency	9	9	4	4	4	14	10-11	4	3	3	3	3

17 Literature

Intel: "Intel 64 and IA-32 Architectures Optimization Reference Manual".
developer.intel.com.

AMD: "Software Optimization Guide for AMD Family 10h Processors".
www.amd.com.

18 Copyright notice

This series of five manuals is copyrighted by Agner Fog. Public distribution and mirroring is not allowed. Non-public distribution to a limited audience for educational purposes is allowed. The code examples in these manuals can be used without restrictions. A GNU Free Documentation License shall automatically come into force when I die. See www.gnu.org/copyleft/fdl.html.